

TENDER SPECIFICATION

BHEL:PSSR:SCT: 1308

FOR

**Handling at Site Stores / Storage yard,
Transportation to site of work, Erection, Testing and
Commissioning of Electrical Package for Unit 10 of
120 MW at Nalco CPP**

At

National Aluminium Company Limited

**CPP Expansion Phase II
Angul District, Orissa state**

PART - I TECHNICAL BID

BOOK NO :



BHARAT HEAVY ELECTRICALS LIMITED

(A Government of India Undertaking)

Power Sector - Southern Region

690, Anna Salai, Nandanam, Chennai - 600 035.

INDEX SCT : 1308 - NALCO CPP ELECTRICAL PACKAGE

Sl.no	Description	Page
1	Covering Letter	1-2
2	Special instructions to Bidders	3-4
3	Procedure for submission of sealed bids	5
4	Tender Notice	6-7
5	Certificate for No Deviation	8
6	Offer of Contractor	9-10
7	Project Information	11
8	Section III - Common Conditions of Contract	12-29
9	Section VI - Special Conditions of the Contract	30-98
10	Section –VII General Technical Requirements and Guidelines for Installation, Testing, Commissioning and Supply	99-139
	SECTION - VIII	
	Appendix- I Data Sheet	140-142
	Appendix-II Declaration Sheet	143
	Appendix-III Certificate of Declaration For Confirming knowledge On site Conditions	144
	Appendix-IV Check list	145-147
	Bill of Materials for Electrical / C&I/Illumination Package	148-171
	Appendix-V Price Bid (Separate Book)	13
	General Conditions of Contract (Separate Book)	73

**BHARAT HEAVY ELECTRICALS LIMITED
(A Government of India Undertaking)
Power Sector, Southern Region
690, Anna Salai, Nandanam, Chennai - 35**

Tender Specification No. BHEL:PSSR:SCT: 1308

Messrs Date:

Dear Sir,

SUB: Handling at Site Stores / Storage yard, Transportation to site of work, Erection, Testing and Commissioning of Electrical Package for unit- 10, of 120 MW at Nalco CPP Expansion Phase II, Angul, Orissa.

Please find enclosed one set of non-transferable tender Specification along with Separate Booklets for general conditions of contract and Rate schedule for the above work.

You are requested to go through the tender documents, GCC Booklet and offer your most competitive rate and submit the tender documents duly filled in as per procedure indicated in the tender specification along with requisite EMD of Rs. 2,00,000/- (Rupees Two lakhs only) in the form Demand Draft drawn in favour of M/s.Bharat Heavy Electrical Limited Chennai - 35.

Bids with Deviations from the tender conditions will be rejected.

A SEPARATE LETTER SHALL BE FURNISHED INDICATING THAT THERE ARE NO DEVIATIONS FROM THE TENDER CONDITIONS (As in Page 8.)

The completed quotations shall reach the office of the under signed on or before **17.9.2008 at 15.00 Hrs.** The Technical bids, will be opened on the same day at **15.30 hrs.**

We shall separately intimate the date for opening the price bids only to those parties who are technically qualified. You are requested to depute your authorized representative at the time of opening.

ANY REVISION OF RATES / PRICES WHAT SO EVER AFTER THE TIME AND DATE MENTIONED IN TENDER SPECIFICATION FOR SUBMISSION OF COMPLETED QUOTATIONS SHALL NOT BE ENTERTAINED UNLESS CALLED FOR SPECIFICALLY BY BHEL.

Kindly acknowledge receipt of the tender documents and confirm your participation.

Kindly note that BHEL reserves the right to reject any or all tenders without assigning any reason.

Thanking you,

Yours faithfully,
For and on behalf of

BHARAT HEAVY ELECTRICALS LIMITED

ADDL. GENERAL MANAGER / CONTRACTS

This Tender document is not transferable.

Place : Chennai -35

Encl: One set of Tender documents along with GCC Booklet & Drawings

BHARAT HEAVY ELECTRICALS LIMITED
(A Government of India undertaking)
Power Sector : Southern Region
690, Anna Salai, Nandanam, Chennai - 600 035.

SPECIAL INSTRUCTIONS TO BIDDERS

The Bidder must submit their bids as requested in a sealed cover prominently super scribing the Tender Specification number, due date and time of submission as mentioned in the TENDER NOTICE.

The following information shall be furnished by the Bidder along with their offer (Technical Bid cover)

01. Details of previous experience during the last Seven years indicating contract value, duration, completion period and present engagement as per G.C.C.
02. Organization structure of the Company as per GCC.
03. Financial status of the firm enclosing balance sheet and profit and loss account for the past 3 years and certificate from the Company's Banker as per G.C.C
04. Turnover of the Company in last 3 Financial years pertaining to this scope of work only.
05. Latest Income Tax clearance certificate.
06. BIO DATA of key personnel presently in the Rolls of the company and proposed site organization for carrying out the work including deployment of Engineers and Supervisors.
07. Declaration sheets as per Appendix of Tender Specification.
08. Checklist and Schedule of General particulars as per Appendix in GCC.
09. T & P owned/deployment details as per G.C.C.
10. Technical manpower deployment details as per G.C.C
11. Other relevant details as per GCC and checklist.
12. These terms and conditions will be read and construed along with General Conditions of contract and incase of any conflict or inconsistency between the General conditions and the Terms and conditions of the tender specification, the provisions contained in the Term and conditions (NIT, Rate Schedule, Common conditions, Special Conditions including Appendices) shall prevail.

13. THE BIDDERS ARE REQUESTED TO FURNISH THE DOCUMENTS LIKE COPIES OF LOI'S, WORK ORDER'S ETC PERTAINING TO THE EXPERIENCE INDICATED IN QUALIFYING REQUIREMENTS, AS GIVEN BELOW.

14. Qualification Criteria

The bidder should have completed erection, testing and commissioning of HT/LT Electrical works consisting of HT oil cooled transformer of rating of min 10 MVA, HT bus ducts of rating min 3.3 KV and other related works like HT / LT cable, switch gear, trays and tray supports, etc. in the last seven years.

(OR)

The bidder should have completed erection, testing and commissioning of Total C&I systems of boiler or Turbine or station C&I and LT electrical works in a power plant of capacity min 210 MW in last seven years.

(OR)

The bidder should have completed erection, testing and commissioning of LT Electrical package comprising of bus ducts, transformers, switch gears, cables, tray work, earthing etc in a power plant of capacity min 110 MW in last seven years.

b) The bidders should have a minimum average financial turn over of **Rs. 77.00** Lakhs per year in the preceding three years ending 2007.

The bidder must have earned profit in any one of the last three financial years ending 31.03.2007 and should have positive net worth as on 31.03.2007

The bidder should submit audited balance sheet and profit and loss account of the company for the last three years ending 31.03.2007 in support of above requirement.

c) Notwithstanding the above, BHEL reserves the right to reject any Tender or all the Tenders for reasons whatsoever beyond its control and the decision of BHEL is final.

d) Approval of agency by customer.

e) LD / Penalty shall be leviable as per the applicable clauses of GCC.

15. A DECLARATION SHEET INDICATING THAT THERE IS NO DEVIATION IN TENDER DOCUMENTS (AS IN **PAGE 8) IS TO BE FURNISHED. TENDERERS MAY FURTHER NOTE THAT THIS DECLARATION IS A PREREQUISITE FOR BHEL TO CONSIDER THEIR BIDS. BIDS SUBMITTED WITHOUT "NO DEVIATION DECLARATION" WILL BE REJECTED BY BHEL.**

16. SAFETY PLAN

Bidder may further note that the submission of safety plan is a prerequisite for BHEL to consider their bids.

BHARAT HEAVY ELECTRICALS LIMITED
(A Government of India undertaking)
Power Sector : Southern Region
690, Anna Salai, Nandanam, Chennai - 600 035.

PROCEDURE FOR SUBMISSION OF SEALED BIDS

The Tenderers must submit their bids as required in two parts in separate sealed covers prominently super scribed as Part I "Technical Bid" and Part II "Price Bid" and also indicating on each of the covers the tender specification number and due date and time as mentioned in the Tender Notice.

Part I (Technical Bid) Cover I

Excepting Rate Schedule, all other schedules, data sheets and details called for in the specification shall be enclosed, in part I Technical Bid only.

Part II (Price Bid) Cover II

All indications of price shall be given in this part II Price Bid only

Tenderers are requested to quote their rates, only in the price bid (part II) provided by BHEL. Quoting of rates in any other form / formats will not be entertained.

These two separate cover I & II (Part I and Part II) shall together be enclosed in a third envelope (Cover III) along with requisite EMD as indicated and this sealed cover shall be super scribed and submitted to Addl. General Manager/Contracts at the above mentioned address before the due date as indicated. The Tenderers will be intimated separately in case clarifications are required.

NOTE:

Tenderers are issued with 2 Nos. of Technical Bids, 2 Nos. of Price Bids and 2 Nos. of GCC booklet., out of which one set of each document shall be retained by them for their reference. Balance one set shall be submitted along with their offer as per procedure indicated above.

EMD amount for this Tender is Rs.2,00,000/-(Rupees Two lakhs only). This EMD amount shall be submitted in the form demand draft only drawn in favor of M/s. Bharat Heavy Electricals Limited, Chennai - 35.

EMD amount in the form of Bank Guarantee / fixed deposit receipt or in any other form will not be Accepted.

ANY REVISION OF RATES / PRICES WHAT SO EVER AFTER THE TIME AND DATE MENTIONED IN TENDER SPECIFICATION FOR SUBMISSION OF COMPLETED QUOTATIONS SHALL NOT BE ENTERTAINED UNLESS CALLED FOR SPECIFICALLY BY BHEL.

Addl. General Manager/Contracts.

BHARAT HEAVY ELECTRICALS LIMITED
(A Government of India Undertaking)
Power Sector, Southern Region
690, Anna Salai, Nandanam, Chennai - 35

TENDER NOTICE

Sealed Tenders are invited from reputed contractors with sufficient previous experience in the under mentioned nature of work and meeting the Qualification Requirements.

Tender Specification No. BHEL:PSSR:SCT: **1308**

Description	EMD
Handling at Site Stores / Storage yard, Transportation to site of work, Erection, Testing and Commissioning of Electrical Package for unit- 10 – of 120 MW at Nalco CPP Expansion Phase II, Angul, Orissa.	Rs.2,00,000/- (Rupees Two Lakhs only)

Cost of Tender Documents (Including all Taxes)	:	Rs.1040/-	
Sale Starts on	:	27.08.2008	
Sale closes on	:	16.09.2008	
Due date and Time for Submission	:	17.09.2008	15.00 HRS
Date and time for opening Of Technical Bids	:	17.09.2008	15.30 HRS

QUALIFICATION REQUIREMENT

- a) The bidder should have completed erection, testing and commissioning of HT/LT Electrical works consisting of HT oil cooled transformer of rating of min 10 MVA, HT bus ducts of rating min 3.3 KV and other related works like HT / LT cable, switch gear, trays and tray supports, etc. in the last seven years.

(or)

The bidder should have completed erection, testing and commissioning of Total C&I systems of boiler or Turbine or station C&I and LT electrical works in a power plant of capacity min 210 MW in last seven years.

(Or)

The bidder should have completed erection, testing and commissioning of LT Electrical package comprising of bus ducts, transformers, switch gears, cables, tray work, earthing etc in a power plant of capacity min 110 MW in last seven years.

- b) The bidders should have a minimum average financial turn over of Rs.**77.00** Lakhs per year in the preceding three years ending 2007.

The bidder must have earned profit in any one of the last three financial years ending 31.03.2007 and should have positive net worth as on 31.03.2007

The bidder should submit audited balance sheet and profit and loss account of the company for the last three years ending 31.03.2007 in support of above requirement.

- c) Notwithstanding the above, BHEL reserves the right to reject any Tender or all the Tenders for reasons whatsoever beyond our control and the decision of BHEL is final.
- d) Approval of agency by customer.

Penalty shall be leviable as per the applicable clauses of GCC.

Interested parties can get the Tender documents from the office of the Additional General Manager / Contracts on all working days (except Second and last Saturdays) by remitting the cost of tender documents either by Cash (10.00 AM- 4.00 PM) or A/c Payee Demand Draft (10 AM- 4.30 PM) drawn in favour of M/s. Bharat Heavy Electricals Limited, Chennai - 600 035. Money order, Cheques and Postal Orders will not be accepted.

Bharat Heavy Electricals Limited takes no responsibility for any delay, loss or non receipt of tender documents sent by post and also reserves the right to reject any or all the tenders without assigning any reason there for.

ADDL. GENERAL MANAGER/CONTRACTS

TENDER SPECIFICATION : BHEL:PSSR:SCT:1308

CERTIFICATE FOR NO DEVIATION

I, _____ Of M/s.

hereby certify that there is no deviation from the Tender conditions either technical or commercial and I am agreeing to all the terms and conditions mentioned in the Tender Specification.

SIGNATURE OF THE TENDERER

OFFER OF CONTRACTOR

Addl. General Manager/Contracts
Bharat Heavy Electricals Limited,
Power Sector: Southern Region
690, Anna Salai,
Nandanam, Chennai - 600 035.

Sir,

I/We hereby offer to carry out the work detailed in Tender Specification No. BHEL:
PSSR: SCT: 1308 issued by Bharat Heavy Electricals Limited, Power Sector: Southern
Region, in accordance with the terms and conditions thereof.

I/We have carefully perused the following documents connected with the above work and
agree to abide by the same.

1. Instructions to Tenderer
2. General Conditions of Contract
3. Special conditions of Contract
4. Other Section, Appendices and Schedules

I/We have deposited/forwarded herewith the Earnest Money Deposit/a sum of **Rs.2,00,000/- (Rupees Two lakhs only)** vide DD No. _____ Dt. _____ which shall be refunded should our offer not be accepted. Should our offer be accepted, I/We further agree to deposit such additional sum which along with the sum of **Rs.2,00,000/- (Rupees Two lakhs only)** mentioned above, to make up the Security Deposit for the work as provided for in the Tender Specification within the stipulated time as may be indicated by BHEL, Power Sector : Southern Region, Chennai - 600 035.

I/We further agree to execute all the works referred to in the said documents upon the terms and conditions obtained or referred to therein and as detailed in the appendices annexed thereto.

DATE:

CONTRACTOR:

PLACE:

ADDRESS:

Witness with their address

Signature

Name

Address

PROJECT INFORMATION

1.0 PROJECT:

- Customer :** M/s NATIONAL ALUMINIUM COMPANY LTD
(A Government of India Enterprise)
**NALCO BHAVAN , NAYAPALLI,
BHUBANESHWAR 751 013**
- Project Site :** NALCO CAPTIVE POWER PLANT EXPANSION
UNIT NO. 9 & 10 AT ANGUL , ORISSA STATE
- Location -** Angul in Orissa about 3 Km on the north of the
junction of the National Highways Nos 42 and 43 and
just by the side of NH42.

2.0 CLIMATIC CONDITIONS

The following site conditions shall be considered for the purpose of design and selection of equipment and materials:

Temperature

Dry Bulb Temperature	27.7° C (Mean)
Dry Bulb Temperature	31.6°C (Max)
Wet Bulb Temperature	23.8° C (Mean)
Wet Bulb Temperature	27.2°C (Max)
Extreme Lowest Temperature	27.7°C (Mean)
Extreme Maximum temperature	46.7° C
Maximum ambient temperature	41.6° C
Minimum ambient temperature	10.8° C
Rainfall Maximum Monthly rainfall	649.9 mm (October)
Average minimum rainfall	678.5 mm (2002)
Average annual rainfall	1700 mm
Relative Humidity- Maximum	84 %
Minimum	57 %
Wind	
Wind Load	55 m/sec
Predominant Wind direction	South-west to North-East South to North
Seismic Zone	Zone III, as per IS - 1893
Plant Elevation	65 m above mean seal level

SECTION III

COMMON CONDITIONS OF CONTRACT

3.1 SCOPE OF CONTRACT

- 3.1.1 The Intent of this specification is to provide erection and commissioning services for execution of projects according to most modern and proven techniques and codes. The omission of specific reference to any method and equipment or material necessary for the proper and efficient services towards installation of the Plant shall not relieve the contractor of the responsibility of providing such services, facilities to complete the project or portion of project awarded to him. The quoted rate shall deem to be inclusive of all such contingencies.
- 3.1.2 The contractor shall carry out the work in accordance with Instructions/drawings / specification / standard practices supplied by BHEL from time to time.
- 3.1.3 Provisions of all types of labour, Supervisors, Engineers watch and ward as required tools and tackles as required consumables as required under various clauses of tender specification for handling, transportation, erection testing and commissioning.
- 3.1.4 Proper out-turn as per BHEL plan and commitment.
- 3.1.5 Completion of work in time.
- 3.1.6 Good quality and accurate workmanship for proper performance of equipment/systems.
- 3.1.7 Preservation of all components at all stages of pre-assembly / erection / testing and commissioning till unit is handed over as specified in detail in clause.

3.2.0 FACILITIES TO BE PROVIDED BY BHEL:

3.2.1 OPEN SPACE

Minimum Open space for building of 1 No temporary office / store shed will be provided free of charges. Contractor has to make his own arrangements for labour colony, including Electricity and water for the labour colony.

3.2.2 ELECTRICITY

For construction purpose and for contractor's office and store sheds electricity **will be provided at one single point on chargeable basis**, as provided by Nalco. The current rate is around **Rs.2.85/-** per KVA which shall be subject to variation as applicable from time to time. Further distribution shall be arranged by the contractor at his own cost including supply of energy meter with calibration certificate.

BHEL is not responsible for any loss or damage to the contractors equipment as a result of variations in voltage / frequency or interruptions in power supply.

Before connecting any equipment the contractor shall ensure that it is rated for the correct voltage to which it is being connected and the equipment is not likely to cause a fuse blow out.

The contractor shall endeavour to minimize the current consumption as far as possible and avoid wastage.

3.2.3 WATER

For construction purpose, water will be provided at one point free of cost nearer to the project site. Further distribution shall be arranged by the contractor at his own cost. For drinking purpose the contractor has to make his own arrangement at his cost.

3.2.4 TOOL AND TACKLES

All the Tools & Plants and instruments required for the complete erection of components shall be arranged by the contractor.

3.2.5 CONSUMABLES

All consumables, electrodes including Oxygen/ Acetylene, Argon , Gases, paints etc., shall be arranged by the contractor at his own cost.

3.3.0 FACILITIES TO BE PROVIDED AND DEVELOPED BY THE CONTRACTOR AT HIS COST.

3.3.1 CIVIL CONSTRUCTION

It shall be the responsibility of the contractor to construct his own office shed, stores shed with all facilities like electricity, water supply, sanitary arrangements in the area allotted to him for this purpose.

3.3.2 WATER DISTRIBUTION

Distribution of water for various work fronts from the single point shall be arranged by the contractor at his cost.

3.3.3 ELECTRICITY DISTRIBUTION

Distribution of electrical power from the given single central common point to the required places with proper distribution boards, approved cable and cable laying including, supply of all materials like cables, switch boards, pipes etc. Observing the safety rules laid down by electrical authority of the State / BHEL / their customer with appropriate statutory requirements shall be the responsibility of the tenderer / contractor. Any duty, deposit involved in getting the electricity shall be borne by the bidder. As regards contractor's office shed also all such expenditure shall be borne by the contractor. Necessary meters for recording consumption of power for cost calculation purpose and maintenance of the same during execution period shall be contractor's responsibility.

3.3.4 POSSESSION OF GENERATORS

As there are bound to be interruptions in regular power supply power cut/load shedding in any construction site due to inherent power shortage in State, suitable extension of time if found necessary only be given on this account and Contractor is not entitled for any compensation. It shall be the responsibility of the tenderer / contractor to provide maintain the complete installation on the load side of the supply with due regard to safety requirements at site. The contractor shall adjust his working shifts accordingly and deploy additional manpower, if necessary to achieve the target.

3.3.5 LIGHTING FACILITIES

Adequate lighting facilities such as flood lamps, low volt hand lamps and Area lighting shall be arranged by the contractor at the site of construction, contractor's material storage area etc, at his cost.

3.3.6 POWER REQUIREMENT

For the purpose of planning, contractor shall furnish along with tender the estimated requirement of power (month wise) for execution of work in terms of maximum KW demand.

3.3.7 CONTRACTOR'S OBLIGATION ON COMPLETION

On completion of work all the temporary buildings, structures, pipelines, cable etc. shall be dismantled and levelled and debris shall be removed as per instruction of BHEL, by the Contractor at his cost. In the event of his failure to do so BHEL will undertake such work and the cost of the same will be recovered from the Contractor including overhead charges. The decision of BHEL. Engineer in this regard is final.

3.4.0 GASES

- 3.4.1 All required gases like Oxygen / acetylene / argon / Nitrogen required for work shall be supplied by the Contractor at his cost. It shall be the responsibility of the contractor to plan the activities and store sufficient quantity of those gases. Non-availability of gases cannot be considered as reason for not attaining the required progress of erection.
- 3.4.2 BHEL reserves the right to reject the use of any gas in case required purity is not maintained.
- 3.4.3 The contractor shall submit weekly / fortnightly / monthly statement report regarding consumption all consumables for cost analysis purposes.
- 3.4.4 The contractor shall ensure safe keeping of the inflammable cylinder at a separate place away from normal habit with proper security etc.
- 3.4.5 The contractor shall arrange air/gas manifold ensuring proper distribution and reduction of handling time.

3.5.0 ELECTRODES & FILLER WIRES

- 3.5.1 All required electrodes shall be arranged by contractor at his cost. It shall be the responsibility of the contractor to obtain prior approval of BHEL, before procurement regarding suppliers, type of electrodes etc. On receipt of the electrodes at site, it shall be subject to inspection and approval of BHEL. The contractor shall inform BHEL details regarding type of electrodes, batch number and date of expiry.
- 3.5.2 Storage of electrodes shall be done in an air conditioned / controlled humidity room as per requirement, at his own cost by the contractor.
- 3.5.3 All low hydrogen electrodes shall be baked / dried in the electrode drying oven (range 375 deg. C - 425 deg. C) to the temperature and period specified by the BHEL Engineer before they are used in erection work and each HP elder should be provided with one portable electrode drying oven at the work spot. Electrode drying oven and portable drying ovens shall be provided by contractor at his cost.
- 3.5.4 In case of improper arrangement of procurement of above electrodes BHEL reserve the right to procure the same from any source and recover the cost from the contractor's first, subsequent bill at market value plus departmental charges of BHEL. Postponement of such recovery is not permissible.
- 3.5.5 BHEL reserves the right to reject the use of any electrodes at any stage if found defective because of bad quality, improper storage, date of expiry, unapproved type of electrodes etc. It shall be the responsibility of the contractor to replace at his cost without loss of time.

3.6.0 TOOLS & TACKLES

- 3.6.1 All T & P required for the satisfactory execution of work shall be arranged by contractor at his cost.
- 3.6.2 All instruments, measuring tools etc., are to be calibrated periodically as per the requirement of BHEL and necessary calibration certificates are to be submitted to BHEL before use.
- 3.6.3 All the T & P, lifting tackles including wire ropes, slings shackles and electrically operated equipment shall be got approved by BHEL engineer before they are actually put on use. Test certificates should be submitted before their usage.
- 3.6.4 All the T & P arranged by contractor including electrical connections wherein required shall be reliable / proven / tested and necessary test certificate to be submitted as per statutory rules of the State / Central Government in force from time to time.
- 3.6.5 For the movement of cranes etc., it may become necessary to lay sleeper bed for obtaining leveled safe approach for usage of equipment. It shall be the contractor's responsibility to lay necessary sleepers. Required sleepers shall be arranged by the contractor at his cost.

3.7.0 SUPERVISORY STAFF AND WORKMEN

- 3.7.1 The Contractor shall supply all the skilled workmen like Welders, Gas cutters, electricians, Riggers, Serangs, Erectors, carpenters, fitters etc. in addition to other skilled, semi-skilled and unskilled workmen required for all the works of handling and transportation from site stores/storage yard to erection site, transportation, erection, testing and commissioning contemplated under this specification. Only fully trained and competent men with previous experience on the job shall be employed. They shall hold valid certificates wherever necessary.

BHEL reserves the right to decide on the suitability of the workers and other personnel who will be employed by the contractor, BHEL reserves right to insist on removal of any employee of the contractor at any time, if they find him unsuitable and the contractor shall forthwith remove him.

- 3.7.2 The supervisory staff employed by the contractor shall be qualified (Engineers - Graduates in Engineering and Supervisors - Diploma Holders) and experienced in the area of work. They shall ensure proper out-turn of work and discipline on the part of labour put on the job by the contractor and in general see that the works are carried out in safe and proper manner and in coordination with other labour and staff employed directly by BHEL or BHEL's client.

- 3.7.3 The Contractor shall furnish daily labour report showing by classification the number of employees engaged in various categories of work and a progress report of work as required by BHEL Engineer. The contractor shall also give a summary report at the end of the month and plan of deployment for the consequent month as per the plan of activities as required by BHEL, to meet the overall contract requirement.
- 3.7.4 The work shall be executed under the usual conditions existing in major power plant construction and in conjunction with numerous other operations at site. The bidder and his personnel shall co-operate with other personnel and other contractor's personnel working in site and proceed in a manner that shall not delay or hinder the progress of work as a whole.
- 3.7.5 The contractor's supervisory staff shall execute the work in the most substantial and workman like manner in the stipulated time. Accuracy of work, good workmanship and aesthetic finish are essential part of this contract. The contractor shall be responsible to ensure that assembly and workmanship conform to the dimensions and tolerances given in the drawings/instructions given by BHEL Engineers from time to time. Wherever finish or tolerances are not specified in drawings/documents, BHEL Engineers instruction are taken as final.
- 3.7.6 The contractor shall employ the necessary number of qualified and approved full time electricians at his cost to maintain his temporary electrical installation till the completion of work.
- 3.7.7 It is the responsibility of the bidder to engage his workmen in shifts or on overtime basis during erection, commissioning and testing period for achieving the target set by BHEL. The contractor's quoted rate shall include all these contingencies.
- 3.7.8 If the contractor or his workmen or employees shall break, deface, injure or destroy any part of a building, road, kerb, fence, enclosure, water pipes, cables, drains, electric or telephone posts or wires, trees or any other property or to any part of the erected components etc. The contractor shall make the same good at his own expense or in default, BHEL may cause the same to be made good by other workmen or by other means and deduct the expenses (of which BHEL's decision is final) from any money due to the contractor.

3.8.0 CIVIL WORKS

- 3.8.1 Foundations of all equipments and plants and necessary civil works shall be provided by BHEL. The dimensions of the foundation and anchor bolt pits shall be checked by the contractor for their correctness as per drawings. Further top elevation of foundations shall be checked with respect to bench mark etc. All minor adjustments upto 25 mm of foundation level, dressing, chipping of foundation surface enlarging the pockets in foundations and grouting of equipments etc. as may be required for the erection of equipment/plants shall be carried out by the Contractor. All the materials like cement, sand, gravel etc. and cleaning consumables shall also be arranged by the contractor at his

cost. The required special cement like CONBEXTRA-GP2 and SHRINKOMP N 30 etc or its equivalent grade cement for grouting of columns, equipments etc. shall be arranged by the contractor at their cost. The contractor should also arrange required nos. of mixing machines and vibrators at their cost.

- 3.8.2 The contractor shall ensure perfect matching of packer plates with foundation by dressing the foundation and between the packer plates and the base plate of structural column/equipment to the satisfaction of BHEL Engineer. Machining/matching of packer shall be carried out by the Contractor at his own cost.
- 3.8.3 The contractor shall arrange for grouting of foundation bolt holes of equipment and final grouting of equipment as per the drawings / specification or as advised by the Engineer or BHEL after preparing the foundation surface for grouting.
- 3.8.4 Contractor has to carry out the grouting as per the work instructions for grouting available at site.
- 3.8.5 The contractor at his cost shall arrange for grouting of anchor points of T & P issued to him and also grouting of winches or any other supports required for T & Ps. Necessary grout materials are to be arranged by the contractor at his cost.

3.9.0 SCOPE OF MATERIAL HANDLING AND SITE STORAGE AND OTHER RESPONSIBILITIES

- 3.9.1 While BHEL will endeavour to store/stack/identify materials properly in their open/closed storage yard/shed it shall be contractor's responsibility to assist BHEL in identifying materials well in time for erection, taking delivery of the same in time following the procedure indicated by BHEL and transport the material safely to pre-assembly yard/erection site in time according to programme.
- 3.9.2 The contractor shall identify necessary supervisor/labour for the above work in sufficient quantity as may be needed by BHEL for areas covering their scope.
- 3.9.3 It shall be contractor's responsibility to arrange necessary cranes/tractors, trailer or trucks/slings/tools and tackles/labour including operators Fuel lubricants etc., for loading from storage yard and on to transport equipment, move it to erection site/pre-assembly yard and unload the same at pre-assembly yard/ erection site and the quoted rate shall include the same.
- 3.9.4 All equipment so used by contractor shall be of proven quality and safe in operation as approved by BHEL site Engineers from time to time.

- 3.9.5. Any loss/damage to materials issued to contractor shall be made good by him or BHEL will arrange for replacement at cost recovery basis and decision of BHEL shall be final.
- 3.9.6 All the surplus, damaged, unused materials, package materials/containers/special transporting frames, gunny bags etc. supplied by BHEL shall be returned to the BHEL Stores by the contractor and maintain records.
- 3.9.7 The contractor shall take delivery of the components and equipments and special consumables from the storage area after getting the approval of the BHEL Engineer on standard indent forms to be specified by BHEL. At periodic/intervals of work, complete and detailed account of the equipment so erected and electrodes used shall be submitted to the BHEL Engineer.
- 3.9.8 The contractor shall submit monthly plan for erection and the same will be mutually agreed upon after discussion. The contractor shall arrange for Engineers, Supervisors and labour force and tools and plants and consumables to suit the above plan and execute the work accordingly.
- 3.9.9 The Contractor shall have total responsibility for all equipment and materials in his custody, stores, loose, semi-assembled, assembled or erected by him at site.
- 3.9.10 The contractor shall make suitable security arrangement including employment of security personnel to ensure the protection of all materials/equipments and works from theft, fire, pilferage and any other damage and loss.
- 3.9.11 The contractor shall ensure that the packing materials and protection devices used for the various equipments during transit and storage are removed before these equipments are installed.
- 3.9.12 All equipments shall be handled very carefully to prevent any damage or loss. No bare wire ropes, slings etc. shall be used for unloading and / or handling of the equipments without the specific written permission of the Engineer. The equipments from the storage yard shall be moved to the actual site of erection / location at the appropriate time as per the direction of BHEL Engineer so as to avoid damage for such equipments at site.
- 3.9.13 The work covered under this scope of work is of highly sophisticated nature requiring best quality / precision workmanship engineering and construction management. He should also ensure successful and timely commercial operation of equipment installed. The contractor must have adequate quantity of precision tools, construction aids in possession. Contractor must also have adequate trained qualified and experienced supervisory staff and skilled personnel.
- 3.9.14 All the necessary certificates and licenses required to carry out this scope of work are to arranged by the contractor then and there at no extra cost.

- 3.9.15 The contractor shall take all reasonable care to protect the materials and work till such time the erected equipment has been taken over by BHEL/their client. Wherever necessary suitable temporary fencing and lighting shall have to be provided by the contractor as a safety measure against accident and damage of property of BHEL. Suitable caution notices shall be displayed where access to any part may be deemed to be unsafe and hazardous.
- 3.9.16 The contractor shall be responsible for taking all safety precautions during the construction and keeping the site safe at all times. When the work is temporarily suspended he shall protect all construction materials, equipments and facilities from causing damage to existing property interfering with the operations of the station when it goes into services. The contractor shall comply with all applicable provisions of the safety regulations clean-up programme and other precautionary measures which the BHEL has in effect at the site.
- 3.9.17 All lifting tackles including wire ropes, slings, shackles etc. used by the contractor shall be got approved by BHEL Engineer at site before they are actually put on the work. It will be the responsibility of the contractor to ensure safe lifting of the equipment taking due precautions to avoid any accidents and damage to other equipments and personnel. All piping shall be adequately supported and protected to prevent damage during handling and erection. The history cards for major equipments to be maintained by the contractor.
- 3.9.18 The contractor shall take delivery of equipment from storage yard/stores/sheds. He shall also make arrangements for verification of equipment, maintain records and keep safe custody, watch and ward of equipment after it has been handed over to him till these are fully erected, tested and commissioned and taken over by BHEL's client. The stolen/lost/damaged goods shall have to be made good by the contractor at his own cost.
- 3.9.19 Sometimes it may become necessary for the contractor to handle certain unrequired components in order to take out the required materials. The contractor has to take this contingency also into account. No extra payment is payable for such contingencies.

3.10.0 PRESERVATION OF COMPONENTS

- 3.10.1 It shall be the responsibility of the contractor to apply preservative painting on all equipment before erection. It shall be contractor's responsibility to arrange for required labour, brush and other consumables like cotton waste, cloth etc. for carrying out preservative painting. The quoted rates shall be inclusive of above work. The required paint and thinner shall be arranged by the contractor at his cost.
- 3.10.2 The contractor shall effectively protect the finished work from action of weather and from damage or defacement and shall cover the finished parts, then and there for their protection.

- 3.10.3 Any failure on the part of contractor to carry out work according to above clauses will entail BHEL to carry out the job from any other party and recover the cost from contractor.
- 3.10.4 Due to atmospheric conditions erected materials are likely to get rusted more frequently. It is the responsibility of the contractor to preserve the erection materials drawn from stores for erection till these are commissioned and handed over to customer. The required paint and thinner shall be provided by BHEL free of cost. All other consumables like painting brush, emery paper, cotton waste, cloth etc. have to be arranged by the contractor at his cost. The contractor should ensure that the materials are not rusted on any account till they are handed over to customer. The decision of the BHEL Engineer is final with regard to frequency of application of paint.

3.11.0 DRAWINGS AND DOCUMENTS

- 3.11.1 The detailed drawing specification available with BHEL Engineers will form part of this tender specification. These documents will be made available to the contractor during execution of work at site.
- 3.11.2 One set of necessary drawings to carry out the erection work will be furnished to the contractor by BHEL on loan which shall be returned to BHEL Engineer at site after completion of work. Contractor's personnel shall take care of these documents given to them.
- 3.11.3 The data furnished in various appendices enclosed with this Tender Specification, describes the equipment to be installed, tested and commissioned under this specification briefly. However, the changes in the design and in the quantity may be expected to occur as is usual in any such large scales of work.
- 3.11.4 Should any error or ambiguity be discovered in the specification, or information, the contractor shall forthwith bring the same to the notice of BHEL before commencement of work. BHEL's interpretation in such cases shall be final and binding on the contractor.
- 3.11.5 Deviation from design dimensions should not exceed permissible limit. The contractor shall not correct or alter any dimensions/details without specific approval of BHEL.

3.12.0 SITE CLEANLINESS AND SAFETY REQUIREMENTS

- 3.12.1 Contractor shall strictly follow all safety regulations/conditions as per clause 2.15 and its sub clauses of general conditions of contract booklet enclosed with this tender, including specification of Health, Safety and Environment (HSE) management of customer / consultant.

- 3.12.2 Non-conformity of safety rules and safety appliances will be viewed seriously and the BHEL has right to impose fines on the contractor as under:

SNo	Safety	Fine (Rs)
01	Not wearing safety helmet	50/-
02	Not wearing safety belt	100/-
03	Grinding without goggles	50/-
04	Not using 24V supply for internal work	500/-
05	Electrical plugs not used for hand machines	100/-
06	Not slinging properly	200/-
07	Using damaged sling	200/-
08	Lifting cylinders without cage	500/-
09	Not using proper welding cable with lot of joints and not insulated properly	200/-
10	Not removing small scrap from platforms	200/-
11	Gas cutting without taking proper precaution or not using sheet below gas cutting	200/-
12	Not maintaining elec. winches which are being operated dangerously	500/-
13	Improper earthing of electrical T & Ps	500/-

- 3.12.3 The contractor should exclusively deploy one safety Engineer along with a safety supervisor for effective implementation and co-ordination of safe working conditions.

- 3.12.4 Contractor shall necessarily fill up the safety plan format available in general conditions of contract book let enclosed with this tender and submit along with their offer.

3.13.0 PROGRESS OF WORK

- 3.13.1 During the course of erection if the progress is found unsatisfactory or if the target dates fixed from time to time for every milestone are to be advanced or in the opinion of BHEL, if it is found that the skilled workmen like fitters, operators, technicians etc. employed are not sufficient, BHEL will induct required additional workmen to improve the progress or take over a part of the job and get it done on risk and cost of the contractor and recover from contractor's bill, all charges incurred on this account including all expenses together with BHEL overheads from contractor's bill.

- 3.13.2 The contractor shall submit daily, weekly and monthly progress reports, manpower reports, material reports, consumables reports and other reports considered necessary by the BHEL Engineer.
- The manpower reports shall clearly indicate the manpower deployed category wise daily specifying also the activities in which they are engaged.
- 3.13.3 The progress reports shall indicate the progress achieved against planned with reasons indicating delays if any and shall give remedial action which the contractor intends to make good the slippage or lost time so that further works can proceed as per the original programme and the slippage do not accumulate and affect the overall programme in a format designed and approved by BHEL site engineer.
- 3.13.4 The contractor shall arrange for weekly progress review meeting with the "Engineers" at site during which actual progress during the week vis-à-vis scheduled programme shall be discussed for action to be taken for achieving targets. The programme for subsequent work shall also be presented by contractor for discussion. The contractor shall constantly update/revise his work programme to meet the overall requirements and suit the material availability.
- 3.13.5 The contractor shall arrange for submitting three sets of progress photographs every month to BHEL office the areas to be photographed will be as per the instruction of BHEL Engineer. The quoted rate shall include this contingency.
- 3.13.6 The contractor must obtain the signature and permission of the security personnel of the customer for bringing any of their materials inside the site premises, without the Entry Gate Pass these materials will not be allowed to be taken outside.
- 3.13.7 The contractor shall maintain a record in the form as prescribed by BHEL for all operations carried out on each weld and maintain a record indicating the number of welds, the name of welders who welded the same, date and time of start and completion, preheat temperature, radiographic results, rejections, if any, percentage of rejection, etc. and submit copies of the same to BHEL Engineer, as required.

SPECIFIC REQUIREMENTS FOR ISO 9001 - 2000

3.14.0 IMPORTANT NOTE

Contractors shall ensure that all their Staff/Employees are exposed to periodical training programme conducted by qualified agencies/ personnel on ISO 9002 Standards.

Contractors shall ensure that the Quality is maintained in all the works connected with this contract at all stages of the requirement of BHEL.

Contractor shall ensure that all Inspection, Measuring and Testing equipment that are used, whether owned by the contractor or used on loan, are calibrated by the authorized agencies and the valid calibration certificate will be available with them for verification by BHEL. A list of such instruments possessed by contractor at site with its calibration status is to be submitted to BHEL Engineer for control.

Contractors shall arrange for the inspection of the works at various stages as required by BHEL. Immediate corrective action shall be taken by the contractor for the non-conformances if any, observed and pointed out by BHEL.

3.15.0 INSPECTION / QUALITY ASSURANCE / QUALITY CONTROL STATUTORY INSPECTION

- 3.15.1 Various Inspection / quality control / quality assurance procedures/methods at various stages of erection and commissioning will be as per BHEL / Customer quality control procedure/codes/IBR and other statutory provisions and as per BHEL Engineer's instructions.
- 3.15.2 Preparation of quality assurance log sheets and protocols with customer's Engineers, welding logs and other quality control and quality assurance documentation as per BHEL Engineer's Instructions, is within the scope of work / specification.
- 3.15.3 The protocols between contractor and customer/BHEL shall be made prior to installation for correctness of foundations, materials, procedures, at each stage of Installation, generally as per the requirement of Customer/BHEL. This is necessary to ensure elimination of errors or keeping them within tolerable limits and to avoid accumulation and multiplication of errors.
- 3.15.4 A Daily log Book should be maintained by every supervisor/Engineer of contractor on the job in Duplicate (One for BHEL and one for Contractor) for detailing and incorporating Alignment/clearance/centering/ Leveling Readings and Inspection details.
- 3.15.5 Approval Given by Customer/BHEL for welding, results tests etc. shall also be recorded in the log book.
- 3.15.6 All the Electrical/Technical Measuring and Testing Instruments / Gauges, Feeler Gauges, Height Gauges, Dial Gauges, Micrometers, Levels, Spirit Levels, Surface plates, straight Edges, vernier calipers and all measuring instruments shall be provided by the contractor for checking, Levelling, Alignment,

centering etc of Erected Equipments at various stages. The Instruments/gauges/Tools etc. provided should be of Brand, Quality and Accuracy, Specified by BHEL Engineer and should have necessary calibration and other certificates as per the Requirements of BHEL Engineer.

- 3.15.7 Total Quality is the Watch Ward of the work and standards, Procedures laid down by BHEL. We shall follow all the Instructions as per BHEL Drawings and Quality / Standards. Contractor shall provide for the services of quality Assurance Engineer.

3.16.0 STAGE INSPECTION BY FES / QA ENGINEERS

- 3.16.1 Apart from Day-to-Day Inspection by BHEL Engineers Stationed at site and also by Customer's Engineers, Stage Inspection of Equipment under Erection and commissioning at various stages of Erection and commissioning by TEAMS of Engineers, from Field Engineering Services of BHEL's Manufacturing units and Quality Assurance Teams from Field Quality Assurance Unit/ Factory Quality Assurance and commissioning Engineers. Contractor shall arrange all labour, Tools and Tackles, etc. for such stage inspections free of cost.
- 3.16.2 Any modifications suggested by FES and QA Engineers Team shall be carried out. Claims of Contractor, if any shall be dealt as applicable.
- 3.16.3 Any minor rectifications of minor repairs of defective work found out during stage Inspection shall be rectified free of cost, by the contractor.
- 3.16.4 Any major Rectification or Major Repair / Major Rework of Defective work found out during stage Inspection verification / checking, But not attributable to contractor shall also be carried out. Claims of contractor if any, shall be dealt as applicable.

3.17.0 STATUTORY INSPECTION

The scope includes getting the Approvals from the statutory authorities (Like Electrical Inspector and Labour Officers). This includes Arranging for Inspection Visits of Inspector Periodically as per BHEL Engineer's Instructions, Submitting Documents, Radiographs, Etc. and following up the matter with them.

All fees connected with the contractors for Testing his Welders/Men / Works and Testing, Inspection, calibrating his instruments and equipments, shall be paid by the contractor. It shall be contractor's responsibility to obtain approval of Statutory Authorities, Wherever Applicable, for the conducting of Any work which comes under the Purview of these Authorities. Any cost arising from this shall be contractor's Account.

However, BHEL shall pay all other Fees (FEES FOR VISITS, INSPECTION FEES, REGISTRATION FEES, ETC.) In case these Inspection have to be Repeated due to Default/Fault of the Contractor and Fees have to be paid again, the Contractor shall have to Bear the charges. These would be Deducted from his Bills.

3.18 HSE SPECIFIC REQUIREMENT

OCCUPATIONAL HEALTH & SAFETY MANAGEMENT SYSTEM

SUB CONTRACTOR TO ENSURE COMPLIANCE OF THE FOLLOWING HEALTH RELATED POINTS

01. Sub-contractor to identify nearest hospital for Health check up of his staff and workers and intimate BHEL site office & PSSR HQ.
02. To arrange for occupational health check up / screening of contractor's staff and workers engaged in sub contracting activities. In this, category of workmen such as welders, gas cutters, grinders, radiographers, crane operators are to be given exclusive attention in respect of health screening.
03. **Sub-contractor to arrange an ambulance vehicle or emergency vehicle on a continuous basis to meet any emergency situation arising at site work in which his staff and workers are engaged.**
04. To provide appropriate facilities for prompt first aid treatment of injuries and illness at work. One first Aider for each sub contractor to be provided. First Aider should undergo training on first aid.
05. To provide filtered drinking water at selected place in a clean container.

SUB CONTRACTOR TO ENSURE COMPLIANCE OF THE FOLLOWING SAFETY RELATED POINTS

01. Personnel protective equipment (PPES): Required number of following PPES (Confirming to Relevant is Standards) to be made available to workmen at site and ensured that they are used
 - ❖ Helmet
 - ❖ Safety goggles
 - ❖ Welding face shields
 - ❖ Safety belts for working at heights ☉ Safety shoes
 - ❖ Ear plugs
 - ❖ Rubber gloves and mats for low tension (I.T) electrical works
 - ❖ Gum boots & aprons
 - ❖ Other items as required by BHEL site
02. Sub contractor to liaise with nearest fire station and inform contact telephone number and contact person to meet any emergency.
03. To provide appropriate fire fighting equipment at designated work place and to provide fire fighting training to selected persons in his group of workmen to meet emergencies.

04. To provide adequate number of 24 V power supply points to work in a constrained and enclosed space.
05. All power tapping points / switch boards /power & control cabling should fulfil required electrical safety aspects as per relevant BIS standard.
06. ELCH's (Earth leak circuit breakers) at all electrical distribution points to be provided.
07. Red and white caution tape of proper width (1.5 to 2 inch) to be used for cordoning unsafe area such as open trench, excavated area, etc.
08. To provide sub-contractors company logo or clothing to all staff and workers for identification including identity cards with photographs approved by BHEL.
09. High pressure and structural welders to be identified with colour clothing and to display copy of welders certificate with photographs of welder at the work place. They also should be in possession of valid welding procedure.
10. To display safe handling procedure for all chemicals such as lube oil, grease, sealing compound, kerosene, diesel etc. At stores & respective work place.
11. Contractor should authorise a person at site to stop work if there is a unsafe work noticed as per his knowledge.
12. Fitness for use of erected scaffolding to be certified by the contractors approved scaffolder and the certificate should be displayed on the scaffolding itself. If the scaffolding is unsafe, the same will not be used. the certificate to be updated daily. The scaffolding to be made as per the relevant is standard.
13. For making platform on the scaffolding, proper thickness and size of the plank of required quality wood to be used. The safe working load of the platform to be displayed on the scaffolding itself. Proper use of platform to be explained to the user.
14. All plant equipment should have inspection report before put in to use.
15. All T&Ps should be of reputed brand and having quality certificates..
16. All IMTEs should have valid calibration certificate from recommended institution / testing lab and these should be in place.
17. All lifting tackle and plant equipment should have safe working load certificate.
18. The right worker should be deployed for right job and the resume of site in charge, supervisors, and key workers to be submitted before commencement of work.
19. Sub-contractor should submit inspection / testing matrix of all T&Ps and to be approved by BHEL.

20. Sub-contractor to display safety slogan, safety board, caution boards wherever required in consultation with BHEL.
21. Sub-contractor to provide gas detectors of reputed make at desired locations.
22. Sub-contractor to conduct emergency mock drills. one drill per 6 month and submit report to BHEL.
23. Safe handling and storing of all equipment with adequate space to be ensured.
24. Sub contractor to deploy safety supervisor till the completion of the project.
25. Sub contractor to comply the safety reporting procedure of BHEL as practiced at present and also additional requirements that may arise out of future improvements in the safety management system. This includes computation of safety indices such as frequency rate, severity rate & incident rate.
26. Sub contractor to identify probable emergency situations such as electric shocks to workmen , caving in of shored earth , fall from height, collapse of scaffolding fire etc., and should have clear action plan to overcome them. Sub contractor to take required guidance from BHEL in this regard.
27. Sub contractor to identify hazardous activities which he may carryout and should train his workmen in those activities with the relevant operation control procedures. Sub contractor to take required guidance from BHEL in this regard.
28. Safe work permit system to be followed while working in confined space / near electric systems.

SUB CONTRACTOR TO ENSURE COMPLIANCE OF THE FOLLOWING ENVIRONMENT RELATED POINTS

1. HOUSE KEEPING : Sub contractor to carry out daily house keeping of work areas / stores through a check list prepared in consultation with BHEL.
2. Sub contractor shall adopt pollution prevention / reduce /control approach in all his site activities. this shall include:
 - a. Transporting of oil / chemicals from stores to site safely without causing spillage. In case of any spillage, the area shall be cleaned and the remnant spilled oil disposed off to a safe place, identified for such disposal.
 - b. To use required containers / cans / safety gadgets /appliances for transporting and for usage of oil / chemicals at site.
3. Sub contractor shall arrange for segregation / collection of scraps and dispose off to the identified place meant for scrap collection.
4. Sub contractor to adopt good erection practices / procedures with the objective of reduction of waste generation / rework

OTHER HSE REQUIREMENTS TO BE COMPLIED BY SUB CONTRACTOR

1. Sub contractor to clearly understand and accept the HCE policy of PSSR with a commitment to comply the requirements of the policy.
2. Sub contractors to arrange for daily meeting of their supervisors and work force before they disperse for their daily planned activities where in the relevant health, safety and environment aspects of the job and use of PPES are explained
3. Sub contractor to conduct monthly HSE meeting (internal) and submit the report to BHEL.
4. HSE slogans to be displayed in a proper board - hoarding at designated places in consultation with BHEL.
5. Sub contractor to submit a structured programme for training & occupational Health Screening of their work force at site after the Award of LOI.

**SCT 1308 SECTION – VI
INDEX**

6.1.0	Scope of work
6.2.0	Electrical - General
6.3.0	Detailed Scope of work
6.3.1	Transformers
6.3.2	Isolated Phase Bus Duct
6.3.3	LT MCC & Power Distribution Boards
6.3.4	AVR/Generator Control /Relay Panel/Other Panels
6.3.5	Battery & Battery Charger
6.3.6	Diesel Generator set
6.3.7	Ash Level Indicator
6.3.8	Heating Elements
6.3.9	(Not Applicable)
6.3.10	Cables
6.3.11	Cable Trays/Conduits/Flexi Conduits
6.3.12	Junction Box, Marshalling Box & PB Box
6.3.13	Fabrication and Erection of Steel Materials
6.3.14	Above Ground Earthing & Lightning Protection
6.3.15	Painting
6.3.16	Civil Works
6.3.17	Calibration
6.3.18	Commissioning of Equipments Erected by Mech Contractor
6.3.19	Pre Commissioning, Commissioning and Post Commissioning
6.4.0	Time Schedule
6.5.0	Over Run Charges
6.6.0	Measurement, Wastage & Cutting Allowances
6.7.0	Collection of Materials
6.8.0	Storage
6.9.0	Tools & Plants to be arranged by Contractor
6.10.0	Materials / Consumables to be arranged by Contractor

SCT – 1308 SECTION VI
INDEX

6.11.0	Technical requirements for Supply Items
6.12.0	Terms of Payment
6.13.0	Guarantee
6.14.0	Electrical Inspectorates Approval
6.15.0	Price Variation Clause
6.16.0	Taxes & Duties
6.17.0	Provident Fund and Minimum wages
6.18.0	Important Conditions for payment
6.19.0	Other Statutory requirements
6.20.0	e-Remittance
6.21.0	(Not Applicable)
6.22.0	Progress & Monitoring of works
6.23.0	Extra work charges for Modification
6.24.0	Reporting Damages and carrying out repairs
6.25.0	Inspection of works
6.26.0	Details to be provided by Vendor
6.27.0	Documentation
6.28.0	Recommended List of T&P / Instruments by Contractor
6.29.0	Recommended list of T&P Instruments for Electrical works
6.30.0	Drawings for reference
VI A	Month-wise Manpower Deployment
VI B	Deployment Plan for major T&P
VI C	Calibration Record-Format

SECTION VI
NALCO ANGUL CPP EXPANSION 2 X 210 MW (UNIT - 10)
ELECTRICAL PACKAGE
SCOPE OF WORK AND SPECIAL CONDITIONS

6.1.0 SCOPE OF WORK:

The scope of work shall comprise but not limited to the following:

- 6.1.0 Identification of equipment at storage yard, technical assistance for checking and making the shortage/damage reports, taking delivery at stores/ storage yard, transportation to erection site and pre-assembly of equipment wherever required, checking, erection testing, commissioning along with the supply of all consumables, tools and tackles, testing instruments as per BHEL Engineer's instruction/ supervision and providing assistance for troubleshooting, trial operation and maintenance of the complete equipment and materials enumerated in the rate schedule of this tender till handing over to customer or till completion of the contract period which ever is earlier.
- 6.1.1 It is not the intent to specify herein all details of equipment and material. Any Electrical item related to this work, that is necessary to complete the system shall be deemed to have been included in the scope of the work, even if not covered by this.
- 6.1.2 All the work shall be carried out as per instructions of BHEL engineer. BHEL engineer's decision regarding the correctness of the work and method of working shall be final and binding on the contractor.
- 6.1.3 Contractor shall erect all items/materials etc. as per sequence prescribed by BHEL at site. BHEL engineer depending upon the availability of materials/work fronts etc will decide the sequence of erection/commissioning methodology. No claims for extra payment from the contractor will be entertained on the grounds of deviation from the methods of erection/commissioning adopted in erection/commissioning of similar job or for any reasons whatsoever.
- 6.1.4 After completing all the works, contractor shall hand over all remaining extra materials with proper identification tags in packed condition to BHEL stores. In case of any use over actual design requirements, BHEL reserves the right to recover the cost of material used in excess or misused. Decision of BHEL engineer in this regard will be final and binding on the contractor.

- 6.1.5 The contractor shall ensure that his premises are always kept clean and tidy to the extent possible. Any untidiness noted on the part of the contractor shall be brought to the attention of the contractor's site representative who shall take immediate action to clean the surroundings to the satisfaction of the Engineer-in-Charge
- 6.1.6 All the surplus, damaged, unused materials, package materials, containers, special transporting frames, etc. shall be returned to the BHEL stores / customer's stores by the contractor.
- 6.1.7 The work shall be executed under the usual conditions without affecting power plant construction and in conjunction with other operations and other agencies at site. The contractor and his personnel shall co-operate with the personnel of other agencies, co-ordinate his work with others and proceed in a manner that shall not delay or hinder the progress of work as a whole.
- 6.1.8 Contractor shall remove all scrap materials periodically generated from his working area in and around power station and collect the same at one place earmarked for the same. Loads of scrap is to be shifted to a place earmarked by BHEL. Failure to collect the scrap is likely to lead to accidents and as such BHEL reserves the right to collect and remove the scrap at contractor's risk and cost if there is any failure on the part of contractor in this respect. All the package materials, including special transporting frames, etc. shall be returned to the BHEL stores / customer's stores by the contractor.
- 6.1.9 Any wrong erection shall be removed and re-erected promptly to comply with the design requirements to the satisfaction of Site Engineer.
- 6.1.10 The contractor shall take delivery of item, materials, from the storage yard / stores / sheds of BHEL / customer which is within a radius of 5 kms. He shall also make arrangements for safe custody, watch and ward of equipment after it has been handed over to him till they are fully erected, tested and commissioned till the contract period. The contractor shall note that items/materials shall be transported to erection site / assembly yard etc. by the prescribed route without disturbing and causing damage to other works in the most professional manner. All items, Hardware, etc. shall be stored in appropriate manner as per BHEL's instructions.
- 6.1.11 The contractor shall take delivery of items/materials, and consumables from the stores/ storage area / sheds of BHEL / customer after getting approval of engineer / customer in the prescribed indent forms of BHEL / customer.

- 6.1.12 Contractor shall, transport all materials to site and unload at site / working area, or pre-assembly yard for inspection and checking. All material handling equipment required shall be arranged by the contractor.
- 6.1.13 The contractor at his cost shall arrange necessary security measures for adequate protection of his machinery, equipment, tools, materials etc. BHEL shall not be responsible for any loss or damage to the contractor's construction equipment and materials. The contractor may consult the Engineer-in-Charge on the arrangements made for general site security for protection of his machinery equipment tools etc.
- 6.1.14 During the course of erection, testing and commissioning of Electrical works, certain rework/modification / rectification / repairs / fabrication etc. may be necessary on account of feedback from other power stations that are already commissioned or under erection or due to change in design or manufacturing defects or to meet operational / maintenance requirements. Contractor shall carry out above such rework promptly and expeditiously, subject to extra works clause.
- 6.1.15 Site testing wherever required shall be carried out for all items/materials installed by the contractor to ensure proper installation and functioning in accordance with drawings, specifications and manufacturer's recommendations.
- 6.1.16 The contractor shall co-ordinate and provide assistance for satisfactory testing, pre-commissioning, commissioning and trial run of the connected equipment to meet the system requirement and customer satisfaction.
- 6.1.17 Contractor shall retain all T&P/Testing instrument/Material handling instrument etc at site as per advice of BHEL engineer and same shall be taken out from site only after getting the clearances from engineer in charge
- 6.1.18 All necessary certificates and licenses required to carry out this work are to be arranged by the contractor expeditiously at his cost.
- 6.1.19 Scope of work covered under this specification requires quality workmanship, engineering and construction management. The contractor shall ensure timely completion of work. The contractor shall have adequate tools, measuring instruments, calibrating equipment etc. in his possession. He shall also have adequate trained, qualified and experienced engineers, supervisory staff and skilled personnel. The manpower deployed by contractor shall match with above scope of works
- 6.1.20 The scope of specification covers the installation, testing and providing assistance for commissioning of the instrument, hardware along with accessories as detailed in Bill of Materials.

- 6.1.21 If any Electrical equipment or item not covered, but requires to be erected/commissioned, same shall be carried out by the contractor. Equivalent unit rate for those items or equipment shall be considered from the Rate Schedule.
- 6.1.22 The contractor shall have valid ELECTRICAL LICENSE to carry out the Electrical Works. All the necessary certificates and licenses required to carryout this work are to be arranged by the contractor expeditiously at his cost.
- 6.1.23 The installation of all the electrical equipments/items shall conform to the technical requirements specified elsewhere in the tender. The contractor shall arrange statutory inspection and obtain necessary certificate for the installation work at his cost. Any modification work required by inspector shall be attended by the contractor at his cost.
- 6.1.24 MANPOWER REQUIREMENT FOR ERECTION.

Manpower requirement for Erection and Commissioning shall as follows:

There shall be a Resident manager as Site In Charge, under whom there shall be 3 erection engineers who shall be in charge of TRANSFORMER&BUSDUCT, SWITCHGEAR&CONTROL PANELS AND CABLES.

Each area engineer shall be provided with minimum four supervisors and adequate number of Technicians/electricians and other erection staff and T&P etc. The testing Engineers/supervisors/electricians shall be identified separately for each package and the minimum requirement shall be as indicated in the relevant Clause. Besides, there shall be separate engineers for Planning, Safety and Quality.

The Site in charge shall be provided with PC and good communication facilities like telephone, fax, email etc. at the cost and expense of the contractor. Lack of communication facilities shall not be an excuse for extension of completion date.

All instructions from BHEL/Customer shall be directed to the contractor through the Site in-charge and he shall be responsible for all the contractor's activities at site. The contractor shall name his authorized representative prior to or immediately on commencement of operations at site.

The Site In charge shall be present at site during all normal working hours and his contact address after normal working hours shall be made available to BHEL so that if any emergency arises, the presence of the contractor's site Representative at site can be called for.

The contractor shall not change the site Representative without the consent of BHEL. Should BHEL require the replacement of the contractor's site Representative for justifiable reasons (including inadequate progress of work) the contractor shall ensure that replacement is made as soon as possible and work is not allowed to suffer delay on this account.

- 6.1.25 The contractor shall provide to the satisfaction of BHEL sufficient and qualified staff for the execution of works. If and whenever any of the contractor's staff is found guilty of any misconduct or be incompetent or insufficiently qualified in the performance of his duties the contractor shall remove them from site as directed by Site Engineer.
- 6.1.26 The contractor shall ensure that all his supervisor's staff and workmen conduct themselves in a proper manner. They shall all be persons who are familiar with and skilled at the jobs allocated to them. Any misconduct / inefficiency noted on the part of the contractor's personnel shall be brought to the attention of the contractor's site representative who shall immediately take such action as necessary including the removal of such misconducting / inefficient persons, if so required by the Engineer-in-Charge.
- 6.1.27 The contractor shall ensure that replacement for such persons removed from site are provided immediately and the work is not allowed to suffer delay on that account.
- 6.1.28 The quantity of various instruments/ hardwares indicated in the BOQ is approximate only. Payments shall be made on unit rate basis.
- 6.1.29** Unit rate quoted on lump sum basis shall include installation of all loose items which are not explicitly mentioned, but comes as part of the system, integration of total system and commissioning. No separate rate shall be payable for loose items. The quantities of loose supplied items are approximate only. No proportional rate will be applicable for any variation in quantity or for any additional items supplied as part of equipments.
- 6.1.30** The scope of work in general covers loading from store, transportation, unloading at site , keeping in safe custody, erection, testing and commissioning along with supply of consumables as detailed in the respective clause, deployment of skilled / unskilled manpower, engineers / supervisors, T & P, Testing instruments and handing over.

6.2.0 SCOPE OF WORK IN GENERAL

Scope of Electrical works covered in this tender are as follows:

- 6.2.0 Erection and commissioning of Generator and Unit Auxiliary Transformers.
- 6.2.1 Erection and commissioning of IP Bus Ducts.
- 6.2.2 Erection and commissioning of LT MCC, AC/DC Distribution Boards, Starter Panels, Excitation Panels, Control Panels etc.
- 6.2.3 Erection and commissioning of Generator and Transformer protection Panels and other Electrical protection and control panels
- 6.2.4 Erection and commissioning of Battery & Battery Charger panels.
- 6.2.5 Erection and commissioning of Diesel Generator.
- 6.2.6 Erection of Trays & accessories and Trays supports.
- 6.2.7 Installation of local push button stations, local starter, Junction Boxes etc.
- 6.2.8 Laying and termination of HT/ LT power and control cables
- 6.2.9 Supply and Installation of lugs, ferrules, tag plates, and cable dressing materials and installation of cables glands.
- 6.2.10 Supply and Installation of items for below ground cable installation like cable markers, cable joint markers etc. (if applicable)
- 6.2.11 Installation of above ground earthing grid, equipment earthing of all equipment, cable racks, trays etc and supply and installation of test pits.
- 6.2.12 Installation of Lightning protection.
- 6.2.13 Fabrication and installation steel supports wherever required.
- 6.2.14 Testing and Commissioning of HT/ LT-drives, MOVs and electrically operated equipment erected by Mechanical contractor.
- 6.2.15 Installation of other items that have not been specifically indicated, but required for completing installation.
- 6.2.16 Supply of paints and painting of all steel fabricated items.
- 6.2.17 Excavation of earth in any type of soil and refilling earth (if applicable)
- 6.2.18 Supply of river bed sand and spreading (if applicable).
- 6.2.19 Supply and Erection of RCC Hume pipes (if applicable).
- 6.2.20 Supply of standard Bricks and spreading (if applicable).

6.3.0 DETAILED SCOPE OF WORK

6.3.1. TRANSFORMERS

6.3.1.1 SCOPE OF WORK AND SPECIFICATION OF TRANSFORMERS

The scope of Transformer covers E&C of Generator and Unit Auxiliary Transformers and commissioning of ESP rectifier Transformer. Generator and Unit auxiliary Transformers shall be located adjacent to the powerhouse building in the transformer yard. ESP Transformer shall be erected by Mechanical contractor at ESP roof and commissioning of Transformer only is in the scope of work.

A) Technical details of 150MVA Generator Transformer:

Description: The Generator Transformer shall be of 150 MVA, 10.5/235 kV, Three phase, OFAF cooled, YNd1, with loose accessories like 2 Nos. of Radiator banks, on load tap changers, HV/LV/HVN bushings, bushing CTs, Turrets, conservators, cooler control cabinet, marshalling box, pipings, common KIOSK etc. Loose items like raise/lower P.Bs, tap changer indicators, fascia windows, W.T.I. repeaters, buzzers, signal lamps,

Accessories: PRV-1, Drain valve2, Cooler control cabinet-1, inlet-2 & out let valves-1 (1 each), 36kv22kVpost insulator-3 4, 17.5kv, 1000A bushing -2 (HV bushing-3),

Conservator: Main conservator tank with air cell, bucholz relay, breather & connected pipelines

Cooling system: Radiator assembly -24, Header -4, A frame support-4, Fan motor-10, Oilpump-4, Turret and bushing: HV line 3& neutral bushing1each, LV bushing -3,HV turret 3, LV turret - 1, valves and fittings as per drg no 3 459 00 00241

Approximate dimensions of each transformer: (l x b x h)

- a) Shipping dimensions: 7900 x 3400 x 3800 mm 7170 x 3450 x 3450 mm
- b) Overall dimensions : 15,000 x 10,500 x 7000 mm

Approximate weight of Transformer Components

a) Tank & fittings	43,000
b) Total wt of transformer	1,83,000
c) Untanking Weight	10,000
d) Shipping weight (gas filled)	1,20,000
e) Total oil (49,440 lts)	44,000

QUANTITY **2 Nos**

B) Technical details of 16MVA UAT Transformer:

Description: UAT shall be of 16 MVA 10.5 / 6.9 kV, 3 Phase, ONAN, with OLTC on HV Side with bushing CTs, radiators, cooling fans, conservator, cooler control panel, marshalling panels, piping etc. including NGR.

Loose items: like raise/lower P.Bs, tap changer indicators, fascia windows, W.T.I. repeaters, buzzers, signal lamps, etc. will be supplied loose, to be mounted and wired in control panel.

Approximate Dimensions : (mm)

- a) Overall dimension: 7700 x 6800 x 5000 mm
- b) Shipping. dimension 4400 x 2900 x 3250 mm

Weight of Transformer Components: (Kg)

- a) Tank & fittings 14,800
- b) Total wt of transformer 46,600
- c) Untanking Weight 17,800
- d) Shipping weight (gas filled) 25,000
- e) Total oil (15700 lts) 14,000

QUANTITY 2 Nos.

C) NEUTRAL GROUNDING RESISTOR

Neutral Grounding Resistor (NGR), Indoor Type, 6.9Kv, 9.95 ohms, 400A with mounting and connected accessories

Size: 1200 x1200 mm

Total Weight (NGR+ Support structure): 600 kg

6.3.1.2 SCOPE OF WORK OF TRANSFORMER

1. Receipt of Transformer and associated loose supplied accessories & Spares including oil in drums from site store/ yard, inspection, transporting the above to the respective erection location up to plinth, storage, maintenance of N2 gas pressure in transformer tank, erection of Transformer and all the accessories including NGR, cabling from transformer accessories to marshalling KIOSK & OLTC panel, oil filling, oil pressure testing, dry out, pre-commissioning test, commissioning of equipment and final painting and handing over.

2. Generator and UAT Transformer shall be dispatched to site in several packages which shall be transported from BHEL storage yard in a suitable trailer to their respective locations. Before loading and transporting the Transformers, contractor shall study the soil condition and identify route for transportation.
3. The contractor shall unload the transformers on rails, turn the wheels/ rollers if necessary, roll the transformers to their respective locations and position them on the foundation. The necessary sleepers, winches, jacks, trailer, etc. required for this operation shall be arranged by the contractor at his cost.
4. Samples of each and every drum of Transformer oil shall be tested and pre-treated to achieve the desired value before filling in to the transformer tank. The entire arrangement for testing the oil sample, filtering whenever required to achieve the desired PPM, BDV within the shortest time shall be made by the contractor at his cost, in consultation with BHEL Engineers at site. All the test equipment for testing specific gravity, PPM, BDV of the oil including testing equipment required for the Tan-Delta Test of the transformer winding and HV Bushing shall be arranged by the contractor. Testing instruments for Dew measurement of N₂ gas, if required, shall also be arranged by the contractor.
5. All the transformers protective system such as Buchholz relay, explosion vent, oil and winding temperature detectors etc., shall be checked under the guidance of BHEL Engineer.
6. Contractor shall carry out all tests with his own testing equipments and testing team.
7. If the charging of Transformers is delayed after filtration, the contractor shall carry out filtration again if necessary before charging the transformers at the discretion of BHEL Engineer in charge without any additional cost. However if the charging of Transformers got delayed after filtration beyond 6 months due to any unforeseen reasons, the filtration shall be carried out at extra cost as per provisional rate quoted and agreed upon.
8. All the T&P, material handling equipment like cranes, Trailer, Transformer oil filtering machines, 5 kV motorized megger and oil tank of suitable capacity shall be arranged by the contractor at his cost. The transformers may have to be suitably lagged/covered during the drying out operation by the contractor at no extra cost.
9. The contractor shall arrange minimum one No. 6000 litre/hour for mineral oil and one number 1000-600 L/H filtering machines for silicon oil for ESP Transformer.

10. The contractor shall engage his men on three-shift operation during drying out of the transformers.
11. The auxiliaries components of the above transformers are to be cleaned and checked before the assembly as instructed by BHEL Engineer.
12. Test value of dielectric strength/PPM, specific gravity and Tan-Delta test shall be as per recommended value of BHEL. If the test results are not satisfactory and if the customer desires to carry out the tests through some other agency, the same shall be carried out at contractor's cost.
13. The scope of erection work includes **final painting for all the oil filled Transformers**, minor civil work such as chipping and grouting of the support structure as well as for the support of the transformer, including supply of grouting material. The scope of final painting involves supply of paints, thinner and other consumables at the cost of the contractor. No separate rate shall be paid for painting. Painting shall be as per details given in the painting clause.
14. During the oil circulation of the transformer, the contractor shall employ sufficient number of personnel who shall take care of the operation of the filter machine as well as safety of the transformer.
15. Calibration of Testing equipment: All testing equipment (IMTE) shall be calibrated before putting into service at site. A copy of calibration certificate to be this effect shall be furnished to BHEL-Engineer for his verification and approval.
16. The contractor shall prepare all log sheets, test certificates, protocols etc. as per field quality plan, get it signed by concerned BHEL/CUSTOMER Engineer and submit to the concerned BHEL Engineer.
17. Preservative gas like N₂ shall be supplied by BHEL free of cost to maintain the N₂ pressure during preservation.
18. The contractor shall provide assistance to maintain the equipment erected and commissioned by him until taken over by CUSTOMER or up to the contract period.
19. ESP transformers will be erected by the mechanical contractor. Testing and commissioning of ESP Transformer alone is covered in Electrical contractor's scope.
20. For scope of work for ESP Transformer, refer Clause 6.13.8.2

6.3.2. ISOLATED PHASE BUSDUCTS

The isolated phase busducts is connected to the low voltage side of the generator transformer and generator. The bus consists of cylindrical/octagonal conductor made of Aluminium alloy supported on post insulators. Flexible connections and expansions joints are provided at terminal and intermediate points to alleviate stresses due to expansion and to arrest vibration. All the CTs shall be mounted inside the busducts.

Isolated phase taps connect the potential transformer, surge protection equipment and unit transformer to the main bus. Each phase of protection equipment and potential transformers shall be housed in metal clad cubicles.

A totally enclosed neutral grounding cubicle is provided to connect the Generator neutral point. The neutral grounding cubicle shall be at 5Mtrs level which houses neutral grounding transformer & resistors. All the generator-isolated busducts are supplied with one set of Air pressurization equipment unit.

The tentative details are as under:

6.3.2.1 Technical Details

1.	Rated working voltage at 50 Hz	10.5 KV
2.	Highest system voltage	12 KV
3.	Basic impulse level	75 KV PEAK (1.2/50 micro-sec wave)
4.	Short time current rating (rms)	85 KA for 3 Sec. (Main Run) 152 KA for 3 sec. (Tap-off Run)
5.	Continuous current rating Within busduct under the site conditions	10000 A (Main Run), 1000 A (Tap -off Run)
6.	Busbar	
a)	Material and grade	Al Alloy
	i) Main Run	Gr-19501
	ii) Tap Off Run	Gr-63401
b)	Shape & Size	
	i) Main Run	Round 450 O/D,15TK
	ii) Tap Off Run	Square-2x152.4,8.1TK

7.	Enclosure	
a)	Material	Al Alloy
	i) Main Run	Gr 19500,
	ii) Tap Off Run	Gr 31000,
b)	Shape& Size	Main: 1000 O/D,6.35 TK Tap off : 780 O/D,4.78 TK
8	Type of cooling	Air Natural
9	Type of busbar joints	Bolted (silver plated)
10	Applicable standard	IS: 8084
11	Degree of protection	Air and water tightness as per Appendix 'F' of IS: 8084
12	Neutral grounding transformer	
	i) Type	Epoxy cast Resin dry type
	ii) Transformer Rating	
	Primary Voltage	10.5 KV
	Secondary Voltage	240 V
	Phase	Single
13	Neutral grounding resistor	
	a) Type	S.S. Punched Grid Type
	b) Voltage	240
	c) Resistance	0.477 Ohms
	d) Current	400 Amps for 5 minutes duty cycle.
14	No. of Rubber Bellows (Approx.)	12 Nos
15	No. of Seal off bushing	3Nos
16	Weight of duct (Approx.) including inside mounting arrangement.	Main: 200 kg /Mtrs, Tap off :140 kg /Mtrs Top camber: 3000Kg(Total) Star Duct:1500 Kg(Total)
17	Max length of busduct	6Mtrs
18	Max weight of busduct	1200 Kg(approx)

6.3.2.2 Welding:

There will be make-up pieces supplied in two halves (one plain and another with window). Most shipping section (assembly of enclosure & conductor) will have conductor projected outside. When two adjacent shipping sections are erected the two conductors will be welded together. The enclosures shall be joined through make-up pieces which will be overlapping 25 mm. on both sides. The two halves of the make-up pieces shall then be welded. All the terminal ducts shall be having bolted connections with rubber bellow and copper connection for conductor termination. No. of rubber bellows and flexible connections are indicated above as well as in the layout drawing.

Recommended welding electrodes and procedure for welding:

The material grade, thickness and other specification have been given in the technical data sheet above. On this basis, welding electrodes, welding procedure shall be decided at site in consultation with BHEL welding Engineer.

6.3.2.3 Shorting Bars

One set of shorting bar common for both the sets shall be supplied for generator dryout.

6.3.2.4 LA VT Cubicle

LA & VT Cubicle shall be of draw out type with VT mounted on trolleys, fabricated out of 3 mm thick steel sheet, complete with illuminating lamps, space heater, busbars, mounting insulators, marshalling box, etc. The cubicle shall be selfsupporting type. Each set shall comprise of the following:

- | | |
|---|-----------------------|
| a. Single phase epoxy cast dry type VT | 09 Nos. |
| b. Lightning Arrestor (KV, KA) | 03 Nos. |
| c. Surge Capacitor (28 KV, 0.125 micro Farad) | 03 Nos. |
| d. Weight of the cubicle | 1000kg |
| e. Overall dim : | 900 x 2250 x 2400 mm. |
| f. Degree of protection | IP54 |
| g. LAVT Cubicle: | 3 Nos. |

6.3.2.5 NG Cubicle

NG Cubicle shall be fabricated out of 3 mm thick steel sheet complete with illuminating lamps, space heater, busbars, mounting insulators, marshalling box, etc. The cubicle shall be self-supporting type and degree of protection shall be IP54/IP23. Each cubicle shall house the following:

a. Dry type epoxy cast NG transformer 1 No.

(35 KVA (cont), 10.5 KV/240 V; 1 ←, Class of Insulation: B)

b. NG Resistor (240 V, 400 A (for 5 min), 0.477 ohms)

NG Cubicle: 2000 x 1250 x 1690 mm; 1400 kg approx.

6.3.2.6 Busduct Supporting Structure.

Busduct supporting structure shall be fabricated from standard steel sections welded/bolted and hot dip galvanized. All structure hardware shall be HTS hot dipped/electro-galvanized.

Weight of structure: 3.5 MT

6.3.2.7 Hot Air Blowing equipment (HAB)

HAB equipment consisting of Blower with Heater box, Centrifugal Fan. Drive Motor, Filter box, Tem indicator and manometer, Flexible pipe, Control panel and other loose supplied items.

Capacity: 6000 cum/ hour, Approx size: 1500 x 1200 x 1500 mm

6.3.2.8 Scope of works for Busducts

1. The scope of works of bus duct covers receipt from BHEL stores/yards, transportation, unloading all the busduct materials and accessories and equipment at the area where the busducts are to be erected, inspection, installation of all the materials as indicated in the BOM and relevant drawings, testing and commissioning of total busduct items, painting and handing over.
2. Dimensions & weights indicated in the Tender specification and BOQ for isolated phase bus ducts are approximate only. The relevant drawings are enclosed for the purpose of detailed study and quoting. The contractor has to ascertain the quantum of work involved and quote the lump sum value for IP Bus ducts as called for in the rate schedule.
3. There may be variations in the weight and dimensions of Busducts with respect to the drawings furnished due to revisions. Any such variation in Busduct length within $\pm 20\%$ shall not be considered for payment. However, for variations in Busduct length beyond $\pm 20\%$, payment shall be considered proportionally. Variations in size of enclosure/ conductors or weight including support structure shall not be considered for payment.

Detailed scope of work for busducts shall be as below:

4. Cleaning of enclosure and conductors, insulators and other panels before assembly and erection.
5. Placement of embedment and erection and alignment of steel support structures.

6. Assembly and checking of busduct at ground level if necessary.
7. Fixing of wall bushings/wall frame assembly
8. Minor civil work such as chipping and grouting of bus duct support structures including supply of grouting materials.
9. Providing earthing connections as per site conditions.
10. Earthing of Busducts and connecting to earth grid /earth pits as detailed in the relevant bus duct drawings.
11. If any modification is required in the support structures due to site conditions, the same shall be carried out without any extra cost.
12. Pockets will be provided during casting in which anchor bolts will be grouted for supporting the structures.
13. Extension of embedment if required and erection of required supports structures as detailed in the drawing.
14. Tightening of all bolts in the joints and flanges by torque wrench to the approved pressure (Anti oxidation compound shall be used for joints which shall be arranged by contractor)
15. Fixing of Space Heaters and wiring from Space Heaters terminal to junction box, taking through rigid/flexible conduit pipe
16. Fixing of Breather wherever required
17. Erection and commissioning of NGT cubicle with all its accessories if supplied as loose.
18. Fixing of neutral side flexible connections to generator and positioning of neutral CTs after testing.
19. Erection and commissioning of LAVT cubicles and its loose equipment/items such as lightning arrestors, voltage transformers, fuses, etc.
20. Erection and alignment of Tap off busducts for unit auxiliary transformer, LAVT cubicle, excitation transformer etc.
21. Erection and commissioning of Air Blower/drier equipment with all the accessories.
22. Carrying out Aluminium welding for bus conductor and on enclosure as detailed in the drawing using MIG/TIG machine with the Aluminium filler wire as per BHEL specification.

23. Supply of MIG/TIG welding machine, Aluminium filler wire, Argon gas of high purity and other required consumables as per BHEL standard for efficient aluminum welding,
24. covering supporting insulators with asbestos cloth whenever aluminum welding is carried out near the supporting insulator.
25. Making necessary modifications of make up pieces, if required, and welding of isolated phase busducts along with NGT, LAVT cubicle, UAT, Excitation transformer tap-offs.
26. Providing well-experienced Aluminium welder to be arranged to meet the radiography quality.
27. Conducting 10% radiography and LPT
28. Grouting the ground bus provided on the entire length of entire length of busducts, all parts of supporting structures and one end of each enclosure.
29. Conducting air-tightness test after erection to meet the requirement of BHEL/Customer Standards. Rectification of leakage, if any without any extra charges- For air tightness test, contractor shall arrange necessary pipe, PVC, hoses, fitting, valve, pressure regulator, rotameter etc. at their cost. Contractors shall tap the air from nearest Instruments air tapping point available at site. The contractor shall prepare detailed test procedure for the above and get it approved by BHEL.
30. Conducting high voltage test, short circuit test and other tests as detailed in Section VII for IP bus ducts as per instruction of BHEL engineer after cleaning inside as well as outside of the busduct & arranging all testing equipment required for carrying out busduct testing.
31. Fixing of Current transformers in busducts including wiring from CT terminal to junction box/Marshalling box, taking through rigid/flexible conduit pipe.
- 32. Carrying out final painting as per the standard color codes recommended by BHEL including supply of paints, thinner and other consumables etc. as required as part of erection. (For more details, refer scope of painting).**
33. Carrying out minor repair, rectification of enclosure/conductors, wherever required.
34. Arranging all T&P, material handling equipment required for erection.
35. Arranging all Testing instruments, which have been calibrated
36. Furnishing copy of the calibration certificate to the concerned BHEL Engineer for verification and approval.

37. Submitting necessary log sheets, protocols, test certificate as per Field Quality Plan and getting them signed by BHEL/Customer Engineers, and submitting the same to BHEL.
38. Other requirement for Erection/Commissioning of IP Busducts.
 - a. Aluminium welders shall appear for test as directed by the BHEL welding Engineer and only test qualified welders shall be permitted to do the welding.
 - b. For MIG/TIG welding only high purity argon gas shall be used. If the contractor is unable to arrange the required high purity Argon gas, the same shall be arranged by BHEL on chargeable basis. The cost of gas shall be recovered from the running bills as per BHEL norms.
 - c. Aluminium filler wire/rod shall be procured in consultation with BHEL Welding Engineer from approved Vendors of BHEL.
 - d. Make up pieces shall be supplied along with bus ducts. Necessary MIG/TIG welding of different sections of enclosures, make up pieces and bus shall be carried out at site.
 - e. Holes on the flanges/Flexible may not be adequate or may not match and any additional holes, if required, shall be drilled at site to facilitate matching of busduct enclosure flanges including generator flange.
 - f. Matching and connecting the Busduct with other equipment erected by other agencies shall be included in the scope.
 - g. The contractor shall carry out testing and commissioning works with their own testing equipments and Testing teams and should not engage outside agency for testing. Testing shall be done under the supervision of BHEL/CUSTOMER Engineers.

6.3.3. SCOPE OF LT MCC AND POWER DISTRIBUTION BOARDS.

1. LT MCCs are simple module type with isolators and fuses. However, some of the MCCs are Double Front draw out type consisting of circuit breakers unit, contactors/starter fuse switch units, MCB etc. arranged in multi-tier construction.
2. AC/DC Distribution Boards are single front non-draw out type, consisting of circuit breaker, contactors, starter, fuse unit, MCB etc. arranged in multi-tier construction. AC/DC DBs, cater to the power supply requirement of Boiler and shall be located in MCC room. These MCCs and AC DBs are mainly supplied to cater the requirement of drives, valves, etc. All the LT Switchgear, AC DB shall be located in Switchgear room of Power House.

3. The base frames shall normally be supplied along with the switchgear boards. These shall be aligned, leveled and grouted in position as per approved drawings. Wherever the base channels are not available, the same shall be fabricated, erected and painted at site. The material for this shall be supplied by BHEL. Base channels shall be grouted on the opening of the floor. All minor concrete chipping and finishing works are deemed to be included in the scope of the job. If base frame is to be fabricated/ erected, separate rate shall be paid on Tonnage basis. This is applicable for local start/stop push button box also. If any grouting bolts are required for the panel, the same shall be supplied within the quoted rate.
4. For the panels to be mounted on the trenches, channel supports have to be provided across the cable trenches over which the base frames of the panels shall be mounted. The contractor shall carry out fabrication and erection of these support structures and separate rate shall be paid on Tonnage basis.
5. Panels will be delivered in different shipping sections. The contractor shall set each section of equipment on its foundation or supporting structures and assemble the panels as required. Skilled manpower shall be engaged for installation of panels with parallel, horizontal and vertical alignment.
6. Necessary interconnection of busbar, inter panel wiring, etc. will have to be done by the contractor as part of panel erection.
7. Normally the panels shall be supplied with complete instrument mounting and wiring. However, if necessary, dismantling of the existing components, making minor modifications in the wiring to suit operating conditions, mounting and rewiring of new components shall be carried out without any extra cost. However, if any major wiring modification is involved inside the panel, the same shall be carried out at extra cost. Mounting and wiring of any instruments, meters, relays, push buttons, indicating lamps, contactors etc. if supplied loose for safety in transit, will also be included in the scope of the job, within the quoted rate.
- 8. The contractor shall carryout touch up painting for panels, including supply of paints, wherever required.**
9. The commissioning of Switchgear shall involve the trial runs and commissioning of all connected equipment like servomotors and drives etc. The contractor will have to keep his personnel round the clock, if necessary during the trial runs and promptly take action for any repair, checks and rectification etc. required in the equipment erected by him.
10. All T&P, Material handling equipment including cranes and Relay Testing/ HV Testing Calibration equipment/ Instruments shall be arranged by contractor.

11. The contractor shall calibrate and commission all switchgear/panel mounted instruments, protection relays, transducers, Recorders, Indicators, energy meters etc
12. MCC incomer bus shall be connected to PCC of customer. The contractor shall co-ordinate for proper connection at PCC.
13. Contractor shall co-ordinate with other cable-laying agency for proper cable termination.
14. All testing Instruments/ Equipment deployed to site shall be calibrated before putting it into service. A copy of calibration certificate shall be submitted to BHEL Engineer for his verification and approval
15. If any removal/ Re-fixing of contactors/relays becomes necessary for the completion of the system, the same shall be done by the contractor at no extra cost.
16. Any loose supplied items like lamps, lens, contactor, fuse/relays/instruments missed from the custody of the contractor shall be replaced by the contractor at no extra cost.
17. Contractor shall put his watch and ward for the equipment under his custody and erected in location against theft and damage by other agencies working on the same area.
18. Laying of rubber mats will be part of panel erection works and no separate rate shall be applicable for the same.
19. Scope of work shall also cover drilling of bottom gland plates for cable entry as required.
20. Closing unused opening at the panel bottom plate with suitable material shall be part of panel erection.
21. Erection of Resistance box of DC drives shall be part of DC starter panels.
22. Contractor shall prepare log sheets, protocol sheets etc. and get approval from BHEL/ Customer. Contractor shall be responsible to get the protocol signed with customer, as per field quality plan.
23. Dimensions & weights indicated in the BOQ against various panels are approximate only. There may be variations in the weight and dimensions. Variations in depth, height or weight of the panel shall not be considered for payment.

24. Any variation in length within $\pm 20\%$ shall not be considered for payment. If the panels have any variation in length beyond $\pm 20\%$ as compared to actual length indicated in the BOQ, payment shall be considered proportional to the length of the panel only.

6.3.4. SCOPE OF AVR/ GENERATOR CONTROL/ RELAY PANELS/ AND OTHER CONTROL PANELS

1. The panels shall be supplied with different type of protection relays, Instruments like Meters, Transducers, etc and these panels shall be installed in unit control room.
2. The scope of work will be generally in line with Electrical MCC panels as detailed under above clause.
3. Unit rate shall also include testing, calibration and adjustment of relays, electronic cards and instruments, transducers mounted on the panels. All testing instruments like Relay Testing/ Calibration Instruments, primary/secondary injection kits, CRO, frequency counter etc. shall be arranged by the contractor.
4. If panels are supplied with monitor, printers, furniture, controller etc. or any loose items or equipments, the erection of above shall be part of respective panel. No separate rate shall be payable for loose supplied items.
5. Normally the panels shall be supplied with instruments / modules mounted and wired. No separate payment shall be made for commissioning of any instrument/ cards/ components. If dismantling of such instruments and rewiring are needed at site, the same shall be carried out at no extra cost. If any instruments/ cards/ components supplied as loose items for safe transit, the same shall be mounted and wired at no extra cost. However, if any major installation/modification/wiring are involved, the same may be carried out as extra work. The decision of BHEL engineer shall be final in respect of above extra works.
6. BHEL shall provide vendors' support for commissioning of proprietary type of microprocessor based instruments, protection relays which requires software loading and programmer etc. However overall responsibility lies with contractor and the contractor shall provide all support like manpower, standard T&P, instruments etc. for calibration and commissioning of above proprietary type instruments.

6.3.5. BATTERY AND BATTERY CHARGER

The batteries are of heavy duty type capable of providing normal and emergency DC loads. The cells will be mounted on insulators carried on suitable wooden stands. The rectifiers/inverters are fully thyristorised and shall comprise of Silicon Controlled Rectifier with transformer, switchgear and automatic regulation. Tentative details are given in the BOM.

Lump sum shall be quoted for Erection and commissioning of UPS and Battery. No additional payment shall be made for any variation in the number of cells. The unit rate quoted for erection of UPS and battery will include the following works.

6.3.5.1. Scope of Work for Battery

1. Collecting the batteries and all the accessories like cable connectors, inter lock connectors, equalizing connectors, rack insulators, fuse box, loop cables etc from stores and assembling on the racks and fixing all loose supplied items as per drawings, laying and termination of loop cables.
2. Filling the individual cells with Acid/alkali - if applicable.
3. Arranging suitable resistive load banks for charging and discharging during charging and discharging cycles.
4. Arranging manpower in shift during battery charging and discharging cycles that may be carried out round the clock as per the code of practice, and conducting other routine tests as per IS under the supervision of BHEL Engineer.
5. Modifications or changes if any for the loose supplied items or any minor changes in wiring.
6. Arranging necessary tools, T&P, Testing equipments required for erection and commissioning of the battery.

Note:- If the length of loop cables exceeds 15 Mtrs, separate unit rate shall be considered for the excess length as per the equivalent unit rate available in the BOQ.

6.3.5.2. Scope of Work for Battery Charger

The scope of work will be in line with scope of work for electrical control panels, as detailed under Clause 6.3.4

6.3.6. SCOPE OF WORK OF DIESEL GENERATOR SET

The DG sets of rating 630 KVA, 3 phase, 415 V skid-mounted type set with diesel engine, AVR, Radiator, Air Intake System, Exhaust system, Fuel Day Tank, battery sets, Acoustic enclosure, panels etc.

Following items shall be supplied as loose.

1. DG Control Panel (Local): size : 2600x1300x2250 mm.
2. DG Control Panel (Remote): size: 2600x1300x2250 mm.
3. DG PCC : size: 3200x1300x2250 mm
4. Aux Distribution Board: size: 1800x600x2250mm
5. Battery Charger panels (Starting) : 2Sets & Battery,size:550x400x800 mm;
6. Battery Charger panels (Control) : 2Sets & Battery,size: 550x400x800 mm;
7. Power/control cables, Trays, Earthing Materials ,trays supports etc. 1Lot

Other Details

1. Static Weight of DG Set: 11500 kg (approx.)
2. Static Weight of Acoustic Enclosure: 6500 kg (approx.)

Cooling system comprising of radiators, engine mounted water pump, self-contained pipe, thermostat etc.

Fuel system consisting of PT fuel pump, injectors, fuel filters, self-contained piping.

Lubricating system consisting of oil pumps, strainers, lube oil cooler, bypass filter, self-contained piping.

Air Intake System consisting of dry type filter, air intake manifold with necessary connectors, turbo charger with after cooler.

Exhaust system consisting of exhaust manifold, flexible piping, residential silencer etc.

Diesel Generator sets shall be located at Diesel Generator Building adjacent to the Power House building.

6.3.6.1. Scope of Work for DG Set

1. The scope of works covers erection skid mounted Diesel Generator and erection of all loose supplied items mentioned above under SI.1 to 8.
2. Minor civil works like drilling, chipping and punching holes and opening in concrete floors, slabs, brick-walls, and cleaning of all debris, Grouting, supply of cement, sand, concrete etc. required for installation of DG sets shall be included in the erection cost of equipment. No separate payment is applicable.
3. If any major civil foundations/modifications/alterations are required for proper installation of Diesel Generator, the same shall be carried out at extra cost. The decision of BHEL Engineer regarding the above will be final.
4. All T&P, material handling equipments, including crane shall be arranged by the contractor.
5. All calibration and testing instruments required for relay testing, high voltage testing and load testing shall be arranged by the contractor.
6. Erection of cable trays, loop cabling between Diesel Generator to Control Panel/MCC and between Control Panel to MCC, i.e., within the DG Building shall be part of the erection and no separate rate shall be paid for erection of trays and cables
7. **The DG set shall be maintained by the contractor after commissioning until full load testing is completed.**

*** Lump sum rate to be quoted**

6.3.7. SCOPE OF WORK FOR ASH LEVEL INDICATOR:

1. Scope of Ash level indicator consists of erection of transmitters (electronic unit), PTFE wires, probes (for high and low level sensing), flexible conduits etc. All PTFE cables shall be routed through ¾" GI flexible conduits.
2. The unit rate quoted for each set consists of erection of transmitters (electronic units), fixing of probes, laying and termination of PTFE cables through conduits, clamping of flexible conduits etc. The unit rate also covers supply of metallic clamps, lugs etc. Lumpsum rate shall be quoted for each set and no separate payment shall be made against erection of any individual item.

3. If any mounting frames are required for installation of transmitters same shall be carried out on tonnage basis as applicable for other fabrication and erection.

6.3.8. SCOPE OF WORK FOR HEATING ELEMENTS:

- 1 Two types of heating elements shall be supplied (panel type and standard heating elements)
- 2 All heating elements shall be fixed by the mechanical contractor.
- 3 The panel type heating elements shall be supplied with extension cables and flexible conduits. Unit rate quoted for panel type heating element includes routing the extension cables through flexible conduits, dressing, terminations and checking of the heating elements.
- 4 Unit rate quoted for thermostat and other standard heating elements covers only checking of elements/thermostat.

6.3.9. = DELETED =

6.3.10. SCOPE OF WORK OF CABLES :

BHEL will supply HT and LT cables (11kV/ 1.1 kV, Armoured/ Unarmoured, Aluminium/Copper PVC FRLS insulation) of different sizes. The scope of work for cables covered in this tender is as below.

1. The scope includes laying & termination of cables, fixing of glands, ferrules, tag plates with necessary numbering and dressing of cable, as per BHEL specification and BHEL engineer's instructions.
2. Unit rates shall be on meter basis. The unit rate quoted for the cabling laying shall also include supply of clamping materials, ferrules, tag plates, lugs up to 2.5 sq. mm. Contractor scope of supply of materials shall be as per BHEL's specification as detailed in Section VI
3. Cables shall generally be laid on cable trays. However, if the cables are to be routed through or laid duct bank, cable shaft etc., the same rate shall be applicable.
4. Separate rate shall be paid for LT Power cable termination , for cable size of 4 sqmm and above only.
5. For single core Power cable Trefoil clamps shall be fixed as part of laying and termination rate.
6. If the cables are to be routed on steel angles as per site condition, steel angles will be supplied by BHEL.

7. All the dressing material such as Aluminium/GI strips, PVC ties etc required for cable shall be arranged by the contractor within the rate quoted .
8. The contractor shall carry out cable dressing and clamping for all the cables laid by the contractor. However, if cables like illumination cables or any other cables of lesser quantity for which no separate trays have been allotted and are to be laid on the same trays, the contractor shall do clamping such those cables also along with the cables laid by him.
9. The unit rate quoted for cable laying shall also cover the following works.
 - a) Modification such as rotating the terminal box through 90° or 180° as required.
 - b) Enlargement of cable entry holes, if necessary, by chipping/tapping or any modification required fixing of cable glands
 - c) Reaming and relocating holes at actual point of entry of cable or conduit in terminal boxes, outlet boxes, pull boxes etc. cleaning off the debris/trapped material from conduit/ducts.
 - d) In case any existing structure is affected/damaged due to installation work of cables the contractor shall repair the same to the satisfaction of Site Engineer
 - e) However any major modification like drilling, tapping etc. are involved in fixing of glands in JBs and Terminal boxes same shall be considered as extra on man hour rate basis as per extra works clause.
10. The approximate number of termination for the purpose of estimation to be for control and pair cable shall be assumed as follows: The average RUN length shall be considered as 150 mtrs. However, 10% of the cable the average length shall be considered as 30 mtrs.

CABLE TERMINATION

11. For LT control cable terminations, no. separate rate shall be paid.
12. The scope of termination shall include, termination of cables on various panels/ JBs/ Pushbuttons etc. installed by other agencies. The contractor shall co-ordinate with such agencies and do the termination, including drilling of gland plates for fixing cable glands, if required.
13. The insulating sleeves shall be of fire resistant and be long enough to over pass conductor insulation and shall be properly sized.

14. The contractor shall provide Tools/ equipment required for the connections and termination of cable wherever necessary.
15. For HT cable termination suitable termination kits shall be supplied and HT cable termination shall be part of installation of HT termination kits. No separate cost shall be paid for HT termination
16. Only printed ferrules should be used and necessary ferrules printer shall be brought and used by contractor at site.

6.3.11. CABLE TRAYS / CONDUITS/ FLEXIBLE CONDUITS

Scope of cable tray works covers erection of various sizes of ladder & perforated trays with accessories in Power House building & ESP area that includes cable galleries/cable vault and cable shaft and trays required for routing of cables for some of the BOP building. All type of cable trays including standard trays accessories shall be supplied by BHEL.

The scope of work for cable trays shall be as follows:

A- CABLE TRAYS

1. Scope of cable tray works covers erection of various sizes of trays with accessories such as elbow, cross, TEEs, bends (90° vertical and Horizontal), reducers, coupler plates/fixing plates, anchor bolts, fasteners etc.
2. If accessories such as TEEs, reducers, bends (90° vertical and Horizontal), cross etc. are not supplied, the same shall be fabricated wherever required from straight trays. The accessories supplied maybe modified to suit site routing as part of work.
3. The scope also covers making offsets by cutting standard tray sections and inserting suitable size of trays to match with the existing arrangement.
4. The unit rate for erection of trays shall be on meter basis which includes erection of trays and accessories, fabrication of tray accessories and modification of straight trays, if required.
5. No separate rate shall be paid for any fabrication of tray accessories or any modification on straight trays.
6. If tray covers are supplied, the same shall be erected after completion of cable lying and no separate payment will be made for fixing these covers. GI strip clamps are to be used for fixing the tray covers.

7. Welded Joints of trays shall be painted with red lead and aluminium paint in turn with bitumen as per IS 3043. The unit rate shall also include supply of paints, thinner, other consumables and brush etc.
8. Cable tray mounting structure shall be welded to the plate inserts or to steel structural beams/ members. Welding of cable tray mounting structure to steel structural beams/ members shall be done with prior approval of Customer/ BHEL Engineer.

B- RIGID & FLEXIBLE CONDUITS

1. Cables shall normally be laid on cable trays. However, in case of shorter routes where trays are not possible, suitable GI pipe/flexible conduits shall be used. Unit rate shall be paid on running meter basis.
2. The scope of works for flexible conduit includes drilling of the holes on the plates, fixing of the end connectors, providing suitable supports and fixing tag marks wherever specified. The supply of suitable clamps, fasteners and tag plates are in contractor's scope.
3. In the case of flexible conduit laying for fixing end connectors, no separate payment will be made for connectors.

6.3.12. SCOPE OF WORK OF JUNCTION BOXES/ MARSHALLING BOX/ STARTER BOXES AND PUSH BUTTON BOXES:

Different type of Junction boxes/Push button boxes shall be supplied. The scope of installation of Junction boxes/Push button boxes shall be as follows:

1. The unit rate quoted for erection of junction boxes/push button boxes shall include providing necessary supports, drilling of bottom gland plates for cable glands as required, Painting the tag No of JB or fixing a separate tag plate as required on junction boxes/push button boxes, minor chipping, grouting as required for mounting the JB/PB and supply of all bolts and nuts (Fasteners) including grouting bolts as required for mounting the junction box/push button.
2. Fabrication and fixing of supports shall be on tonnage basis.
3. The contractor shall close all unused holes on the gland plates using grommet or other suitable material issued by BHEL, at no extra cost.

4. If any intermediate JBs are required to terminate power cables for drives, the same shall be installed and also any modification like replacement of terminals, enlarging gland holes etc. required to accommodate power cables shall be carried out as part of this works. Equivalent Unit rate shall be paid for installation of such JBs. Decision of site engineer will be final regarding the equivalent rate.

6.3.13. SCOPE OF WORK FOR FABRICATION & INSTALLATION OF STEEL MATERIALS

1. Scope of steel fabrication and installation covers, fabrication and installation of various type of supports for cable tray, GI pipes, JB, Control Box/Panel, local Push Buttons, bus ducts etc. with angles and channels of different sizes.
2. The fabrication steel materials such as angles, channels, plates, etc shall be supplied in standard lengths by BHEL.
3. Fabrication shall be carried out by the contractor as per schemes in consultation with site engineers.
4. For fixing frames or supports if any minor grouting is required the same shall be carried out by the contractor. After installation of frames, grouting of the same is in the scope of contractor. Supply of all cement, sand etc. required for grouting of supports is in the scope of contractor. All site fabricated items, all supports or brackets needed for installation shall be fabricated and painted by the contractors with two coats of red chromate Zinc primer and two coats of epoxy based paint. The paint shade shall be approved by BHEL Site in charge. Immediately after fabrication, primer shall be applied to prevent corrosion. The installation shall be carried out only after applying the primer as detailed in painting clause.
5. A composite single rate shall be quoted for fabrication and installation of steel, on tonnage basis. The above rate shall include supply of paints and painting, grouting and grouting material as required.

6.3.14. ABOVE GROUND EARTHING & LIGHTNING PROTECTION INSTALLATION

A) Above ground earthing

- a. The scope of work shall include installation of earthing and lightning protection system materials and associated fittings. Civil agency will provide earthing grid system comprising of main earthing conductor buried in soil, embedded in concrete inside the building. Installation of earthing conductors for connecting equipment pertaining to BOILER/TG/BOP area to the plant main earth grid shall be carried out by the contractor.
- b. Different types of earthing materials like GI Flats, wires etc shall be supplied by BHEL and the contractor shall lay and connect the earthing materials as per site requirement. The unit rate shall be quoted for earthing on meter basis and shall cover supply of fasteners, saddles, spacers, lugs for earthing wires, minor civil works, painting on the welded joints including supply of anti corrosive primer and paint etc.
- c. Drawings of main earth grid system provided by others will be made available to the contractor to enable them to carry out rest of the earthing system work.
- d. Treated test pits as per drawing No:PE-DG-219-509-E763 shall be provided.
- e. Unit rate for test pit shall be on Nos. basis. The unit rate quoted for Test pit will cover casting of test pit chambers, supply of all other materials like cement, brick, sand, salt, charcoal etc. except Earth Electrode. Earth Electrode shall be supplied by BHEL in standard length and contractor shall fabricate suitably as per the drawing.
- f. Earthing System Installation scope covers, earthing of all cable trays in inside/outside plant building as well as inside the trenches at an interval as detailed in section VII metallic frames of all current carrying equipment, supporting structures adjacent to current carrying conductors, neutral points of various /equipment, panels, motors, JB, push button boxes etc. as listed in various drawings
- g. The connection between earthing pads/ terminal to the earth grid shall be made short and direct and shall be free from kinks and splices.
- h. Metallic conduits and pipes shall not be used as earth continuity conductor. Pipe racks shall be earthed at every 25 meters. Earth continuity shall be ensured across all flanges joints etc as per earthing drawing.

- i. Connection between the equipment earth lead and the grid conductor shall be welded. For rust protection, the welds shall be painted with anti- corrosive primer & paint.
- j. Supply of anti- corrosive primer & paint is in the scope of the contractor.
- k. Generator neutral from the NGT/NGR cubicle shall be earthed using two dedicated rod electrodes, which shall in turn be connected to the main plant grid.
- l. Generator transformer neutral shall be earthed using 2 dedicated rod electrodes.
- m. All electrical equipment operating above 250V shall have two separate and distinct connections to the earth pit.
- n. Transformers shall be provided with two dedicated earth electrodes for earthing of neutral and transformer tank earthing. The contractor shall carry out earthing for all Electrical equipment, which may be erected by other agency.
- o. If the equipment is not available at the time of earthing conductor laying tap connections from the main earthing conductor shall be brought out up to slab equipment foundation level with at least 200 mm spare length left for further connections to equipment earthing terminals.
- p. For different floors in a building, localized internal earthing ring shall be formed and connected to the ground earthing through vertical risers. The earthing mat shall be common to both power and lighting installation
- q. Each RCC steel column of the building will be interconnected to the floor-earthing grid in basement/ground floor.
- r. For Electronic earthing, separate conductor shall be used for flow of earth fault current. All Electronic panels shall be connected separately to Electronic bus which in turn will be connected to electronic earth pit.

B) Lightning protection system installation

- 1 The scope of works for Lightning Protection system includes installation of vertical air terminations, Horizontal conductors, vertical down conductors, fabrication of fixing clamps, test links, supply of saddles, Spacers and associated minor civil works etc as per drawing PE-DG-217-509-E014.
- 2 HORIZONTAL AND VERTICAL DOWN CONDUCTORS: The horizontal conductors shall be installed on the top of the building with suitable clamps/saddles arrangements. This horizontal conductor shall be connected with down conductors which in turn will be connected to risers through test links. Both

horizontal and down conductors shall be supported on the clamps/saddles and spacers which will be fixed on the walls/columns or on top of the parapet walls. The clamping arrangements shall be provided at a span as specified in the earthing drawing.

- 3 The unit rate quoted for horizontal and vertical conductor on meter basis shall include supply of supports clamps, saddles, spacers Anchors/ fasteners etc.
- 4 TEST LINKS: The unit rate quoted for Erection of Test links shall include supply of TEST LINK which shall be supplied as per drawing PE-DG-247-507-E002 and installed at different places as shown in the lightning protection drawings.
- 5 The unit rate quoted for the test link on sets (Nos.) basis shall cover supply of GI fasteners like washer/bolt/nut required for fixing Test Link and connecting Test Link to riser rod of MS 40 mm size. by welding. If the riser rod is provided already , Test Link shall be directly shall be directly welded to riser rod with down conductor.
- 6 RISER ROD:(If applicable)The unit rate quoted for riser rod shall also covers excavation of earth for laying of riser rod , welding with lightning earth electrodes and Test link down conductor, refilling of the excavated earth, consolidation etc . Even if the building plinth area has already been consolidated, the same shall be removed, conductors shall be installed ,welded, refilled and consolidated
- 7 VERTICAL AIR TERMINATIONS: The vertical air terminations shall be located in different locations of the buildings as shown in the drawings. The vertical terminal shall mostly be fixed on the top of peripheral wall using a GI base plate of size 150x150x6 mm. The vertical air terminal shall be grouted on the wall and minor civil works required for grouting the air terminals as shown in drawing PE-DG-247-507-E002 and supply of grouting materials are in the scope of Contractor. The supply of above base plate is in the scope of Contractor.
- 8 The unit rate quoted on sets (Nos) basis for vertical air terminal includes supply of base plates, bolt with nuts & washer, chipping and minor civil works, grouting and supply of grouting materials
- 9 Entire system shall be earthed in accordance with the provisions of the relevant IEC recommendations/IS code of practice IS 3043-1947 and Indian Electricity Rules, so that the values of the step and contact potentials in case of faults are kept within safe permissible limits. Parts of all electrical equipment and machinery not intended to be alive shall have two separate and distinct earth connections each to conform to the stipulation of the Indian Electricity Rules and apparatus rated 240 V and below may have single earth connections.

6.3.15. SCOPE OF PAINTING

1. The scope of painting generally includes painting of all steel items such as supports, racks, frames, Transformer, Bus ducts etc, as detailed in Scope of work of respective equipment besides touch up paints wherever required.
2. **The scope also includes supply of paints, primers, tools/consumables like brushes, rollers, emery papers, thinner etc., at no additional cost.**
3. Touch up painting is generally required for trays, control panels, junction boxes. Full painting shall be required for specific equipments as per the scope of erection.
4. All damaged painted surfaces shall be cleaned and painted as detailed above.
5. All damaged galvanized surfaces including cable trays shall be coated with cold galvanizing paint.
6. No separate rate shall be paid for painting and supply of paints, and other consumables. Painting shall be accommodated in the unit rate quoted for items which calls for painting as per scope of work.

6.3.16. SCOPE OF CIVIL WORKS

1. Only minor civil works like chipping, drilling and punching in concrete floors/ slabs/ brick walls, grouting of bus duct /Transformer supports in foundation, base frame of panels/ push button stations/ Junction Boxes, etc. are covered in the scope of this contract.
2. Scope of civil works includes supply of grouting materials like grouting cement, sand, etc., and cleaning of all debris.
3. More details regarding scope of civil works are given in the respective equipment erection.
4. No separate payment will be applicable for above civil works.

6.3.17. SCOPE OF CALIBRATION

1. Contractor shall calibrate all the local instruments, panel mounted instruments including transducers, protective relays, Recorders, Indicators etc. that will be supplied along with equipments mounted in or in loose
2. Contractor shall maintain calibration records as per the format CP:PEX:FOX enclosed in the tender specification.

3. All testing Instruments/ Equipment deployed for calibration shall be calibrated before taking it into service. A copy of calibration certificate shall be submitted to BHEL Engineer for his verification and approval.
4. All testing instruments shall have calibration certificate issued by recognized/accredited agencies.
5. **BHEL shall provide vendors supports for proprietary type of microprocessor-based instruments, protective relays, which requires software loading and programmer etc. However overall responsibility lies with contractor and Contractor shall provide all supports like manpower, standard T&P, Instruments etc for calibration and testing of above proprietary type instruments**
6. **If BHEL is unable to provide or arrange vendor support for above mentioned proprietary instruments, contractor shall carry out the calibration through authorized agency, at extra cost. The actual cost of such calibration carried out by out side agency shall be reimbursed by BHEL. However if above such calibrator is available with BHEL at site the calibration shall be carried out by the contractor within the quoted rate.**

6.3.18. SCOPE OF COMMISSIONING OF EQUIPMENT ERECTED BY THE MECHANICAL CONTRACTOR

1. All types of HT Drives and Generator

- a- Cable identification, checking and meggering.
- b- IR value of motor, measurement of winding resistance etc. c- Dryout all the motors if required to improve IR value.
- d- Checking direction of rotation of motors and testing and commissioning from local as well as remote.
- e- Checking the bushing and HV test/Tan delta test
- f- Attending to any defects till the handing over of the unit to customer

2. ESP Transformer

- a- Dry out of transformers (Oil filtration) till achieving desired BDV, IR Value, Calibration of oil temperature gauges, Checking of breather gauge, HV Test etc. i.e. scope of commissioning of ESP Transformer shall be in line with transformers erected by the contractor.

b- Replacing defective components like Temperature gauges, breather glass etc.

c- Attending to any defects till handing over of the unit to customer by BHEL

3. All types of drives and motor operated valves

a- Cable identification, checking and meggering.

b- IR value of motor, measurement of winding resistance etc.

c- Dryout all the motors if required to improve IR value.

d- Limit switch and torque switch setting

e- Calibration of Electronic cards, modules etc. and fixing the same if supplied as loose item.

f- Checking direction of rotation of motors and testing and commissioning from local as well as remote.

g- Attending to any defects till the handing over of the unit to customer by BHEL

h- Replacing defective components like limit switches, electronic cards etc.

4. Panels.

The panels shall be mostly skid mounted and the skid will be erected by mechanical contractor. The scope of commissioning of Panels covers checking of internal wiring and associated loop cables from panels to field instruments, Push Buttons, JBs, drives, replacing defective components/instruments/electronic cards etc.

If any loop cables (power or control) are to be laid or replaced, the same shall be carried out at unit rates available in the BOQ.

5. Hoist :

All cabling will be carried out by the vendors. However the scope of works of hoist covers besides works mentioned in SI No1, the checking of control panels wiring, field wiring like push button, motors, limit switch etc., fixing of Trailing cables, and making ready for load test by mechanical agency.

6. ESP Heating Elements and Thermostats

a- Checking the healthiness of Elements and Thermostats.

b- Setting the value

c- Replacement of defective Elements and Thermostats.

6.3.19. SCOPE OF PRE-COMMISSIONING/ COMMISSIONING AND POST COMMISSIONING WORKS:

1. The scope of commissioning works covers arranging suitable skilled manpower - technician, supervisor and engineer as required for commissioning of all Electrical equipments covered in the BOQ including loop checking and establishing the operation of equipments/systems to meet plant commissioning/operation. BHEL will provide vendor supports for special or proprietary type instruments/systems and contractor engineers/supervisors shall associate with the vendors and provide necessary manpower, T&P etc.
2. Scope of commissioning starts with the commissioning of various Elect equipment erected by the contractor and making them available, as required, for the various commissioning activities of the main plants. The commissioning activities of the main plant shall be as below:
 - a. Trial run of various equipment.
 - b. Light up of boiler.
 - c. Boiler acid cleaning.
 - d. Boiler alkali boil out.
 - e. Turbine barring gear.
 - f. Steam blowing of piping.
 - g. Turbine rolling.
 - h. Safety valve floating.
 - i. First synchronisation
 - j. Heavy oil firing and synchronisation.
 - k. Coal firing.
 - l. Trial Operation / Full load.
3. The above commissioning activities, tests, trial runs may have to be repeated till satisfactory results are obtained to the satisfaction of customer / consultant. Contractor shall co-ordinate with other contractors during the above main plant commissioning activities to ensure proper commissioning of total plant.

4. The pre-commissioning activities of the main power plant shall start with energizing of start up power supply systems followed by trial run of various drives prior to light up of boiler. Commissioning operations shall continue till trial operation of the unit. The contractor shall simultaneously start checking cables erected by him to match with the various milestone activities /commissioning programme of the project. Contractor shall earmark separate manpower for various commissioning activities. The manpower shall not be disturbed or diverted for erection work
5. Contractor shall arrange commissioning engineers, supervisors, electricians, in each area to be associated with BHEL commissioning staff. Contractor shall earmark separate manpower for various commissioning activities. The manpower shall not be disturbed or diverted. It shall be specifically noted that above employees of the contractor may have to work round the clock along with BHEL commissioning engineers involving considerable payment of overtime, which forms part of Contractors Scope
6. The mobilization of these commissioning groups shall be such that planned activities are taken up in time and also completed as per schedule and the work undertaken round the clock if required. It is the responsibility of contractor to discuss on day to day / weekly / monthly basis the requirement of manpower, consumables, tools and tackles with BHEL engineer and arrange for the same.
7. If the contractor fails to arrange the requisite manpower, consumables, T&P to meet the schedule, BHEL shall make alternate arrangements and recover the cost with overhead from the running bills of the contractor.
8. The contractor shall make necessary protocols with BHEL/ customer after erection as well as testing/ commissioning of various equipments. The contractor shall prepare the formats and obtain approval from BHEL. The approved formats shall be printed by the contractor in adequate numbers.
9. In case any rework/repair/rectification/modification/fabrication etc. is required because of contractor's faulty erection which is noticed during commissioning at any stage, the same has to be rectified by the contractor at his cost. If during commissioning, any improvement / repair / rework / rectification / fabrication / modification due to design improvement / requirement is involved, the same shall be carried out by the contractor promptly and expeditiously. Claims if any, for such works from the contractor shall be governed by clauses covered elsewhere.

10. During commissioning activities and carrying out various tests, if any of the instruments has to be temporarily erected and commissioned to suit the commissioning activities, the contractor have to carry out the erection of the same. After completion of activities the temporary systems have to be removed and returned to stores and no extra rate shall be paid for this.
11. Minimum requirement of Man Power for testing/checking works shall be as follows:

	TRANSFORMER/BUS DUCT	SWITCHGEAR/CONTROL
-Engineer	1	1
-Supervisor	1	2
-Technician	2	6

12. The above commissioning group shall be identified at the Pre-commissioning and commissioning time. The above commissioning group shall have the knowledge of various systems referred in the tender and also should have adequate experience. The above manpower for commissioning is only tentative and for any additional manpower as per site requirement the same shall be arranged by the contractor.
13. If the contractor fails to deploy the above Engineer/Supervisor/ Technician at appropriate time of commissioning, no payment shall be made against commissioning activities as per terms of payment.
14. All the T&P instruments required for commissioning are to be arranged by the contractor. (However, any special instruments, which are of proprietary nature, shall be arranged by BHEL.)
15. It shall be the responsibility of the contractor to arrange and complete all the testing, pre-commissioning and commissioning activities for the particular equipment as per relevant standard, code of practice, manufacturer's instructions and BHEL norms. All the above will be witnessed by BHEL engineers and reports signed jointly. Contractor shall follow checklist of BHEL and testing & commissioning activities shall be carried out in accordance with the checklist.
16. The scope of commissioning by the contractor shall cover the equipment/drives erected by the mechanical contractors as detailed in the BOQ.

6.4.0 TIME SCHEDULE

6.4.1 The entire scope of work erection, testing and commissioning shall be completed within **10 months** as detailed in overall erection commissioning programs.

The contractor shall mobilize his resources and work force within two weeks from the date of telegraphic LOI in such a manner that the entire electrical work covered in his scope is completed to match the following commissioning program for Unit-9.

- a. Boiler Light up : 2 months from start of work.
- b. Barring Gear : 5 months from start of work.
- c. Synchronization : 6 months from start of work.
- d. Full Load/ Trial operation : 8 months from start of work
- e. Handing over : 10 months from start of work

6.4.2 = **DELETED** =

6.4.3 BHEL, owing to its commitment to their customer, may ask contractor to compress the total completion schedule. Contractor shall plan his activities and mobilize additional resources accordingly to the satisfaction of BHEL engineer within the quoted rates.

6.4.4 The contractor shall reach site and establish his site office and mobilize to commence the work as per directions of BHEL engineer. The date of starting the work at site shall be fixed in consultation with BHEL's engineer and the same shall be recorded in measurement book while entering the first RA bill.

6.4.5 Subject to availability of materials and other inputs, it is the responsibility of the contractor to carry out work to achieve the monthly progress and keep up the schedules.

6.4.6 Contractor shall draw the monthly erection programme along with BHEL engineer indicating the work to be achieved and events to be completed. Once the programme is drawn, he shall adhere to the same. Contractor shall plan and erect the materials as it is received at site. The monthly planned percentage shall take into consideration the material available at site before the start of the month and also any material received during the month. Contractor shall mobilize his resources required to achieve the monthly programmes.

6.4.7 = **DELETED** =

6.4.8 The work under this scope of contract is deemed to be completed in all respects only when all the items/materials/equipment are erected and trial runs, testing and commissioning the equipment are completed. The decision of BHEL in this respect shall be final and binding with the contractor.

6.4.9 During the tenure of contract, if BHEL is not satisfied with the progress of work, BHEL has the right to withdraw any portion of work / balance work and get the same done through any other agency at the risk & cost of the Contractor. The contractor shall not be entitled for any compensation whatsoever in this regard.

6.5.0 OVER RUN CHARGES

6.5.1 In case due to reasons not attributable to the contractor, the work gets delayed and completion time gets extended beyond **10** months from the date of commencement of work. Contractor shall be entitled to claim ORC after **10** months from the commencement of work .If eligible, the contractor shall be paid Over Run compensation of **Rs.50,000/- (Rupees Fifty Thousand only) per month** for the extended period beyond **10** months.

6.5.2 Contractor is not entitled to avail ORC for the work for which sufficient work front and time was available during the contract period and if the contractor could not attend due to his own reasons during the contract period and try to complete after the contract period, ORC payments shall be paid only after approval of competent authority.

6.5.3 The payment of over run charges for extended stay for reasons not attributable to contractor will be subject to achieving the monthly programme of work as mutually agreed upon during the extended stay.

6.5.4 The period of over run compensation will have to be ascertained before commencement of the ORC period

6.6.0 MEASUREMENTS & WASTAGE & CUTTING ALLOWANCES:

6.6.1 For all payment purposes, measurement shall be made on the basis of the execution of drawings/physical measurements. Physical measurements shall be made by the contractor in the presence of the Engineer.

6.6.2 The measurement for cable, impulse pipes/tubes, GI pipe, conduits, flexible conduits, trays etc. shall be made on the basis of length actually laid.

6.6.3 All the surplus, scrap and serviceable materials, out of the quantity issued to the contractor shall be returned to BHEL in good condition and as directed by the engineer.

- 6.6.4 All materials returned to stores should carry an aluminium tag indicating the size and type. More than 5 metres length termed as serviceable material and shall be returned size wise and category wise to the owner's stores/yard. Cable of serviceable length being returned to the stores in drums shall have their free ends sealed and the balance lengths on the drum(s) shall be noted and certified by the Engineer-in-charge. This shall be applicable only for the purpose of accounting the cables issued for installation.
- 6.6.5 While carrying out material appropriation with contractor, all the above points will be taken into account. All serviceable material returned by the contractor shall be deducted from the quantities issued for the respective sizes and categories and the balance quantity(ies) will be taken as the net quantity(ies) issued to the contractor. Material appropriation shall be done and allowable scrap quantity calculated as per wastage allowance specified in Section VII. Any scrap/wastage generated by the contractor in excess of the allowable percentage shall be charged at the rates decided by the Engineer whose decision shall be final and binding on the contractor.
- 6.6.6 For all site-fabricated steel items such as supports, racks, frames etc. physical measurement shall be made and then converted to tonnage. For steel material supplied to the contractor, all scrap shall be returned to BHEL stores with due accounting.
- 6.6.7 Every month the contractor shall submit an account for all the materials issued to him by BHEL in the standard proforma prescribed for this purpose by the site in charge/ Engineer.
- 6.6.8 The erection contractor shall make every effort to minimize wastage during erection work. In any case, the wastage shall not exceed the following limits:

S.No.	Item	% Wastage on issued Qty
01.	Fabrication steel	2
02.	Each size of power cables	1
03.	Each size of control cables	2
04.	Impulse pipe/ tubes/GI pipes/ Cu tube	1

If the actual wastage be more than the specified figure, then equivalent price of the excess portion will be deducted from the contractor's bill.

6.6.9 The cable take off from drums shall be planned strategically such that jointing in the run of cables and wastage are avoided. For this purpose the exact route length between various equipment/panels as per the cable schedule shall be measured and the route length recorded before laying of the cables. Depending upon the route length the type of cable required for various destinations, the cable drums shall be suitably selected for cable laying. Any jointing which may be approved by the engineer all the cut pieces/bits of cables which are not used/unused shall be returned to BHEL Stores for accounting towards wastage. The cables damaged by the contractor shall have to be replaced by the contractor at his own cost.

NOTE:

Salvageable scrap shall mean lengths of pipes, multicables, other cables etc., that can be used one time or other at a later date and normally they are recovered from the cut-pieces of tubes, pipes, multicore cables, cables etc. Non - Salvageable scrap means the lengths of tubes, pipes, multicore cables, cables etc., and they are from cut-pieces of tubes, pipes, multicore cables, cables etc., that cannot be used at all.

6.7.0 COLLECTION OF MATERIALS

1. BHEL shall issue materials covered in BHEL scope from their stores/ storage yard at site. The contractor shall collect such materials from BHEL stores/ storage yard and transport to his worksite at the contractor's cost.
2. The contractor shall inspect such materials as soon as received by the contractor and shall bring to the attention of the Engineer-in-Charge any shortage / damage or other defects noticed before taking over the materials. Materials once taken over will be deemed to have been received in good condition and in correct quantities except for intrinsic defects which cannot be observed by visual and dimensional inspection and weighing.
3. Upon receipt by the contractor the responsibility for any loss, damage and / or misuse of such materials shall rest with the contractor.
4. All materials issued by BHEL shall be properly stored and systematic records of receipts, issue and disposal will be maintained. Periodic report on inventory shall be made available to BHEL Engineer-in-Charge.

5. All materials issued by BHEL shall be utilized as directed by Engineer-in-Charge or most economically in the absence of such direction. The contractor shall be responsible for the return to BHEL Stores of all surplus material, as determined by the Engineer-in-Charge.
6. If the materials issued by BHEL are lost, damaged or unaccounted, the cost of such items shall be recovered from payments to the contractor. However, the contractor shall raise FIR for lost/ stolen items and inform BHEL all details.

6.8.0 STORAGE:

- 6.8.1 The equipment should be preferably in its original package and should not be unpacked until it absolutely necessary for its installation. The equipment should be best protected in its cases. It should be arranged away from walls.
- 6.8.2 The wooden pallet provided for packing itself can be retained for raised platform to protect equipment from ground damp, sinking into ground and to circulate air under the stored equipment. This shall also help in lifting the packing with forklift truck.
- 6.8.3 Periodic inspection of silica gel placed inside the equipment is necessary. It has to be replaced when decolorisation takes place or regenerated. BHEL shall supply the material and the contractor shall replace the same.
- 6.8.4 Due care should be taken to ensure that the equipment is not exposed to fumes gases etc. which can affect electrical contacts of relays and terminal boards.
- 6.8.5 The storage room and the equipment should be checked at regular interval of 3 months to ensure protection from termites, mould growth, condensation of water etc. which can damage the equipment. Contractor shall keep BHEL informed about such problems.
- 6.8.6 All the equipment, materials and goods kept in the store room should be identified and registered in a book. Inspection report should be recorded. Any discrepancy observed should be communicated to site.
- 6.8.7 Packing material shall be retained if the cubicle to be repacked after inspection.
- 6.8.8 Sub-Assemblies
 - a) All sub-assemblies should be kept in a separate place where it is easily accessible.
 - b) Sub-assemblies should have a protective cover in case it is stored without wooden packing/case to prevent accumulation of dust. Silica gel packets should also be kept along with it.
 - c) Sub-assemblies should not be stacked one above the other.

6.8.9 Loose items (wherever applicable)

The loose items supplied for the main equipment falling into various categories like tools, cables, recorders and display units, cable glands, frames etc. are to be categorized and stored separately.

6.9.0 TOOLS AND PLANT TO BE ARRANGED BY THE CONTRACTOR

6.9.1 Equipment, vehicles, tools and plants and materials brought to site by the contractor from his resources shall have distinctive identification marks and the description and quantity shall be intimated to BHEL in writing by the contractor.

6.9.2 All construction materials brought by the contractor shall have prior approval regarding quality and quantity by BHEL. The contractor shall also provide without extra cost necessary enclosures containers and protective materials for proper storage of materials inside, whenever so instructed by the purchaser without any extra cost.

6.9.3 No material or equipment or tools etc. shall be taken out of the work-site without the written consent of BHEL.

6.9.4 BHEL shall not be responsible for the safety and protection of the materials of the contractor and the contractor shall make his arrangements for proper watch and ward for his materials.

6.9.5 Until such time the work is taken over by BHEL, the contractor shall be responsible for proper protection including proper fencing, guarding, lighting, flagging, watching. The contractor shall during the progress of work properly cover up and protect any part of the work liable to damage by exposure to the weather and shall take every reasonable precaution against accident or damage to the work from any cause.

6.10.0 MATERIALS/CONSUMABLES TO BE ARRANGED BY THE CONTRACTOR WITHIN THE QUOTED RATE FOR E&C OF RESPECTIVE EQUIPMENT/ ITEMS

01 All type of welding electrodes, Gases

02 Provision for Temporary Scaffoldings.

03 Insulation tape.

04 Paints required for primer coating and final coating and for protective coating.

05 Solder wire (Lead) -(60/40)

06 Protocol/Calibration report sheets as per BHEL Format.

07 Panel/ JB Sealing compound material (for cable entry from bottom/Top of Panel).

08 Materials required for cable dressing.

09 Ferrules and Tag plates

10 Lugs upto 2.5 Sqmm

6.11.0 TECHNICAL REQUIREMENTS FOR SUPPLY ITEMS

1 CABLE LUGS:

a)	Type:	Solderless crimping type
b)	Material	Copper / Aluminium
c)	Whether tinning required (For copper cable lugs)	Yes.
d)	Thickness of tinning:	10 microns
e)	Applicable Standard for LT Cables	IS:8309
f)	Approved Vendors	Dowels/ Lotus/ Jainson/ Power Engineering/ KlipOn/ Multi (Any other make proposed by bidder shall be subject to BHEL's approval)

2 FERRULES:

a)	Colour of ferrules:	Yellow/White
b)	Colour of engraving	Black

3. TAGS:

a)	Material :	Al/Fiberglass/ Stainless Steel
b)	Markings:	Engraving/Embossing/Printing

6.12.0 TERMS OF PAYMENT

The contractor should submit his monthly on account monthly bill with all the detail required by BHEL on specified date every month covering progress of work in all respects and areas from the 25th of previous calendar month to 24th of the current month For erection and commissioning. Upto **93 %** of the value will be released progressively against running bills, as per break up details furnished below.

6.12.1 Transformers :

- | | | |
|----|---|-----|
| a. | Receipt, transport to the placement of erection on Placement, assembly, alignment, grouting mounting and wiring loose parts on pro rata basis | 50% |
| b. | Oil filling (gas filling) filtration, mechanical operation checking on pro rata basis | 20% |
| c. | Pre commissioning checks, tests, calibration and energisation and commissioning on pro rata basis | 20% |
| d. | On painting | 3% |

6.12.2 LT switchgear and control panels.

- | | | |
|----|--|-----|
| a. | Receipt, transport to erection site on Placement, assembly fixing and clamping on pro rata basis | 50% |
| b. | Adjustment, Alignment, grouting and on pro rata basis electrical interconnections | 20% |
| c. | Pre-commissioning tests, checks, calibration and making ready for energisation on pro rata basis | 23% |

6.12.3 Battery, Charger:

- | | | |
|----|--|-----|
| a. | Receipt, transport to erection site, checking, Placement, assembly, grouting Mounting and wiring of loose components | 50% |
| b. | Adjustment, alignment, inter connections and pouring of Alkali | 20% |
| c. | Pre commissioning test checks, and making ready for Energisation | 20% |
| d. | Completion of pending points | 3% |

6.12.4 Laying and termination of HT cable

- | | | |
|----|---|-----|
| a. | Laying /tagging /termination on pro rata basis and protocol signed | 70% |
| b. | Checking, Fixing Trefoil calmps and Highpo test on pro rata basis and protocol signed | 20% |
| c. | On submission of as built drawing | 3% |

6.12.5 Laying and termination of LT Power and control cable.

- | | | |
|----|---|-----|
| a. | Laying and tagging on pro rata rate basis | 70% |
| b. | After termination and dressing on pro rata rate basis | 20% |
| c. | On submission of as built drawings | 3% |

6.12.6 For Cable Trays, Tray Supports, Rigid & Flexible Conduits, Above Ground Earthing

- | | | |
|----|--|-----|
| a. | After satisfactory completion of work on pro rata rate basis | 70% |
| b. | After completing drawing wise on pro rata rate basis | 23% |

6.12.7 Fabrication and installation of Steel material

- | | | |
|----|--|-----|
| a. | After fabrication and applying of primer on pro rata basis | 50% |
| b. | After installation on pro rata basis | 40% |
| c. | On completion of painting | 3% |

6.12.8 DG Sets

- | | | |
|----|---|-----|
| a. | Receipt, transport to the placement of erection, Placement, assembly, alignment, grouting, mounting loose parts- on prorata basis | 70% |
| b. | Pre commissioning checks, tests, calibration and energisation and commissioning on prorata basis | 20% |
| c. | Load test | 3% |

6.12.9 OTHER ITEMS WHICH ARE NOT COVERED IN THE ABOVE TERMS OF PAYMENT, THE PAYMENT SHALL BE MADE AS UNDER

- 70% of the accepted rate for the respective item of work on pro rata basis on satisfactory completion of work.
- 23% of the accepted rate on commissioning of the system.

6.2.10 2 % of the total value will be paid on submission and acceptance of final bill.

5 % of the total value will be paid after a guarantee period of 12 months.

However, the above 5 % of guarantee amount shall be released against submission of bank guarantee for an equivalent amount from a nationalized/scheduled bank in the prescribed pro forma of BHEL valid for the total guarantee period.

6.13.0 GUARANTEE

6.13.1 All the works executed by the contractor including supplies are to be guaranteed for a period of 12 months from the start of guarantee period.

For all categories of above works, the guarantee period shall be 12 months. The guarantee period shall commence from the date of handing over of work to Customer or 6 months from the date of first synchronisation, whichever is earlier.

The contractor shall be responsible for the quality of workmanship and shall guarantee the work done, shall rectify/replace at no extra cost all defects due to faulty supply/erection and commissioning during the guarantee period.

6.13.2 In the event of contractor failing to replace/repair the defective supplies/works within the time required BHEL may proceed to undertake the replacement/repairs of such defective supplies/works at the contractor's risk and cost without prejudice to any other points/right.

6.14.0 ELECTRICAL INSPECTORATE'S APPROVAL:

6.14.1 The contractor shall be responsible for getting Electrical Inspector/ Statutory authority's approval for all electrical installation covered in his scope. This also includes the Electrical equipments that are erected by mechanical contractor for which commissioning is to be carried out by the Electrical contractor.

6.14.2 For getting the approval of electrical Inspector, the contractor shall arrange the following:

- a. Erection Completion certificate.
- b. Details of equipment (Specification)
- c. Test results conducted at site
- d. Any other documents as required by statutory authority.

6.14.3 Contractor shall carry out the modifications/rectifications as suggested by the authority at his cost. However, it is not applicable for equipment erected by Mechanical contractor.

6.14.4 The contractor shall also conduct re-test if required by the statutory authority at his cost.

6.14.5 Contractor shall also have valid electrical installation license on his company as well as for individuals acceptable to respective state electrical inspectorate requirement.

6.14.6 BHEL shall pay all other fees (FEES FOR VISITS, INSPECTION FEES, REGISTRATION FEES, ETC). However any expenditure related to documentation shall be borne by contractor.

6.15.0 PRICE VARIATION CLAUSE

Price Variation will be applicable as per following Price Variation clause:

- 1 The finally accepted rates for scope of work as defined in this tender are subjected to price escalation provisions as per the following formulae.

$$P1 = 0.75 \times P0 (F1-F0)/F0$$

P1 = Increase in billing amount (escalation for the particular month of billing)

P0 = Billing amount calculated on the accepted contract rate

F1 = New All India Average CPI published by Labour Bureau, Simla, Government of India for Industrial workers (Base 2001 - 100) applicable for the month under consideration i.e. for which bill has been raised.

F0 = New All India Average CPI published by Labour Bureau, Simla, Government of India for Industrial workers (Base 2001-100) applicable for the month of commencement of work.

- 2 Price escalation as per above formula shall be calculated and paid (excluding payments towards extra works and overrun, if any), on month to month basis.. BHEL however reserves the right to freeze escalation for that such of duration of delays, from time to time, which are entirely attributable to the contractor.
- 3 With the provision of prior escalation as per above clause, no claim/compensation on account of any increase whatsoever, (irrespective of whether escalation are steep/unanticipated or not compensated by the above escalation provisions in full towards minimum wages, consumables, electrodes, gases or any other items/reason) shall be payable during the entire period of execution including extended period, if any.
- 4 The payment of PVC shall be restricted to 10 % of the contract value.
- 5 However the contractor shall maintain sufficient work force and other resources required for completion of the job expeditiously for the entire contractual period including total extended period.

6.16.0 TAXES & DUTIES

6.16.1 Value Added Tax (VAT) for the works

Price quoted shall be inclusive of VAT except service tax.

Notwithstanding the fact that this is only an erection service contract not involving any transfer of materials whatsoever and not attracting VAT liability, being labour oriented job work, for the purpose of VAT the contractor has to maintain the complete data relating to the expenditure incurred towards wages etc. in respect of the staff/workers employed for this work as also details of purchase of materials like consumables, spares etc., interalia indicating the name of the supplier, address and VAT Registration No. and VAT paid and should furnish to BHEL at the year end.

The bidder shall get registered with State VAT authorities and the registration certificate shall be forwarded to BHEL immediately after commencement of work. In case the bidder had already registered under Orissa State VAT, they must quote their registration Number and forward copy of Registration Certificate while submitting this tender. The bidder has to obtain VAT clearance certificate from the concerned authorities, for the completed project, and submit along with the final bill as one of the document for contract closure.

In case the Bidder decides to include any VAT element along with the quoted price, they shall specify the value of VAT included in the quote, the rate of VAT adopted and also reason for such inclusion as additional information. If no VAT element is included in the price, the same shall be indicated in the quote.

6.16.2 Service Tax

Price quoted shall be exclusive of Service Tax. The service tax as statutorily leviable and payable by the bidder under the provisions of service tax Law / Act shall be paid by BHEL as per bidder claim through various running bills. **The bidder shall furnish proof of service tax registration with Central Excise Department specifying the name of services covered under this contract.** Registration Certificate should also bear the endorsement for the premises from where the billing shall be done by the bidder on BHEL for this project. The bidder shall obtain prior consent of BHEL before billing the service tax amount.

6.16.3 Other Taxes & Levies

Any other taxes and duties (except VAT & Service Tax) viz. Entry Tax, Octroi, eigniorage, Licenses, Deposits, Royalty, Stamp Duty, other charges / levies, etc. prevailing / applicable on the date of opening of technical bids and any variation thereof during the tenure of the contract **are in the scope of bidder.** In case BHEL is forced to pay any such taxes, BHEL shall have the right to recover the same from the bidder either from running bills or otherwise as deemed fit.

6.16.4 New Levies / Taxes

In case Government imposes any new levy / tax after award of the work during the tenure of the contract, BHEL shall reimburse the same at actuals on submission of documentary proof of payment **subject to the satisfaction of BHEL that such new levy / tax is applicable to this contract.**

6.16.5 Statutory variations

Statutory variations are applicable only in the cases of Value Added Tax and Service Tax. The changes implemented by the Central / State Government in the VAT Act / Service Tax during the tenure of the contract viz. increase / decrease in the rate of taxes, applicability, etc. and its impact on upward revision / downward revision are to be suitably paid/ adjusted from the date of respective variation. The bidder shall give the benefit of downward revision in favour of BHEL. No other variations shall be allowed during the tenure of the contract including extended period, if any.

6.16.6 Direct Tax

BHEL shall not be liable towards Income Tax of whatever nature including variations hereof arising out of this contract as well as tax liability of the bidder and their personnel. Deduction of tax at source at the prevailing rates shall be effected by BHEL before release of payment as a statutory obligation, unless exemption certificate is produced by the bidder. TDS certificate will be issued by BHEL as per the provisions of Income Tax Act.

6.17.0 PROVIDENT FUND & MINIMUM WAGES

The contractor is required to extend the benefit of Provident Fund to the labour employed in connection with this contract as per the Employees Provident Fund and Miscellaneous Provisions Act 1952. For due implementation of the same, Contractor is required to get himself registered with the Provident Fund authorities for the purpose of reconciliation of PF dues and furnish to us the code number allotted by the Provident Fund authorities within one month from the date of issue of this letter of intent. In case the contractor is exempted from such remittance, an attested copy of authority for such exemption is to be furnished. Please note that in the event of failure to comply with the provisions of said Act, if recoveries there for are enforced from payments due to us by the customer or paid to statutory authorities by us, such amount will be recovered from payments due to the contractor. The contractor shall ensure the payment of minimum labour wages to the workmen under him as per the rules applicable from time to time in the state.

The final bill amount would be released only on production of clearance certificate from PF/ESI and labour authorities as applicable.

6.18.0 IMPORTANT CONDITIONS FOR PAYMENT

It may be noted that the first running bill will be released only on production of the following.

1. PF Regn. No.
2. Labour Licence No.
3. Workmen Insurance Policy No.
4. Un Qualified Acceptance for Detailed L.O.I.
5. Initial 50% Security Deposit.
6. Rs. 100/- Stamp Paper for Preparation of contract

6.19.0 OTHER STATUTORY REQUIREMENTS

The Contractor shall submit a copy of Labour License obtained from the Licensing Officer (Form VI) u/r25 read with u/s 12 of Contract Labour (R&A) Act 1970 & rules and Valid WC Insurance copy or ESI Code (if applicable) and PF code no along with the first running bill.

The contractor shall submit monthly running bills along with the copies of monthly wages (of the preceding month) u/r78(1)(a)(1) of Contract Labour Rules, copies of monthly return of PF contribution with remittance Challans under Employees Provident Fund Act 1952 and copy of renewed WC Insurance policy or copies of monthly return of ESI contribution with Challans under ESI Act 1948 (if applicable) in respect of the workmen engaged by them.

The Contractor should ensure compliance of Sec 21 of Contract Labour (R&A) Act 1970 regarding responsibility for payment of Wages. Incase of "Non-compliance of Sec 21 or non-payment of wages" to the workmen before the expiry of wage period by the contractor, BHEL will reserve its right to pay the workmen under the orders of Appropriate authority at the risk and cost of the Contractor.

The Contractor shall submit copies of Final Settlement statement of disbursal of retrenchment benefits on retrenchment of each workmen under I D Act 1948, copies of Form 6-A(Annual Return of PF Contribution) along with Copies of PF Contribution Card of each member under PF Act and copies of monthly return on ESI Contribution – Form 6 under ESI Act1948 (If applicable) to BHEL along with the Final Bill.

In case of any dispute pending before the Appropriate authority under I D act 1948, WC Act 1923 or ESI Act 1948 and PF Act 1952, BHEL reserve the right to hold such amounts from the final bills of the Contractor which will be released on submission of proof of settlement of issues from the appropriate authority under the act.

In case of any dispute prolonged/pending before the authority for the reasons not attributable to the contractor, BHEL reserves the right to release the final bill of the contractor on submission of Indemnity bond by the contractor indemnifying BHEL against any claims that may arise at a later date without prejudice to the rights of BHEL.

6.20.0 e- Remittance

It may be noted that all payments due to the contractor will be made cheque payment or 'e-Payment'. The tenderer is requested to fill the form below for e-remittance. This e-remittance is also applicable for the return of EMD to the unsuccessful bidder.

6.21.0 FROM TO BE FILLED BY VENDORS FOR REGISTERING FOR E-PAYMENT

BHEL : PSSR : CHENNAI

DETAILS OF CONTRACTORS / SUPPLIER FOR E-REMITTANCE OF PAYMENTS BY BHEL/PSSR

1	NAME & ADDRESS OF THE CONTRACTOR / SUPPLIER	:	
2	BANK A/C NO.	:	
3	TYPE OF A/C (CC / CURRENT)	:	
4	NAME OF THE BANK	:	
5	NAME OF THE BRANCH	:	
6	BRANCH CODE	:	
7	BANKER'S ADDRESS (BRANCH)	:	
	MICR NO.	:	
	IFSC CODE	:	

Note : THE ABOVE DETAILS ARE TO BE FURNISHED IN THEIR LETTER HEAD BY THE CONTRACTOR / SUPPLIER, DULY ATTESTED BY THEIR BANKERS.

6.22 PROGRESS AND MONITORING OF WORK

- 6.22.1 The contractor shall provide all the relevant information on a regular basis regarding erection progress, welding progress, labour availability, equipment deployment, consumption of electrodes, gases, etc.
- 6.22.2 The contractor shall submit daily, weekly and monthly progress reports, manpower reports, material reports, equipment reports etc. as per formats specified by BHEL. The progress reports shall indicate the progress achieved against planned with reasons indicating the delays, if any. The report shall also give the remedial actions which the contractor intends to make good the slippage or lost time so that further works can proceed as per the original programme and the slippage do not accumulate and affect the overall programme.
- 6.22.3 Contractor shall monitor the progress of works as per the format furnished by BHEL.

6.23 EXTRA CHARGES FOR MODIFICATION AND RECTIFICATION WORK

- 6.23.1 BHEL may consider payment for extra works on man day basis for such of those works which require major revamping / rework / rectification / modification which is totally unusual to normal erection or commissioning work which are not due to contractor's faulty erection.
- 6.23.2 The All the extra work, if any, carried out should be done by a separate gang which should be identified prior to start of work for certification, of man hours. Daily labour sheets should be maintained and should be signed by contractor's representative and BHEL Engineer. Signing of the labour sheets does not necessarily mean the acceptance of extra works. Only those works which are identified as not usual to normal erection and certified so by the Project Manager and accepted by designers/supplier or competent authority only shall be considered for payment .
- 6.23.3 The decision of BHEL in this regard shall be final and binding on the contractor.
- 6.23.4 The following man hour rates shall be applicable for modification/rectification work.
- Average single manhour rate including overtime if any, supervision, use of tools and tackles and other site expenses and incidentals, including consumables for carrying out any rework revamping as may arise during the course of erection -
Rs. 40/- per man hour.
- Average single man hour rate including overtime if any, supervision, use of tools and tackles and other site expenses and incidentals excluding consumables for carrying out any rework/revamping as may arise during the course of erection -
Rs. 25/- per man hour

6.23.5 Extra works are broadly defined as below:

- Design changes which shall be intimated to the contractor after the start of the work which calls for dismantling of the erected components, rectification, modification, etc.
- Modification, rectification of erection wrongly erected /fabricated at site as per drawing subject to acceptance by approving authority.
- Jobs which require major modification, major repair, major reworks etc which shall be identified as major and warrant extra, payment, certified as such by the Project Manager and accepted by the designers/competent authority of BHEL.

6.23.6.1 However prior to carryout the repair/rework BHEL site will obtain administrative approval with the estimate before starting the works.

6.23.6.2 The decision of BHEL in this regarding the Extra works shall be final and binding on the contractor.

6.24 REPORTING DAMAGES AND CARRYING OUT REPAIRS

6.24.1 Checking all components/equipments at siding/site and reporting to transport and/or insurance authorities of any damages/losses shall be by BHEL. Contractor shall render all help to BHEL in assessing and preparing estimates for repairs of components damaged during transit, storage and erection, commissioning and preparing estimates for fabrication of materials lost/damaged during transit, storage and erection. Contractor shall help BHEL to furnish all the data required by railways, insurance company or their surveyors.

- 6.24.2 Contractor, on drawing the materials from stores, shall report to BHEL in writing any damages to equipments/components. The contractor shall also report in writing to BHEL, damages while in transit to site and unloading at place of work and any damages during erection and commissioning. The above report shall be in as many number of copies as required and in the proforma prescribed by BHEL site management. Any consequential loss arising out of non-compliance of this stipulation shall be borne by contractor.
- 6.24.3 Contractor shall carry out fabrication of any material lost for which insurance claim has been made only after getting written instructions from BHEL engineer.
- 6.24.4 BHEL, however, retains the right to award or not to award to the contractor any of the rectification/rework/repairs of damages and also fabrication of components.
- 6.24.5 All the repairs/rectification/rework of damages and fabrication of materials lost, if any, shall be carried out by a separately identifiable gang for certification of manhours. Daily log sheets should be maintained for each work separately and should be signed by contractor's representative and BHEL engineer. Signing of log sheets does not necessarily mean the acceptance of these as extra works.
- 6.24.6 Payments for all extra works for repair/rectification/reworks of damages and fabrication of materials lost shall be as per provisions of clause 3.8
- 6.24.7 In case the repairs/rectification/rework and fabrication of materials lost, the work has been done by more than one agency including the contractor, the payment towards extra charges shall be on pro-rata basis and the decision of BHEL in this regard is final and binding on the contractor.

6.25 INSPECTION OF WORKS

BHEL/Customer shall have full power and authority to inspect the works at any time, either on the site or at the contractor's premises. The contractor shall arrange every facility and assistance to carry out such inspection. On no account shall the contractor be allowed to proceed with work of any type unless such work has been inspected and entries are made in the site inspection register by CUSTOMER. Wherever the performance of work by the contractor is not satisfactory in respect of workmanship, deployment of sufficient labour or equipment, delay in execution of work or any other matter, BHEL shall have the right to engage labour at normal ruling rates and get the work executed through other agency and debit the cost to the contractor and the contractor shall have no right to claim compensation thereof. In such a case, BHEL shall have the right to utilize the materials and tools brought by the contractors for the same work.

6.26 DETAILS TO BE FURNISHED BY THE TENDERERS

Apart from other details called for in the tender document under the various other provisions, the tenderers shall submit the following details also along with their offers. Please also refer the check list.

- a. HQ Organization chart
- b. Site Organization Chart Covering various function
- c. Month wise Manpower deployment plan
- d. T&P deployment plan
- e. Erection Schedule.
- f. A copy of Electrical license

Tenderers shall go through very carefully all the provisions under section VI and shall submit manpower deployment plan as per appendix VI A. The list of T&P and instruments that are available with him for mobilization for the work, as specified in Appendix VI B, shall also be submitted by the contractor along with his offer. Tenderers shall indicate the present location and submit a schedule of tools and plants for this site to meet the schedules of erection and commissioning.

6.27 DOCUMENTATION

6.27.1 The following information shall be furnished within two weeks of award of contract for purchaser's approval

- a) Erection Schedule/ Bar chart covering planned activities at site
- b) Detailed organization chart
- c) Experience details of staff
- d) Details of T&P available with contractors with documents proofs.

6.27.2 The following information shall be furnished during the progress of work:

Test certificates of various tests conducted at site.

Erection and commissioning protocols signed by customer & BHEL.

6.27.3 As built drawings: After successful completion, testing and commissioning of installation work, all the E&C drawings/documents shall be updated in line with the actual work carried out and as built drawings/documents for the project shall be submitted by the contractor.

6.28 RECOMMENDED LIST OF TOOLS AND TACKLES /INSTRUMENTS FOR ELECTRICAL WORKS.

- a) Insulation tester:
 - i) Motorised megger - 0 - 1000 - 2000 - 5000V, 0 - 25000 M ohms
 - ii) Hand operated megger - 0.5 KV/1.0 KV/2.5 KV, 200 - 100 M ohm
- b) Earth resistance tester 0 to 1, 10, 100 ohms
- c) Transformer oil test kit
- d) Torque wrench
- e) Voltmeter ac 0 - 125 - 250 - 625 V ac
- f) Ammeter ac 0 - 2A - 10A ac.
- g) Wattmeter - ac/dc - 0 - 125 - 250 V 0-5-10A.
- h) Multimeter - analogue: acV 2.5V - 2500V, ac A - 100 mA - 10 A
dc V 25.V - 2500V, dc A - 50mA - 10A
Resistance - 0 - 200 M ohms
digital : voltages ac & dc - 100mv - 1000 V
current 10-mA - 10A Resistance - 0-20 M ohms
- i) High vacuum stream line oil filter of 6000 LPH for mineral oil and 1000- 600 LPH for silicone oil for transformer dryout.
- j) Variac - 1 phase - 5A, 15A 3 phase - 10A, 20A.
- k) Primary injection kit - 0-5000 A.
- l) Secondary injection kit - 0-5A.
- m) HV Test kit - 50 KV AC 400kVA.
- n) Wheatstone bridge - 0.05 m ohm - 100 ohm.
 - o) Oscilloscope.
 - p) Oil. Tank for transformer oil.
- q) Air compressor.
- r) Vacuum pump.
- s) Phase sequence meter - 110V - 450V - 25 to 65 Hz.
- t) Frequency meter - 0 - 115 - 230 - 4500 - 45 -601/s.
- u) Tong tester - 0 - 5A - 10A, 30A, 60A, 150A - 600A.

- v) Tachometer etc.
- x) mA Source
- y) Standard temperature gauges
- z) Temperature oil bath
- aa) Micro Ohm Meter for contact resistance measurement of circuit breakers.
- bb) Event recorder for measurement of closing and opening time (with micro second accuracy)
- cc) DC Power Supply , 24 V ; 5A
- dd) Single Phase Variac 250V; 10A
- ee) Three Phase Variac 415V
- ff) Function Generator
Soldering irons, soldering pump, Vacuum cleaner, Air blower etc.
- hh) Tan Delta Test kit
- ii) Oil specific gravity and PPM measuring equipment
- jj) Dew point measurement instrument

6.29 RECOMMENDED LIST OF TOOLS & PLANTS TO BE ARRANGED BY CONTRACTOR FOR ELECTRICAL WORKS

S.NO	DESCRIPTION
01	Steel wire ropes
02	Chain pulley block/turfer
03	2 " size pipe bending machine
04	Grinding machine
05	Drilling machines : 1/4" , 1/2" , 3/4" , 1 "
06	Copper tube bender and cutter sizes 6 mm ;8 mm ;1/2",1/4"
07	Dye sets for threading upto 2 " pipe
08	Set of spanners
09	Allenkey sets
10	Bench vice
11.	Spirit level
12	Tap sets for both BSP & NPT threads upto 1 "
13	Measuring instruments like micrometers, calipers etc.
14	Welding generator
15	Welding transformer
16	TIG Welding set
17	Mechanical tool kit for fitters
18	Electrician tool kit
19	Crimping tool
20	Flood light fittings
21	Fire extinguishers
22	Distribution boards with power cable complete as required
23	Hydraulic test pump rating 750 Kg/SQ.cm
24	Painting brush
25	Fire proof tarpaulin
26	Safety belts & safety helmets
27	Telephone sets

6.29.1 ACCURACY REQUIREMENT OF TESTING INSTRUMENTS

SI. No	INSTRUMENT / TOOL	RANGE	ACCURACY
1	Power Pack	0 to 50V DC, 3A	+ 2%
2	Analog Multimeter	Voltage 2.5 to 2500V AC	+ 1.0%
		Current 100 mA to 10A AC	+ 2.0%
		Current 250 micro A to 1A DC	+ 1.5%
		Resistance upto 100 ohms	+ 3.0%
		Voltage 2.5V to 2500V DC	+ 1%
3	Digital Multimeter	Voltage 200mV to 1000 V DC	+ 1% + 1 digit
		Philips Voltage 200mV to 1000 V AC	+ 1% + 1 digit
		Hcl Current 200mA to 20 A AC	+ 0.8% + 1 digit
		Philips Current 20 mA to 20 A AC	+ 0.8% + 1 digit
		Resistance (Hcl) 2120 200* to 200M*	+ 0.5% + 1 digit
		Resistance (Hcl) 2105 200* to 200M*	+ 0.25% + 1 digit
		Hcl Voltage 200mA to 750 V	+ 0.8% + 1 digit

SI. No	INSTRUMENT / TOOL	RANGE	ACCURACY
4	Vibration Measuring Equipments	Philips Current 20 mA to 20 A DC	+ 0.5% + 1 digit
		Hcl Current 200 mA to 010 A AC	+ 1% + 1 digit
5	Secondary Injection Kit	Velocity upto 50 mm/sec.	+ 0.5% mm/sec
		Displacement upto 300 microns	+ 2 microns
6	Motor operated Megger	Upto 5A	+ 0.5mA
7	Tongue tester	Upto 200 Ohms	+ 5% at Centre scale
8	Tachometer (Hand held)	0/300/600A AC	+ 5%
		0 to 300A DC	+ 5%
9	Phase Sequence Meter	0 to 4000 rpm	+ 5%
10	Three Phase Variac		N/A
11	Feeler gauges	15 A Capacity	N/A
12	Dial gauges	300 mm long and 100 mm long	+ 2 microns
13	Hand operated Megger 500 V / 1000V	Q	+ 0.01 mm
14	Motorised Megger 2.5 KV	Upto 200 M Ohms	+ 5% at Centre Scale + 10% at end of Scale
		Upto 200 M Ohms	+ 5% at Centre Scale + 10% at end of Scale
15	Earth Megger (Tester)	0 to 1, 10, 100 Ohms	+ 5% at Centre Scale range
16	AC tongue Tester	0 to 300A AC	+ 3%
17	DC Tongue Tester	0 to 300A DC	+ 5%
18	High Voltage test Kit	Upto 50 KV AC	+ 10%
		Upto 70 KV DC	+ 10%
19	Tacho Generator (Mech)	0 to 4000 rpm	+ 0.25%
20	DC Ammeter	0 to 300 A	+ 10%
21	DC Voltmeter	0 to 500 V	+ 10%

6.29.2 OTHER REQUIREMENTS OF CONTRACTORS'S INSTRUMENTS T&P

- a. The contractor shall arrange all the above. T&P, equipment and instruments as indicated except testing instruments which are proprietary in nature.
- b. The contractor at his cost shall arrange all cranes and truck/tractor, trailers required for material handling purpose and also cranes required for erection. If contractor requires any equipments other than what is mentioned as free issues from BHEL same can be hired from BHEL on chargeable basis subject to availability.
- c. Any other tools and plants instruments and equipment required in addition to the above other than propriety type T&P/Instruments for the successful completion of this job shall be arranged by the contractor at his cost.
- d. Necessary accessories for the above shall also be provided by the contractor.
- e. The above instruments/equipment shall be sent for testing and calibration wherever from time to time and maintained by contractor as required by BHEL.
- f. List of such agencies and periodicity of calibration required for different instruments shall be furnished by BHEL at site.
- i. Contractors shall arrange experienced/qualified persons for using these calibration instruments at laboratory and also at work spot.
- j. Wherever frequent calibration is required, contractor shall arrange adequate number of instruments such that the work does not suffer for want of test instruments.

6.30 DRAWINGS FOR REFERENCE (BID PURPOSE ONLY)

The following drawings are enclosed for general information to the tenderer.

- 1 Out line General arrangement of 150 MVA Transformer
- 2 Table of fittings for OGA -150 MVA Transformer
- 3 Outline General Arrangement of 16 MVA Transformer
- 4 Table of fittings for OGA - 16 MVA Transformer
- 5 Line Diagram for IP Bus duct
- 6 Layout of IP Bus Duct -12 KV
- 7 Structural Layout of Bus Duct support
- 8 GA of LAVT Cubicle
- 9 GA of NGR Cubicle

NOTE

01. Minimum Number of persons to be indicated monthwise.
02. Above deployment plan shall be discussed with BHEL Site Engineer and necessary changes shall have to be made by the contractor as per discussion. If required, any additional deployment during execution of the work shall have to be arranged by the contractor for meeting various schedules/targets set by BHEL without any additional compensation.
03. Resident Engineer should have a minimum qualification of Engineering Degree or Diploma in Engineering with 15 years of experience in Thermal Power Station.
04. Supervisor should have a minimum qualification of Diploma in Engineering or a graduate with 10 to 15 years of experience in Thermal Power Station.
05. Lab Technicians should have experience in Thermal Power Stations.
06. Contractor should have one Store Keeper and one Transport Supervisor for the safe transportation of materials.

APPENDIX - VI B

DEPLOYMENT PLAN FOR MAJOR TOOLS AND PLANTS / INSTRUMENTS

S.NO	CATEGORY	MONTHS	PRESENT
		1 2 3 4 5 6 & SO ON	LOCATION
01	Welding Generators		
02	Welding Transformer		
03	TIG Welding sets (air cooled)		
04	Insulation Tester a. Motorized Megger 1000 & 5000 V Grade b. Hand operated Megger 500 & 1000 V Grade		
05	Earth resistance Megger		
06	Transformer oil testing kit		
07	Torque wrench		
08	Volt Meter/Ammeter/ Avometer/other instrument		
09	Multimeter/Test lamps/ Field telephone sets/ different gauges		
10	High vac steam line filter of 6000/4500 LPHfor transformer dryout		

S.N O	CATEGORY	MONTHS	PRESENT
		1 2 3 4 5 6 & SO ON	LOCATION
11	3 phase/Single phase Variac 15 Amps		
12	Primary and Secondary Injection testing kits.		
13	HV test kit		
14	Resistance measurement unit		
15	Oscilloscope		
16	5 Amps DC Power Supply unit		
17	Crimping Tools with various sizes of dyes.		

NOTE

01. The list of Tools and other plants to be deployed for this project may be indicated by the tenderers separately.
02. Above deployment plan shall be discussed with the site engineer and necessary changes shall have to be made by the contractor as per discussions. If required, an additional deployment during execution of work shall have to be made by the contractor for meeting various schedules/targets set by BHEL without any additional compensation.

BHEL PS:SR

Format No. **CP: FEX**

CALIBRATION RECORD OF SUB-CONTRACTOR'S INSTRUMENTS

Name of Site :

Name of Sub-contractor :

Sl.No.	NAME OF INSTRUMENT	INSTRUMENT REGN. NO.	DATE OF		PERIODICITY OF CALIBRATION	CALIBRATION DETAILS
			ENTRY	EXIT		
						DATE OF CAL. CAL. AGENCY NEXT DUE DATE DATE OF CAL. CAL. AGENCY NEXT DUE DATE DATE OF CAL. CAL. AGENCY NEXT DUE DATE

SIGN OF SITE CIC

SECTION VII
NALCO CPP EXPANSION, ANGUL (2X120 MW)
TECHNICAL REQUIREMENTS AND GUIDELINES FOR
INSTALLATION, TESTING, COMMISSIONING AND SUPPLY ITEMS
OF HT/LT ELECTRICAL PACKAGES

7.1.0 INSTALLATION, TESTING & COMMISSIONING IN GENERAL:

The stages of completion of various works shall be as follows:

Completion

- Equipment shall be considered to be completely erected when the following activities have been completed.
- Moving of all equipment to the respective foundations.
- Fixing of anchor bolts or tack welding as required.
- Leveling and alignment of equipment.
- Assembling of all accessories such as relays, CTs, PTs, meters, instruments etc. as described in the job specification.
- Cable laying, termination with continuity check.
- Applying of finishing coat of paint.

All the equipment shall be tested at site to know their condition and to prove suitability for required performance. The site tests and acceptance tests to be performed by contractor are detailed below.

The contractor shall be responsible for satisfactory working of complete integrated system and guaranteed performance.

7.1.0 SITE TESTS AND CHECKS

a) General

All the equipment shall be tested at site to know their condition and to prove suitability for required performance.

The test indicated in following pages shall be conducted after installation. All tools, accessories and required instruments shall have to be arranged by contractor. Any other test which is considered necessary by the manufacturer of the equipment, contractor or mentioned in commissioning manual has to be conducted at site.

In addition to tests on individual equipment some tests/checks are to be conducted/observed from overall system point of view. Such checks are highlighted under miscellaneous tests but these shall not be limited to as indicated and shall be finalized with consultation of client before charging of the system.

The contractor shall be responsible for satisfactory working of complete integrated system and guaranteed performance.

All checks and tests shall be conducted in the presence of client's representative and test results shall be submitted in six copies to client and one copy to Electrical Inspector. Test results shall be filled in proper proforma.

After clearance from Electrical Inspector system/equipment shall be charged in step by step method.

Based on the test results clear cut observation shall be indicated by testing engineer with regard to suitability for charging of the equipment or reasons for not charging are to be brought by the contractor.

b) Trial Run Test

After the successful test of each equipment as per standard test procedure the entire control system shall be put on trial run test on actual site conditions and operation of the system.

c) Acceptance Test

The acceptance test on the system shall be carried out by the supplier as per mutually agreed test procedures to establish satisfactorily functioning of the system as a whole and each equipment as part of the system.

7.2.0 BUSDUCTS - ISOLATED/SEGREGATED PHASE BUSDUCTS

7.2.1 HANDLING AND STORAGE

General

Busduct form the main electrical connections between the Generator and associated generator transformer and tap-off to UAT, VT & SP cubicle and GCB. The ducts are made of aluminium sheet which house the busbar conductors supported on post insulators. e duct assembled are suitably supported on the structures in the station. The bus enclosure assembled are despatched with the insulators assembled and the conductor are sent either loose or assembled inside the duct, keeping in view the erection necessities and transport limitations.

7.2.2 INSPECTION AT SITE :

When the packages are received at site, these must be checked for the following:

- a. Completeness and correctness of the consignment. (Compare with delivery documents)
- b. Physical damage if any during transit.

7.2.3 HANDLING DURING ERECTION :

The busducts are in unpacked conditions, therefore, great care is necessary in handling. Ensure that :

- a. While lifting enclosure assemblies manila ropes are passed round the busduct enclosure near the support channels.
- b. All shipping steel clamps are to be tightened and busbars do not slip out while handling, if the busbar is assembled in the enclosure.
- c. While inserting and mounting the busbar in the enclosure care is taken that the busbar does not hit and damage the insulators.
- d. Eye bolts are used while lifting the cubicles.

On completion of 7.2.3 items must be returned to original packing cases unless required for immediate erection.

7.2.3A Caution

1. When inspecting the enclosures assemblies etc. the wooden packings, braces and polythene covers should be replaced, if removed, to prevent damage and ingress of duct and moisture.
2. Aluminium being softer material, great care must be taken in handling enclosures and other aluminum items.
3. If the site conditions make it impossible to return the items to the cases for storage:
 - a. Nothing must be laid direct on the ground.
 - b. All items must be protected against weather and damages.

7.2.4 HANDLING OF BUS DUCT.

Handling from delivery station to power station stores :

1. Use suitable slings to lift the packages
2. No impact should come on the packings while loading. Do not drop from height.
3. Do not stack busduct packings one above the other; also avoid stacking of heavier items on busduct packings.

7.2.5 DURING UNPACKING, HANDLING AND STORAGE

DO's

1. Check all the packings for any damage during transit.
2. Open the packings carefully.
3. Verify material as per shipping list and report any shortage/damage immediately.
4. Keep material in original packings unless required for erection.
5. Ensure that Manila ropes are used for lifting the busduct.
6. Check the tightness of shipping steel clamps while lifting busduct assembly with busbar in position.
7. Ensure that CTs, LAs, capacitors, N.G. transformer, grounding resistor, fuses, insulators, wall bushings, moulded and rubber items and flexibles are stored in well ventilated area.

DON'Ts

1. Don't destroy any markings.
2. Don't drop packings from height.
3. Don't stack heavier items on busduct packings.
4. Don't keep door of cubicle open during storage.
5. Don't lay down unpacked material directly on the ground.
6. Don't cause damage or scratches by dropping, dragging etc. on fragile items such as CTs, PTs, Insulators, rubber items etc.

7.2.6 DURING ERECTION & COMMISSIONING :

DO's

1. Carry out pre-lay survey to verify the position of various equipment to be connected, levels of floors and positions of cutouts.
2. Keep the layout drawing etc. ready for reference.
3. Draw the material from stores as per erection sequence.
4. Ensure alignment and proper matching of various enclosures and busbars.
5. Ensure proper alignments of epoxy cast CTs and seal-off bushings before final tightening of hardware.
6. Make the busbar joints as per the instructions.
7. Ensure aluminium welding by qualified welder only.
8. Take care for proper sealing while joining the enclosure.
9. Ensure proper earthing of enclosure and structure as specified.
10. Check wiring as per relevant wiring diagram.
11. Ensure that CT secondaries are shorted and grounded before HV test on busduct.

DON'Ts

1. Don't allow accumulation of dirt or foreign material inside the enclosure during erection.
2. Don't overtighten the bolts.

3. Don't hammer the bolts etc. while joining the busbars if holes are not matching.
4. Don't forget any foreign material inside the enclosure.
5. Don't allow aluminium welding by unqualified welder.
6. Don't subject IAS, capacitors, and PTs to HT test as these are pre-tested and test at site is not required.
7. Don't subject NG transformers to over voltage as these are pre-tested.
8. Don't apply rated voltage unless pre commissioning checks are completed.

7.2.7 ERECTION INSTRUCTIONS

A. Packing and Shipping

Layout drawing and main bill of material (M.B.O.M) or shipping list should be referred to for identification of various items. All the drawings necessary for assembly and erection are furnished separately.

Busducts are usually despatched as single phase assemblies generally assembled with busbars. The busbars are braced with steel clamps to avoid any damage to insulators and displacement of busbars during transport. Structures, hardwares, flexibles, and other miscellaneous items are packed separately.

B. Marking :

Following markings are done with paint on busduct assemblies and cubicles for identification :

- a. Project name and unit number
- b. Item no of main BOM this is encircled
- c. Phase marking R, Y or B
- d. Work order number
- e. Drawing number and item/variant number
- f. Arrow indicating direction towards transformers end. Direction of arrow shall be decided from lay out.

C. Similarly loose items are also identified by suitable marking on tags.

7.2.8 PRE LAYOUT SURVEY

Before starting the erection work the centre lines of the complete busduct installation, location of connected equipment such as main transformer, unit auxiliary transformer, VT & SP cubicle, NG Cubicle etc. with respect to generator central line should be established and marked clearly. The various levels of floor, ceiling, terminal position of main transformer, unit auxiliary transformer etc. should also be verified. Any deviations in this regard should be recorded and necessary remedial measures should be taken. In case of any substantial deviation which may effect the erection of busduct installation, the same should be referred to the design engineer. The remedial measures should be planned in advance, which may consist of levelling by suitable packers chipping of the concrete floor or wall etc. or rectification of the components with the concurrence of engineers.

7.2.9 PROVISION OF FOUNDATION BOLTS & EMBEDDED ITEM

In the power station, busduct is supported on various floors, halls, ceiling, etc. and support structure is suitably attached to the building. For this foundation bolts, embedded items are grouted on the number of locations as per foundation drawing.

7.2.10 SEQUENCE OF ERECTION

Normally the following sequence of erection is recommended.

A. Erection of steel work :

First, all the vertical structures are to be installed, levelled and foundation bolts grouted. Next, place all the longitudinal cross channels in position, adjust the level and bolt/weld them.

Check up the correctness of levels and positions of various installed structures. For installation of foundation bolts refer foundation details drawing of the project.

B. Erection of Enclosures :

Before the installation of enclosures in position each assembly of enclosure and conductor complete with insulator supports is to be checked for correctness and cleaned on the working floor.

The various enclosures assembled are to be erected as per layout drawing. After placing the assemblies in position the packing braces/steel clamps inside the ducts are to be removed.

Some of the busduct assemblies will be self supporting only when they are welded to adjacent enclosures, as such some temporary scaffolding is necessary to support these enclosures during erection, levelling and welding.

C. Handling of Busducts :

For handling of busducts specified instructions should be followed.

D. Sequence of erection-enclosure assemblies :

In positioning the various enclosures assemblies the following sequence is recommended :

E. Indoor Portion :

(a) Neutral Side

Complete the assembly of top chamber/neutral shorting chamber at the working floor as per the drawing. Connect copper flexibles on the generator neutral terminals, and fix it the generator plate. Provide temporary support as necessary. Complete the assembly of bottom chamber (if applicable) alongwith CTs and wiring as per drawing at the working floor and match with the top chamber (if applicable). Now fix the supporting structure. Assemble N.G. Transformer and N.G. Reactor and complete the terminal connections.

Note : Before fixing top chamber / bottom chamber, care should be taken that shunts are welded on line side busduct as shown in lay out drawing :

(b) Line Side

Assemble copper flexibles and connections with generator line terminals. Match each phase generator enclosure with generator plate and fix to the support structure. Complete the generator terminal bolted connections.

Place P.T cubicle in position match and connect with the respective tap off.

F. Outdoor Portion :

Position the wall frame at the power house wall, place the wall duct and inset the rubber sealing ring over the enclosure. Complete the wall frame assembly.

Place the remaining enclosures on the structure starting from the wall duct and complete the main run to generator transformer. From main run tap-off enclosures are to be connected to unit auxiliary transformers, accommodating current transformers, flexible connection, disconnecting link and rubber bellows.

The alignment and exact locations of ducts may be verified before proceeding for making the assemblies of make-up piece rubber bellows, wall frame and bolted/welded joints of conductor and enclosures.

G. Busbar Joints :

Busbar joints may be bolted type or welded type as specified for the installation. For making the busbar joints, it is essential that specified procedures and precautions are followed.

H. Cleaning of Busduct

Before putting the split covers, enclosures make up pieces (welded to enclosure) & covers of inspection windows, all the insulator should be cleaned again. The busduct should also be cleaned and dried up for any moisture/condensates. Thoroughly check the interior of every enclosures and ensure that these are free from any foreign matter.

I. Inspection of windows, covers, etc.

Finally, the split covers, inspection windows and make-up piece may be assembled. The assembly of split cover, inspection windows and make-up pieces should be done as per recommended procedures and if should be ensured that proper sealing is achieved.

7.2.11 BUSBAR BOLTED JOINTS

A. Aluminium to Aluminium Joints (Un plated)

Wipe the contact surfaces with dry clean cloth to remove any dirt, dust and moisture and smear these with recommended jointing compound. Clean the surfaces under the compound by breading with dry coarse emery cloth or stainless steel wire brush. Wipe the surfaces with a clean dry cloth and immediately make a light application of jointing compound. Close up the joints and wipe off excess compound.

B. Aluminium to Copper Joints :

Cleaning of Aluminium surface (Unplated)

Follow Instructions given under 7.2.11A above and apply jointing

ompound. Cleaning of copper surfaces (unplated)

Clean the copper contact surface with emery cloth and wipe the surface with clean dry cloth.

Cleaning of copper aluminium surfaces (unplated)

Clean the contact surface with dry cloth to remove dirt, dust and moisture. Apply a light coating of jointing compound.

C. Aluminium to Copper Joints using bimetallic strip

For cleaning of aluminium and copper surfaces follow instructions given under 7.2.11 A&B above. Apply jointing compound to aluminium and copper surfaces.

The contact faces of bimetallic strip should also be cleaned as per the above practice and jointing compound applied.

Note : Bimetallic strip is inserted between the copper and aluminium surfaces. Care should be taken that copper faces copper surface and aluminium faces aluminium surface.

D. Cleaning of copper surfaces (plated)

Clean the contact surface with dry cloth to remove dirt, dust and moisture.

Note : Wire, brush, emery cloth or jointing compound containing metallic particles or other abrasives should not be used on plated surfaces.

7.2.12 CONTACT PRESSURE

To obtain correct tightening pressure on contact surfaces following torques are recommended for various bolt sizes.

Bolt Size	Recommended Torque	torque	Spanner Capacity
M10	0.85 to 1.3 NM (20-30 Ft-lb)	0.85 to 1.3 NM	(20-30 Ft-lb)
M12	1.3 NM to 1.7 NM (30-40 Ft-lb)	0.85 to 4.3 NM	(20-100 Ft-lb)
M16	1.7 to 2.1 NM (40-50 Ft-lb)	0.85 to 4.3 NM	(20-100 Ft-lb)
M20	2.1 to 2.5 NM (50-60 Ft-lb)	0.85 to 4.3 NM	(20-100 Ft-lb)

Alternatively tighten the nut till belleville washer becomes flat. Then unscrew the nut by about 1/8 th. turn.

7.2.13 RECOMMENDATION FOR WELDED JOINTS

A. Circumferential weld circular section :

A FULLY penetrated, fully fused welded with a 10%T (4mm max) reinforcement is required.

Welding conditions M.I.G. Process

Filler wire : 1.6mm dia (NG 21 with 5% silicon)

Angle : 10° to 15° Forehand

Cleaning	:	Decrease and scratch brush
Setting	:	250A to 320A, 28 to 30 Volts (Dependent on tk)
Process	:	4 off 25mm long equispaced tack welds
Gas supply	:	50 Cu. ft/hr argon
Shield	:	5/8" dia

B. Tubular Conductors :

Tubular Conductors are used in tee-off connections.

Welding conditions M.I.G. Process

Filler wire	:	1.6 mm dia (NG 21 with 5% silicon)
Angle	:	10° to 15° Forehand
Cleaning	:	Degrease and scratch brush
Setting	:	215A to 275A, 22 to 2 Volts
Gas supply	:	50 Cu. ft/hr argon
Shield	:	5/8" dia

C. Enclosures

Fillet weld for make up pieces/shunts. Tack weld at four places.

Welding conditions M.I.G. Process :

Filler wire	:	1.6mm dia (NG 21 with 5% silicon)
Angle	:	10° to 15° Forehand
Cleaning	:	Degrease and scratch brush
Setting	:	200A to 300A, 25 to 30 Volts (Dependent on thickness)
Gas supply	:	50 Cu. ft/hr argon
Shield	:	5/8" dia

D. Drain valve and welding :

Owing to the dissimilar thickness used for this fillet weld, the arc must be directed into the pad only and not allowed to melt away and enclosure.

7.2.14 WELDED BUS ENCLOSURE JOINTS

Bridge the gap between the bus enclosure by means of make up pieces and clean the area by paint removed which is to be welded. Tack weld the make up pieces before final filled weld all around.

7.2.15 WELDED JOINTS OF SHUNTS

Various locations of shunts to be welded to the enclosures are shown in layout drawing.

7.2.16 DRAIN VALVE WELDING (IF APPLICABLE)

Mark the location as per lay out and drill 10mm dia hole at the bottom most point of enclosure. Tack weld the drain valve pad to enclosure ensuring proper alignment of pad hole with enclosure hole. Weld continuously as per jointing recommendations. Clean with wire brush and point for final finish.

7.2.17 FIXING OF NEOPRENE SEAL :

Enclosures are fitted with access covers. Each cover is fitted with four pieces of neoprene seal and held in position by bolted clamps.

(Note : Only one cover should be removed from enclosure at any time to minimise the air flow into the enclosure).

7.2.18 EARTHING OF ISOLATED /SEGREGATED PHASE BUSDUCT AND CUBICLES

A. General

One end of the electrical continuous enclosure should be earthed to station earth at the shunt location where all the three enclosures are shorted. Location of earth points are shown in the layout drawing. For this purpose two drillings are to be done on these shunt to suit at site and two separate earth strap are to be connected to the station earth thus ensuring double earthing.

In some assemblies (such as transformer hood etc) due to short length of enclosures shunts are not provided. In such cases, each phase enclosure should be separately earthed.

One point of the earth phase split cover, rubber bellow clamping strap should be electrically connected to enclosures and in turn enclosures should be earthed.

B. Cubicle earthing :

Each cubicle is provided with two number of earthing terminals. These terminals are generally located on side face of the cubicle. Both the terminals are to be connected independently to the station earth by suitable connectors.

For earthing the top and bottom C.T. chambers, station earth can be connected to each chambers of two locations for double earthing.

7.2.19 SITE TESTS ON ISOLATED /SEGREGATED PHASE BUSDUCT

A. Physical Checks :

Design survey which include dimensional checking of electrical clearances and cleanliness of the installation.

B. Cleanliness :

The inside of all enclosures, outside of conductors and insulators should be free from dirt, all, grease, swaft and any deposits, special attention should be paid to the insulators and seal off bushings and oil moisture is to be removed and surfaces polished with a dry soft clutch. All panels/inspection windows cover are to be replaced after cleaning operation.

C. Power Frequency High Voltage Test

Preparation :

Following equipment must be disconnected from busbars removing the bolted link and grounded suitably prior to conducting this test :

- a. Generator terminals
- b. Unit auxiliary transformer terminals
- c. Generator transformer terminals
- d. Neutral grounding transformer HV terminal
- e. Lightning arresters
- f. Capacitors
- g. Potential transformer.

It is important to ensure that secondaries of all the current transformers mounted on busbars are shorted and grounded properly before conducting this test.

Ensure that all insulators seal-off bushings are cleaned free from any dust, grease and moisture etc before test.

During the test, ensure the following

- a. The generator rotor is kept stationary
- b. H.V. Circuit breakers on system side are kept in the open position.

D. Test Voltage :

The test voltage shall be attenuating current on any frequency between 25 hertz to 100 Hz and approximately of sine-wave form. The r.m.s. value shall be as given in table-1 below :

For A.C. voltage duration of test shall be one minute.

The test with D.C. at a voltage not in excess of the values given in Table-1, Column-3 for the corresponding rated voltage may be substituted for the AC test prescribed.

Table - 1

Rated Highest System Voltage	Test Voltage (A.C.)	Test Voltage (D.C.)
Upto & Including	KV	
3.6	16.8	
7.2	21.6	
12	28	
24	44	
36	60	

E. Meggar-Checks :

Before the application of high voltage, check the insulation of each bus, conductors by means of 2.5 KV meggar. A value e. 100 mega ohms is expected under normal conditions. However, during mainly season this value may fall down considerably and drying up by hot air may be necessary before the test. Minimum acceptable value is around 20 mega ohms. After the application of high voltage the insulation value is checked gain.

F. Application of Test Voltage :

Corresponding test voltage as indicated in Table-1 shall be applied in turn between each phase conductor and its enclosure which shall be kept at ground potential. Remaining two phase conductors and their enclosure shall be properly as in consistent with its value being indicated by the measuring instrument. The full test voltage shall be then maintained for specified duration. Each bus including tap-off must withstand the above test voltage.

7.2.20 SITE TEST RECORDS ON ISOLATED / SEGREGATED PHASE BUSDUCTS :

Test conducted on date... Site ...

Power Frequency high voltage test :

Instrument ...

Phase	Meggar Reading before HV test after HV test	HV applied & duration A.C./D.C.	Leakage current	Remarks
R				
Y				
B				

7.3.0 TRANSFORMER

7.3.1 INSTALLATION

To ensure that a Transformer will function satisfactorily, it is important that handling, lifting, storing and assembling are carried out with great care and cleanliness by experienced personnel who know the various working operations very well.

7.3.2 INSPECTION

In connection with receiving and unloading at site, and at the final storing place before assembling, the transformers shall be inspected carefully. External visible damages as dents, paint damage etc. may imply that the transformer has been subjected to careless handling during transport and/or re-loading, and a careful investigation is therefore justified.

After the arrival of the material at receiving points, before unloading, the condition of packing and of the visible parts should be checked and possible traces of leaks verified (condenser bushing). If necessary, appropriate statements and claims should be made.

Drums containing oil which have despatched separately should be examined carefully for leaks or any sign of tampering,. All drums are despatched filled upto their capacity and any shortage should be reported.

Check immediately the gas pressure at the arrival. A positive indicates that the tank and the transformer components respectively are tight, and that the active part including the insulation materials is dry.

If there is no positive gas-pressure, transformer should be immediately filled with dry Nitrogen gas at a pressure of 0.17 kg/Cm² (2.5 psi) without loss of time.

Otherwise, it should be checked if the core isolation is satisfactory and that accessories packed separately have not been damaged during transportation .

7.3.3 UNLOADING

Whenever rollers/trolleys are supplied with transformer, movement of transformer at site is carried out by mounting these rollers/trolleys.

Alternatively for movement of transformer from loading bay to actual site of the equipment, skidding on greased rails etc can also be resorted to.

7.3.4 STORING

Dismantled equipment and components are packed to the protected against normal handling and transport stresses. The instructions for lifting given on the packages, must be complied with to avoid damages.

Goods stored outdoors must not be placed directly on the ground, and should be covered carefully with tarpaulin or similar materials.

Oil drum should be stored in horizontal (lying) position with both the bungs also in horizontal position.

7.3.5 LIFTING

Lifting devices on the transformer tank are dimensioned of lifting of the complete transformer filled with oil. The positioning of the lifting devices, permissible lifting angles, minimum height to crane hook and transformer weight, appear from the OGA drawings. Check at lifting of complete transformer that the lifting wires/ropes are not in contact with bushing or other components on the cover.

For lifting with hydraulic jacks, the transformer is provided with jacking pads dimensioned for lifting of complete transformer filled with oil. The position of the pads appear on the OGA drawings.

7.3.6 CHECK POINTS BEFORE STARTING AND DURING ERECTION

a. Check points before starting erection.

1. Conditions of leads
2. Bracing, clamping of leads
3. Connections
4. Tap changer checks
5. General conditions of insulation
6. Core check that it has not moved in transit.
7. Core-ground; this is checked with the megger after removing earth connection
8. CTs, including the secondary leads and their passage through metal parts
9. Check that shipping frame for bushings have been removed.
10. Check that coil position has not moved in transit
11. Check for dirt, metal swarf, moisture
12. Check that the bushing leads set without being too close to ground or other points of different potential.

b. Check-points during erection:

By means of the part list and the transformer/reactor OGA, the assembling of a fully completed transformer is carried out according to the following instructions. The following precautions are to be taken:

- i. Fire-fighting equipment shall be available at the oil-treatment equipment as well as at work on and adjacent to the transformer.
- ii. Welding work on or adjacent to the transformer shall be avoided, but if this is not possible, the work shall be supervised by fire-protection personnel.
- iii. Smoking on or near the transformer shall not be allowed.
- iv. Transformer tank, control cabinet etc, as well as assembling and oil-treatment equipment shall be connected with the permanent earthing system of the station
- v. Check that there is no overpressure in the transformer when blanking plates or connection lids are to be opened.

- vi. All loose objects, tools, screws, nuts etc.. shall be removed from the transformer cover before opening the connection and blanking lids.
- vii. All loose objects (tools, pencils, spectacles etc..) shall be removed from the boiler- suit pockets etc. before starting the work through man holes.
- viii. Tools to be used inside the transformer e.g. for tightening of screws-joint-shall be fastened to the wrist or another fixed point by means of cotton tape or string.
- ix. Tools with loose sleeves and tools with catches must not be used at work inside the transformer.
- x. Greatest possible cleanliness shall be observed at work inside the transformer, and at handling of part to be mounted inside the transformer.
- xi. Fibrous cleaning materials should not be used as it can deteriorate oil when mixed with it.
- xii. All components despatched separately should be cleaned inside and outside before being fitted.
- xiii. A Transformer is best protected from damp hazard by circulating warm, dry, de-aerated oil through it until its temperature is 5 C to 10 C above ambient. This should be done before allowing external access to the interior of the tank. The warm oil should be circulated all the time transformer is open to atmosphere.
- xiv. Oil pump & all joints in the oil pipe work should be air tight to avoid entrance of air through leakage joints.
- xv. The active part (core and winding) should be exposed to the surrounding air as short time as possible. Open therefore only one blanking plate or connection lid at a time for remounting of bushing, valves etc.
- xvi. Objects which-despite all precaution are dropped inside transformer/reactor, must absolutely be brought up from the equipment.
- xvii. Check that the oxygen content inside the transformer tank is minimum 20% if a person is to enter the tank..

7.3.7 ASSEMBLY

Assembly of wheels Bushing Valves, cooling device, Oil conservator, Pilol Flanges, Blanking plates and accessories like cooling fans, pumps, OLTC and components for supervision and control oil level indicator, flow indicators, gauges, Buchholz relay, PRV, thermometers etc. are assembled according to leaflet/description valid for the components.

7.3.8 OIL FILLING

The following procedure is recommended.

- (i) Close and blank the valve to isolate the conservator from main tank. Fill the oil in transformer under vacuum upto Buchholz level as per instructions given else where.
- (ii) After filling the oil in transformer and breaking the vacuum, oil can be filled in the conservator either through reactor or by drain valve.
- (iii) Remove the inspection cover (ii) provided on the side of the conservator and check the air cell assuring that it is inflated. The air must remain in fully inflated condition during oil filling operation. If the air cell is found deflated fit the inspection cover and inflate the air cell with dry air/nitrogen gas to 0.035 kg/sq.cm max . A gauge may be put by removing plug . After filling close these connections.
- (iv) Remove air release plugs provided on top of the conservator.
- (v) Slowly pump the oil through main reactor/drain valve . Temporarily stop filling operation when oil starts coming from opening after ensuring that no air bubbles come out through these air release holes. Fit the two air release plugs.
- (vi) Continue oil filling till oil start coming from air release plug stop oil after ensuring that no air bubbles come out. Fit the plug .
- (vii) Now release the air pressure held inside the air cell from point and continue oil filling until magnetic oil gauge indicates 35 deg. C level.
- (viii) Remove oil pump and connect air cell to breather from point . Also remove pressure gauge and put plug .
- (ix) The system is now properly filled. Air release plugs are fitted in normal operation.

7.3.9 EQUIPMENT FOR OIL-FILLING UNDER VACUUM

- (i) High-vacuum 2 storage oil filtration plant provided with thermostat-controlled oil heaters and vacuum-proof hoses with dependent vacuum pumping system for tank evacuation. Capacity:6000 lph
- (ii) Oil-storage tanks provided with silica-gel breathers and inlet/outlet valves for oil circulation. Recommended capacity 20KL
- (iii) Vacuum gauges provided in filtration plant.
- (iv) Equipment for measurement of electric strength (BDV) of oil - 100 kv set.

- (v) Equipment for moisture content of oil.
- (vi) Equipment for measurement of Resistivity and Tan delta at 90 C.
- (vii) Transparent vacuum-proof tubes for checking of oil-level during oil filling.
- (ix) Valves, fitting, gaskets etc.
- (x) Dry nitrogen cylinders.

7.3.10 COMMISSIONING

Testing after Assembly of the Transformer

After the transformer/has been assembled at site, it shall be tested in order to check that it has not been damaged during transport and assembly to such an extent that its future operation will be at risk. Regarding the performance of the test, refer to the testing method as per standards. The results of the test shall be documented.

COMMISSIONING CHECKS

SL NO	DESCRIPTION
1.	Breather Silica gel (Blue when dry)
2.	Oil in the Breather housing cup.
3.	All valves for their correct opening and closing sequence.
4.	Oil level in conservator tank.
5.	Oil in cooling system.
6.	Oil level in bushings.
7.	Release air, wherever necessary.
8.	Cooling accessories (Pump motors, Fan motors etc.) for direction and O/L setting.
9.	Buchholz, oil level indicator, pressure gauges, thermometer, Temp. indicators etc.
10.	Neutral earthing.
11.	Earth Resistance of Electrodes.
12.	Earthing of bushing test tap.
13.	Check oil leakage for 24 hrs.

14. Check Auxiliary circuit voltage (415 V)
15. Calibration of OTI/WTI with hot oil.
16. Check Working of WTI/RTD repeaters at control room.
17. IR of core to earth.
18. Die electric strength of oil PPM & Chemical analysis, specific gravity test
19. IR tests on windings to earth and between winding
20. Phase sequence test & vector group check
21. Continuity test
22. No load voltage ratio on all tap position
23. Winding resistance in all taps
24. Tap changing at 415v 3 50 Hz supply in all three phases
25. TAN-DELTA test if quality check list calls for.
26. Dew point check for N2 Gas at the time of oil filling

INSULATION RESISTANCE TEST

Sl.No	Descriptio	Date	Time in Hrs	Megger (not IR Value	Temp	Remarks less than 500 V)
1.	Control wiring					
2.	Tap Changer					
	a) Motor					
	b) Control					
3.	Cooling system					
	a) Motor Fan					
	b) Motor pump					
	c) Control Wiring					

4.Main Winding

- a) HV/E+:V Not less
- b) LV/E+HV+LV than 1000 V
- c) HV/IV megger)
- d) IV/LV
- e) HV/L

Note :-

- (1) While checking these values no external, lightning arrestors etc should be in circuit.
- (2) Special care should always be taken while meggering the transformer winding to ensure that there is no leakage in the leads.

Oil Characteristics.

Take necessary precaution (regarding rinsing the bottle, cleaning hand, air bubble etc) while withdrawing the samples, Each sample should be free of air bubbles and should not be tested when it is hot. The sample should satisfy IS:1866.

- 1. Tank Top Sample Bottom Sample
- 2. Cooling system Top Sample Bottom Sample
- 3. OLTC Divertor (each phase)

Tests on CT

- 1.. Ratio
- 2. Polarity
- 3. Magnetising current
- 4. IR Value

Potential Transformer Tests

- 1. IR test of primary winding by HV megger between windings
- 2. IR test of secondary winding by LV megger between winding and winding to earth
- 3. Checking of voltage ratio

4. Verification of terminal markings and polarity
5. Checking of oil level if applicable
6. Checking of continuity and IR values for cables from PT to M
7. Checking tightness of earthing connection.
8. Checking of insulator for cracks
9. Checking output on charging of the system with connected meter

On Load Tap changer

Sl.No	Description	Date	Observation	Remarks
1.	Visual Inspection of equipment.			
2.	Hand operation on II taps.			
3.	Complete wiring of the circuits.			
4.	Limit Switch			
5.	Over running device			
6.	Remote Panel Wiring.			
7.	Overload Device of Driving Motor.			
8.	Local Operation (Electrical)			
9.	Remote Operation (Electrical)			
10.	Tap Position Indicator.			
11.	Step by step contractor			
12.	Out of Step Relay.			

Note

- 1) While operating the mechanism on Electrical Control, check once again limit switches, step by step contractor, over running device etc. for their actual operation and prove that they are functioning properly.
- 2) For More details Please refer Respective Manuals.

7.4.0 GUIDELINES FOR ERECTION OF HT SWITCHGEAR PANELS : (NOT APPLICABLE)

7.4.1 Erection

The base frames will be supplied normally along with the boards. These will have to be aligned, levelled and grouted in position as per approved drawings. Wherever the base channels are not available, the same will have to be fabricated and painted at site. Base frames shall be grouted on the openings which shall be made on the floor during the time of casting. All necessary concrete chipping and finishing works are to be completed.

7.4.2 All the panels/board shall be placed on its foundation or supporting structures and shall be assembled as required. All panels should be installed with parallel, horizontal and vertical alignment by skilled craftsmen.

7.4.3 All the boards will be delivered in sections. Necessary interconnection of busbar, bolting of panels, left out panel/interpanel wiring, etc. will have to be done after assembling the panel.

7.4.4 THE FOLLOWING POINTS SHALL BE CHECKED UP DURING ERECTION

1. Layout of foundation channels.
2. Floor level covered by the panel with respect to main floor level.
3. Location and serial no. of panels.
4. Positioning of panels.
5. Verticality of switchgear panels within the limit specified.
6. Freeness of Breaker Truck and modules in housing and its manual operation.
7. Earthing of panels and breaker truck to station earth.
8. Lugs for termination of HT and LT cables.
9. Mounting and fixing arrangements of Bus bars.
10. Tightening of Busbar jointing bolts as specified.
11. Clearance between :
 - i. Phase to Phase
 - ii. Phase to earth

12. Minimum clearance for :
 - i. Breaker, Truck and moduls withdrawal
 - ii. Distance required for maintenance work
13. Check the operation of :
 - i. Remote control
 - ii. Various required - closing / tripping / alarm / indications / interlocks
14. Installation position of insts and relays
Operation of relays and meters by secondary injection.
15. AC/DC supplies for panel
Final relay settings as per customer requirements.
16. Tightness of terminal connections for HT & LT connections.
17. Opening operation of breaker, manually and electrically.
18. Working of ammeters and voltmeters for their entire range and other panel mounted insts
like recorder, indicator etc.

7.4.5 HT SWITCHGEAR TESTS

1. IR test
2. HV one minute P.F. test checking of oil level
3. Measurement of contact resistance for HT breakers
4. Test to prove inter changeability of similar parts (including breaker module)
5. Testing of relays as per supplier's commissioning manual
6. Testing and calibration of all meters.
7. Operation of all relays by secondary injection method
8. Testing of CT polarities and CT ratio by primary injection test.
9. Measurement of kneepoint voltage and secondary resistance for CTs used for differential protection.'
10. IR and voltage ratio test for PTs

11. Functional test of all circuit components for each panel / feeder.
12. Test to prove closing/tripping operation at minimum and maximum specified voltage in test and service position.
13. Check for drawout test and service position of breakers for all feeders.
14. Check for covering of all openings in the panel - check for continuity and operation of
aux. contacts of breaker.
15. HV test on vacuum interrupters (for VCBs)
16. Check for pressure of SF6 gas and air (for SF6).

7.5.0 LT SWITCHGEAR PANELS

1. Erection

- 1.1 The base frames will be supplied normally along with the boards. These will have to be aligned, levelled and grouted in position as per approved drawings. Wherever the base channels are not available, the same will have to be fabricated and painted at site. Base frames shall be grouted on the openings which shall be made on the floor during the time of casting. All necessary concrete chipping and finishing works are to be completed.
- 1.2 All the panels/board shall be placed on its foundation or supporting structures and shall be assembled as required. All panels should be installed with parallel, horizontal and vertical alignment by skilled craftsmen
- 1.3 All the boards will be delivered in sections. Necessary interconnection of busbar, bolting of panels, left out panel/interpanel wiring, etc. will have to be done after assembling the panel.

2. Checks during erection

12. Layout of foundation channels.
13. Floor level covered by the panel with respect to main floor level.
14. Location and serial no. of panels.
15. Positioning of panels.
16. Verticality of switchgear panels within the limit specified.
17. Freeness of Breaker Truck and modules in housing and its manual operation.
18. Earthing of panels and breaker truck to station earth.
19. Lugs for termination of LT cables.
20. Mounting and fixing arrangements of Bus bars.
21. Tightening of Busbar jointing bolts as specified.

- 22. Clearance between :
 - iii. Phase to Phase
 - iv. Phase to earth
- 12. Minimum clearance for :
 - i. Breaker, Truck and moduls withdrawal
 - ii. Distance required for maintenance work
- 13. Check the operation of :
 - i. Remote control
 - ii. Various required - closing / tripping / alarm / indications / interlocks
- 14. Installation position of insts and relays
Operation of relays and meters by secondary injection.
- 15. AC/DC supplies for panel
Final relay settings as per customer requirements.
- 16. Tightness of terminal connections for HT & LT connections.
- 17. Opening operation of breaker, manually and electrically.
- 18. Working of ammeters and voltmeters for their entire range and other panel mounted insts
like recorder, indicator etc.

3 LT Switchgear tests

- 1. IR test
- 2. Measurement of contact resistance for LT breakers
- 3. Test to prove inter changeability of similar parts (including breaker module
- 4. Testing of relays as per supplier's commissioning manual.
- 5. Testing and calibration of all meters.
- 6. Operation of all relays by secondary injection method.
- 7. Testing of CT polarities and CT ratio by primary injection test.
- 8. Measurement of kneepoint voltage and secondary resistance for CTs used for
differential protection
- 9. IR and voltage ratio test for PTs
- 10. Functional test of all circuit components for each panel / feeder
- 11. Test to prove closing/tripping operation at minimum and maximum specified
voltage in test and service position

12. Check for drawout test and service position of breakers for all feeders
13. Check for covering of all openings in the panel - check for continuity and operation of
aux. contacts of breaker.

7.6.0 BATTERY AND BATTERY CHARGER

1 Battery Checks

1. Checking for completion of civil/ventilation requirement of battery room.
2. Checking of adequacy of charger output/requirement w.r.t. current required battery charging as per the manual
3. Check availability of safety devices, water and first aid
4. Check polarity of connections between battery and charger
5. Visual inspection test for level and leakages
6. Checking of layout as per approved drawing
7. Checking of IR value from positive to earth and negative to earth
8. Checking of voltage per cell and total voltage between positive negative and earth to positive/negative and also tap cell voltage (as applicable)
9. Checking of tightness of connectors on each cell
10. Checking of capacity test and hourly measurement of specific gravity and voltage for each cell

2 Battery Charger

1. IR test.
2. HV test.
3. Checking voltage ratio of boost and float mode transformers.
4. Checking for charging mode of batteries, constant current and constant voltage mode.
5. Load test on chargers by running of DC drives and by liquid resistance system.
6. Checking of tightness of earthing connections.
7. Check for all alarm conditions.
8. Checking and calibration of all indicating meters.

9. Check functional operation of charger, auto/manual change over from float to boost and boost to float etc.
10. Checking and setting of all relays.
11. Check AC ripple in boost and float mode after charging.
12. Check polarity of cables connected to battery.

3. Additional tests

- a. Insulation resistance and earth resistance checks.
- b. Primary and secondary injection test.
- c. Calibration of all instruments
- d. Tests at normal voltage and when required at reduced voltage to prove satisfactory closing and tripping from local and remote points, checking of tripping from relay and protective gear, inter-tripping, interlocks etc. Reduced voltage test at 70% rated voltage to prove tripping of each circuit breaker.
- e. Battery capacity test

7.7.0 GUIDELINES FOR CABLE LAYING

- 1 In the plant building, substations, switchgear rooms, control rooms etc. Power and control cables shall generally be laid on cable trays installed in concrete trenches, tunnels, cable basements, cable vaults, cable shafts or along building and structures as the case may be.
- 2 In case of multicore cables of diameter upto 20 mm where not more than 3 cables are taken in one run, these can be taken directly along structures, walkways, platforms, galleries, walls, ceiling etc. by proper clamping at regular intervals of more than 300 mm.
- 3 Power & control cables installed along buildings and structures, ceilings, walls, etc. which are required to be protected against mechanical damage shall be taken in G.I. conduits.
- 4 GI conduits shall also be used for flameproof installations, wherever required, with sealing at both ends
- 5 In corrosive atmosphere, where 1100 V grade cables are required to be taken in pipes, rigid heavy duty PVC pipes shall be provided.

- 6 Entry of cables through trenches/tunnels into buildings shall be by means of one of the methods indicated in drawing as applicable for different buildings.
- 7 Cables laid exposed in racks/trays and routed through trenches/tunnels/basements etc. to individual drive/control devices etc. shall be taken in embedded surface exposed rigid GI conduits and or flexible conduits unless directly terminated to the equipment in the panels located, above trenches, tunnels or basement.
- 8 All cables routed along walls or in equipment rooms shall be protected by means of laying them through GI pipes or by providing sheet metal covers upto a height of 2000 mm from the working floor levels and platforms, for protection against mechanical damage. All vertical risers shall be of enclosed type.
- 9 Tray covers shall not be provided for the cable trays within trenches, tunnels and basements. Non-perforated type sheet steel covers shall be provided for the trays in the areas susceptible to accumulation of coal dust/atmospheric abuses etc.
- 10 Cable trays shall be supported on ISA 50x50x6mm MS/GI brackets. Brackets shall be welded to steel plate inserts in the trenches/tunnels or supporting channel angle/inserts in other areas.
- 11 Wherever direct heat radiation exists, heat isolating barriers (subject to customers approval), for cabling system shall be adopted.
- 12 For 415V power wiring in ancillary buildings, offices and laboratories, cables shall be taken through embedded/exposed GI conduits or rigid PVC pipes as applicable.
- 13 If required, a few number of cables in exceptional areas may be directly buried into the earth.
- 14 Wherever cables are to be laid below roads and railway tracks, the same shall be taken through ducts buried at a suitable depth as decided by Engineers.
- 15 At certain places where hazardous fumes/gases may cause fire to the cables, cable trenches after installation of cables may be sand-filled.
- 16 In corrosive atmosphere, PVC conduits shall be used for cables.
- 17 Single core cables, when pulled individually shall be taken through PVC pipes only.
- 18 Laying and installation of power, control and special cables shall generally conform to IS : 1255
- 19 The cables shall be laid-out in proper direction from the cable drums (opposite to the normal direction of rotation for transportation).

- 20 In case of higher size cables, the laid out cables shall run over rollers placed at close intervals and finally transferred carefully on the racks/trays. Care shall be taken so that kinks and twists or any mechanical damage does not occur to cables. Only approved cable pulling grips or other devices shall be used. Under no circumstances cables shall be dragged on ground or along structure while paying out from cable drums, carrying to site and straightening for laying purpose.
- 21 Suitable extra length of cables shall be provided for all feeders for any future contingency, in consultation with Engineer.
- 22 Cable runs shall be uniformly spaced, properly supported and protected in an approved manner. All bends in runs shall be well defined and made with due consideration to avoid sharp bending and kinking of cable. The bending radius of various types of cables shall not be less than those specified by cable manufacturers and that specified in IS 1255.
- 23 All cables shall be provided with identification tags indicating the cable numbers in accordance with the cable circuit schedule. Tags shall be fixed at both ends of cables (both inside & outside of panel) both sides of floor/wall crossings, every 25m spacing for straight runs or as specified by Engineer for easy identification of cable.
- 24 When a cable passes through a wall, cable number tags shall be fixed on both sides of the wall.
- 25 Single core cables for AC Circuits shall form a complete circuit in trefoil formation supported by means of trefoil clamps of non-magnetic material.
- 26 Multi-core cables above 1100 V grade shall be generally laid in ladder type trays in one layer with spacing not less than one cable diameter of bigger diameter cable.
- 27 All 1100 V grade multicore power cables and single core DC cables shall be placed in single layer, touching each other and clamped by means of single or multiple galvanised MS saddles/aluminium strips/nylon cable ties. Cables above 35mm diameter shall be clamped individually.
- 28 Control cables shall be laid touching each other and wherever required may be taken in two layers. All control cables shall be clamped with a common clamp/tie.
- 29 Segregation of the cables on the basis of their types and their functions shall be as under for horizontal formation:
- 30 HT cables shall be laid in the top tier(s)
- 31 LT power cables to be laid in the tray(s) below the HT cable trays.
- 32 LT control cables to be laid in the Tray(s) next below to the LT power cable (trays)
- 33 Special control cables including screened control cables to be laid in the bottom most tray(s).

- 34 For vertical formations, the trays closest to the wall shall be considered as bottom most tray and the order indicated in clause just above shall be followed. However, where there is no clear distinction of bottom/top trays, the order convenient for linking the horizontal and vertical formations shall be followed.
- 35 When it may not be possible to accommodate the cables as per the criteria indicated in the two clauses indicated above, the following rules shall override the criteria. However, prior approval of the Engineer will be required. In hierarchical order:
 - 36 Control cables are mixed up with the special control cables with clear minimum gap of 100 mm between them.
 - 37 LT power cables are mixed up with control cable with clear minimum gap of 150 mm between them.
 - 38 LT power cables are mixed up with HT power cables with clear minimum gap of 200 mm between them.
 - 39 LT power cables are mixed up with special control cables with clear minimum gap of 200 mm between them.
- 40 In case of duplicate feeders to essential loads, the respective cables shall be laid through separate raceways. Alternatively, such cables shall be laid on the opposite sides of a trench/tunnel/basement.
- 41 For laying cables along building steel structures and technological structures, the cables shall be taken by clamping with MS saddles screwed to the MS flats welded to the structure. MS saddles and flats shall be galvanised.
- 42 For laying cables along concrete walls, ceilings etc. The cables shall be taken by clamping with MS saddles screwed to the MS flats welded on the inserts. Where inserts are not available the saddles shall be directly fixed to the walls using raw plus and MS flat spacers of minimum 6 mm thickness.
- 43 To facilitate pulling of cables in GI conduits, powdered soft stone, plastic scoop or other dry inert lubricant may be used but grease or other material harmful to the cable sheaths shall not be used.
- 44 No single core cable shall pass through a GI conduit or duct except DC single core cables. AC single core cables shall pass through GI conduits/pipes in trefoil formation only.
- 45 In case of a 3 phase, 4 wire system, more than one single phase circuit, unless originating from the same phase shall not be taken in the same GI conduit.

46 Entry of cables from underground trenches to the buildings or tunnels shall be by some approved method. Necessary precautions shall be taken to make the entry point fully water tight by properly sealing the pipe sleeves wherever they enter directly into the building at trench level. The sealing shall be by cold setting compound. Any alternative sealing arrangement may be suggested with the offer for consideration by BHEL.

47 Wherever specific cable routes are not shown in cable schedules cables shall be laid as directed by Engineer.

48 SUPPORT SPACINGS & CLAMPINGS

Support spacing and clamping suitably provided and as required

49 LAYING OF CABLES DIRECTLY BURIED IN GROUND

Laying and installation of directly buried cables in ground shall conform to the requirements of IS 1255.

50 SUPPORT SPACINGS & CLAMPINGS

Trefoil Clamps:

- | | |
|--|---|
| i. Horizontal run spacing | 1000 mm (max) |
| : | : 1000 mm (max) |
| ii. Vertical run spacing | Double the diameter of larger cable or 150 mm |
| iii. Axial spacing between adjacent trefoils | Whichever is less |

Other Clamps

A. Power Cables:

- | | |
|----------------------|--|
| Above 35mm OD | Individually clamped at 3000 mm Interval |
| i) Horizontal runs : | (max) |
| ii) Vertical runs : | Individually clamped 3000mm intervals |
| Upto 35mm OD | (max). |
| i) Horizontal runs | : Collectively clamped at 3000 mm intervals |
| (max) | |
| ii) Vertical runs : | Collectively clamped at 2000 mm interval (max) |

B. Control Cables:

- | | | |
|----------------------|--|-------|
| i) Horizontal runs : | Collectively clamped at 3000 mm interval | (max) |
| ii) Vertical runs : | Collectively clamped at 3000 mm interval | (max) |

C. Spacing for cables supported along structure/ceiling

Clamping Spacing:

- i) In horizontal runs : 750mm (max)
 - ii) In vertical runs : 750mm (max)
- Spacing between cables : 30 mm (min)

Note:

- a. Supports shall also be provided at each bend.
- b. For any change in above spacing, prior approval of Engineer will be taken

51 CABLE TERMINATION AND JOINTING

1. When the equipment are provided with undrilled gland plates for cable/conduit entry into the equipment, drilling and cutting on the gland plate and any minor modification work required to complete the job shall be carried out at site and drawings shall be prepared and take engineer's approval before drilling holes. Cutting shall not be allowed.
2. Termination of cables shall be done as per termination drawings & interconnection diagrams furnished to the contractor. Looping of cores/wires at terminals as shown in interconnection diagrams is to be done.
3. All cable entries in the equipment shall be sealed after glanding the cables..
4. Adequate length of cables shall be pulled inside the switch boards, control panels, terminal boxes etc. as per near termination of each core/conductor.
5. Power cable terminations shall be carried out in such a manner as to avoid strain on the terminals by providing suitable clamps near the terminals.
6. End sealing/termination of cables shall be done by means specified on the specification for terminations. The system shall be suitable for types of cable specified and complete with stress relief system.
7. Termination and jointing of aluminium/copper conductor power cables shall be done by means of compression method using compression type aluminium/tinned copper lugs.
8. Copper conductor control cables shall be terminated directly into screwed type terminals provided in the equipment. Wherever control cables are to be terminated by means of terminal lugs, the same shall be of tinned copper compression type.
9. Cable joints shall normally be made at an intermediate point in the straight run of the cable only when the length of the run is more than the standard drum length supplied by the cable manufacturer. In such cases, when jointing is unavoidable, the same shall be made by means of specified cable-jointing kit, subject to BHEL's approval of Engineer shall be taken for deciding location of joint.
10. Termination and jointing shall generally conform to the requirements of IS : 1255 and shall strictly conform to the recommendations of termination and jointing kit supplier.

52 TESTING OF CABLES:

- 1 The contractor shall submit to the Engineer a checklist for testing and commissioning and the activities shall be carried out in accordance with the checklist.
- 2 Testing and electrical measurement of cable installations shall conform to IS : 1255
- 3 Prior to installation, cables shall be tested for :
 - a) Continuity of conductors
 - b) Insulation resistance between conductors & earth
 - c) Insulation resistance between conductors.

- 4 After installation cables shall be tested for :
 - a) Insulation resistance between conductors & iron
 - b) Insulation resistance between conductors & earth
 - c) Conductor resistance
 - e) Capacitance between conductors & earth (for cables above 7C.1.3KV grade)
 - f) DC high voltage test (for LT power cables of higher sizes interconnecting PCCs & MCC)
 - g) Absence of cross phasing
 - h) Firmness of terminations.

7.8.0 TESTS FOR THE EQUIPMENT ERECTED BY MECHANICAL CONTRACTOR

The tests to be carried out on the equipment at which are normally being erected by Mechanical contractor.

a) **Generator :**

Generator set with all auxiliaries and controls shall be assembled and tested to verify compliance with the guaranteed technical particulars and for satisfactory performance. Relevant standards shall be followed as guideline for testing. All the tests shall be witnessed by customer or its representative. The commissioning tests shall be carried out at site under normal service conditions.

Following tests shall be carried out on the generators :

1. Insulation resistance test and determination of polarization index value of:

- Generator

- Exciter

- Resistance temperature detectors

2. Dielectric test

3. No load characteristics

4. Short circuit characteristics

5. Temperature rise at rated voltage, current, power factor and frequency.

6. Over-speed test

7. Calculation of efficiency

8. Phase sequence/voltage balance/current balance checks.

Note :

1. Vibration tests in the factory to be taken at 100% of synchronous speed and at 120% during overspeed test.

2. Vibration test at site to be taken at 100% of synchronous speed of the complete generator with its driver.

9. Instantaneous short circuit test (Optional).

10. Noise measurement test.

11. Response of voltage and frequency with sudden shedding of 25%, 50%, 75% and 100% of rated load respectively.

12. Temperature detector test

13. Measurement of DC resistance of winding

14. Inter turn insulation test of stator winding with induced voltage 130% of rated value for 5 minutes (if applicable).

15. Measurement of shaft voltage.

16. Tan Delta test for generator bushing. (if required).

b) AC Motors

1. IR test of stator and rotor windings.
2. Heating of both windings upto the permissible temp.
3. Checking/testing of associated switchboard, cables, relays/meter interlockings as mentioned in relevant chapters are completed.
4. Tightness of cable connection.
5. Winding resistance measurement of stator and rotor.
6. Checking continuity of winding.
7. Checking tightness of earth connections.
8. Checking space heaters and carryout heating of winding (if required)
9. Checking direction of rotation in decoupled condition during kick start
10. Measurement of no load current for all phases
11. Measurement of temperature of body during no load and load conditions.
12. Check for tripping of motor from local/remote switches and from.
13. Checking of vibration (if required).
14. Checking of noise level (if required)
15. Measurement of stator and bearing temperatures during load running (if applicable) for every half an hour interval till saturation comes.
16. Checking operation of speed switch (if there)
17. Checking of polarisation index of stator winding, R10/R1 by motorised megger (The value should not be less than 2.0) R60/10 absorption coefficient shall not be less than 1.5.
18. Dielectric test.

B) DC Motors

1. IR measurement and heating the winding as per heating curve.
2. Check for earth connection
3. Winding resistance for field and armature.
4. Check running of drive at minimum and maximum specified.

5. Check auto start of drive on failure of AC supply (if applicable)
6. Check operation of overload relay.
7. Measure vibration.
8. Check temperature rise on body of drive after required period of continuous running.
9. Measure load currents and no load currents (if possible)
10. Check direction of rotation.
11. Check continuity of winding.
12. Measurement of RPM.

7.9.0 PAINTING

The surface shall be free from rust, foreign adhering matters, grease etc. Two coats of rust preventing red-oxide primer and final painting of two coats as per the colour decided by the site engineer. (More details please refer Section VI scope of works). After cleaning the surface is painted with one coat of Red oxide zinc chromate primer conforming to IS 2074 and allowed to dry completely. The primer coated surface is painted with two coat of final painting of desired colour which shall be selected from IS-5.

The contractor shall paint steel fabrications at site with two (2) coats of primer followed by two (2) final coats of epoxy paint of shade 631 of IS:5 as detailed in section VI.

7.10.0 CODES AD STANDARDS

- 7.10.1 All equipment and materials shall be designed, manufactured and tested in accordance with the latest applicable Indian Standards (IS) except where modified and/or supplemented by this specification.
- 7.10.2 Equipment and materials conforming to any other standard which ensures equal or better quality may be accepted. In such case, copies of the English version of the standard adopted shall be submitted along with the bid.

IS The electrical installation shall meet the requirement of Indian Electricity Rules as amended upto dates, relevant IS codes of Practice and Indian Electricity Act. In addition, other rules or regulations applicable to the work shall be followed. In case of any discrepancy, the more restrictive rule shall be binding. A list of applicable standards is given below for reference.

IS 3043	Code of practice for earthing
IS 3072	Installation and maintenance of switchgear
IS 5133	Box for enclosure of electrical equipment
IS 5216	Guide for safety procedure and practice in electrical work
IS 13947	Degree of protection provided by enclosures for low voltage switchgear and control gear.
IS 5216	Guide for safety procedures and practices in electrical works.
IS 800	Code of practice for use of structural steel

In addition to the standards mentioned above, all works shall conform to the requirements of the following rules and regulations.

- a) Indian Electricity Act and Rules framed thereunder
- b) Fire insurance regulations
- c) Regulations laid down by the Chief Electrical Inspector of State and CEA
- d) Regulations laid down by the Factory Inspector of State
- e) Any other regulations laid down by the authorities.

In case any clause of contradictory nature arises between standards and this specification, the latter shall prevail.

7.11.0 TECHNICAL REQUIREMENT FOR ITEMS SUPPLIED BY THE CONTRACTOR.

1. GENERAL

Equipment and material supplied shall comply with description, rating, type and size as detailed in this specification, drawings and annexures.

Equipment and materials furnished shall be complete and operative in add details.

All the accessories, fittings, supports, anchor bolts etc., which form part of the equipment or which are necessary for safe and satisfactory installation and operation of the equipment shall be furnished.

All parts shall be made accurately to standard gauges so as to facilitate replacement and repair. All corresponding parts of similar equipment shall be interchangeable.

Samples of all items shall be made available for purchaser's approval prior to supply of item to site.

2 FERRULES

- a) Ferrules shall be required for individual core of cable hence they shall be suitable for the insulated conductor diameter.
- b) Ferrules shall be of plastic material.
- c) Numbering on the ferrules shall be engraved type with contrast colour to the base. Engrave colouring shall be of durable quality to match the entire life of the plant. Engraving shall be legible from a distance of 600 mm.
- d) Ferrules shall be interlocking type in such a way that the interlocked ferrules take the shape of tube with complete ferrule number appearing in a straight line.

3 TAGS

- a) Cables shall be provided with cable number tags for identification.
- b) Cable tags shall be of durable fibre, aluminium or stainless steel sheets.
- c) Cable number shall be engraved type in case of aluminium or stainless steel tags, and printed type in case of fibre sheet.
- d) Tags shall be durable quality of size 60mm x 12mm with holes at both ends.
- e) Samples of tags shall be approved by BHEL Engineer before delivery.
- f) Tags shall be provided with non-corrosive wire of sufficient strength for taggings.

4 FIRE STOP CABLE SEALING SYSTEM (AS APPLICABLE)

Fire stop cable sealing system shall have two (2) hours fire protection rating suitable for sealing both vertical & horizontal cable penetrations. The sealing compound in conjunction with mineral wool shall form effective fire seals. The sealing compound shall have special property to allow for short circuit conditions. **GPG fire stop sealing compo** or equivalent sealing compound shall be used.

7.12.0 GUIDELINES FOR ERECTION OF GI PIPES , SUPPORTS AND ACCESSORIES

- 7.12.1 For installation of cables in GI conduits the conduits shall be installed first without cables but having suitable pull wires laid in conduits.
- 7.12.2 For equipment and devices having GI conduit entry arrangement other than standard GI conduit adopter, adopters shall be provided as required to enable the GI conduit to be properly terminated, between conduit end and motor T.B.
- 7.12.3 GI conduits shall run without moisture or water traps and shall be made drawing arrangement towards the end.
- 7.12.4 The entire GI conduit system shall be firmly fastened in position. All boxes and fittings shall generally be secured independently from the GI pipes entering them.

- 7.12.5 Bends of GI pipes/conduits shall be made without causing damage to the pipes/conduits.
- 7.12.6 Occupancy of conduits shall not be greater than 40%.
- 7.12.7 The adopter for coupling rigid GI pipe/conduits and flexible conduit shall be of aluminium or galvanised steel.
- 7.12.8 Transportation and storage of cable drums
- Transportation and storage of cable drums shall generally conform to the requirements of IS : 1255
- 7.12.9 All the cables shall be supplied to the contractor free of cost from BHEL/Customer's store/storage area. Transportation of cables from storage area to the work site shall be the responsibility of the contractor.
- 7.12.10 The cable drums shall be transported on wheels to the place of work.

Note : The test specified above for all the electrical equipment are not exhaustive. Any other pre-commissioning and field tests not included in the above list but necessary as per relevant standards, Electricity rules, code of practice and instructed by the manufacturer of the equipment shall also have to be carried if deemed necessary shall be carried out as per requirement either at free of cost or at additional cost. Decision of Engineer in charge will be the final regarding additional cost for testing. The contractor shall take the full responsibility of testing, commissioning, trial run and successful operation of the equipment under overall guidance of BHEL engineer

SECTION VIII
APPENDIX - I DATA SHEET

SPECIFIC TECHNICAL REQUIREMENTS

SUPPLY ITEMS

1. Clamps
 - a. Material & Type : Nylon self locking ties aluminium strips clamps as per Section VI
 - b. Sizes : To meet the requirements of :
2. Ferrules : Section VI : As per Section VI
3. Tag
 - a. Material : Aluminum/Fibre/Stainless Steel
 - b. Markings : Engraving/Embossing/Printing
 - c. Size : As required.
4. Cable lugs : Copper/Aluminium (crimping type)
5. Clamp Spacing:
 - a. Trefoil Clamps:
 - i. Horizontal run spacing : 1000 mm (max)
: 1000 mm (max)
 - ii. Vertical run spacing : Double the diameter of larger cable or : :
 - iii. Axial spacing between adjacent trefoils : 150mm
Whichever is less

Other Clamps

A. Power Cables:

Above 35mm OD

 - i) Horizontal runs : Individually clamped at 3000 mm Interval (max)
 - ii) Vertical runs : Individually clamped 3000mm intervals (max).

Upto 35 mm OD

- i) Horizontal runs : Collectively clamped at 3000 mm intervals (max)
- ii) Vertical runs : Collectively clamped at 2000 mm interval (max)

B. Control

Cables: : Collectively clamped at 3000 mm interval

- i) Horizontal (max)

runs : Collectively clamped at 3000 mm interval

- ii) Vertical runs (max)

C. Spacing for cables supported along structure/ceiling

Clamping Spacing:

- i) In horizontal runs : 750mm (max)
- ii) In vertical runs : 750mm (max)

Spacing between cables : 30 mm (min)

Note:

- a. Supports shall also be provided at each bend.
- b. For any change in above spacing, prior approval of Engineer will be taken

6. **Cable termination:**

Type of Lugs:

- a. Power Cables : Copper/Aluminium/Both crimping type
- b. Control Cables : Copper pin type, copper screw type,
Direct termination
- c. Special Cables : Pin type, maxi-termi type.

7. **Wastage Allowance:**

- a. HT cables : 1%
- b. LT cables above 70mm : 1%
- c. LT cables upto 70mm : 1%
- d. Control & Special cables : 1%
- e. Fire Survival cables : 1%
- f. Steel materials (for cable trays/tray support installation) : 1% by weight

SECTION VIII

APPENDIX - II

DECLARATION SHEET

I, _____ hereby certify that, all the information and data furnished by me with regard to this Tender Specification No.BHEL:PSSR:SCT:1308 are true and complete to the best of my knowledge. I have gone through the specifications, conditions, stipulations in detail and agree to comply with the requirements and intent specifications.

I further certify that I am duly authorized representative of the under mentioned tenderer and a valid power of Attorney to this effect is also enclosed.

TENDERER'S NAME & ADDRESS

**AUTHORISED REPRESENTATIVE'S
SIGNATURE WITH NAME & ADDRESS**

SECTION VIII

APPENDIX - III

TENDER SPECIFICATION NO BHEL:PSSR:SCT:1308

**CERTIFICATE OF DECLARATION FOR CONFIRMING
KNOWLEDGE ON SITE CONDITIONS**

We,

hereby declare and confirm that we have visited the project site under subject, namely and acquired full knowledge and information about the site conditions. We further confirm that the above information is true and correct and we will not raise any claim of any nature due to lack of knowledge of site conditions.

TENDERER'S NAME AND ADDRESS

Place:

Date :

**SIGNATURE OF AUTHORISED
REPRESENTATIVE WITH NAME & ADDRESS:**

OFFICE SEAL

BHARAT HEAVY ELECTRICALS LIMITED
(A Government of India Undertaking)
Power Sector: Southern Region
474, Anna Salai, Nandanam, Chennai - 600 035.

SECTION VIII

APPENDIX - IV

CHECK LIST

TENDER SPECIFICATION NO, BHEL: PSSR : SCT : 1308

Tenderers are required to fill in the following details:

- | | | | |
|----|--|---|--------|
| 1. | a) Name of the Tenderer with address | : | YES/NO |
| | b) Telegraphic/Telex address | : | YES/NO |
| | c) Phone (Office/Residence) | : | YES/NO |
| | d) Management Structure of firm (Pvt. Ltd./Public Ltd./Partnership/Sole Proprietorship) Documentary proof For the same enclosed) | : | YES/NO |
| 2. | Whether EMD submitted as per Tender specifications terms and Conditions | : | YES/NO |
| 3. | Validity of offer (offer shall be kept open for acceptance for minimum six months) | : | YES/NO |
| 4. | Whether tenderer visited the erection site and acquainted with the site conditions before quoting | : | YES/NO |

SIGNATURE OF THE TENDERER

5. Whether the following details are furnished : YES/NO
- a) Previous Experience : YES/NO
- b) Present assignments : YES/NO
- c) organization chart of the company : YES/NO
- d) Company financial status : YES/NO
- e) Incase of company, proof of Registration of the company : YES/NO
- f) Memorandum & Articles of Association of company/copy of Partnership deed : YES/NO
- g) Profit & Loss account for the Last 3 years : YES/NO
- h) Audited Balance sheet for the Last 3 years : YES/NO
- i) Income Tax clearance certificate (latest) : YES/NO
- j) Solvency Certificate from a Nationalised Bank : YES/NO
- k) Power of Attorney of the person Signing the tender duly attested By a Notary Public : YES/NO
- l) Manpower organization chart With deployment plan at site For posting of Engineers/super Visitors and workers/labourers For satisfactory completion of Work under this specification : YES/NO

SIGNATURE OF THE TENDERER

6. Whether the Tenderer is conversant with local labour laws & conditions : YES/NO
7. Whether the tenderer is aware of all safety rules and codes : YES/NO
8. Whether the Declaration sheet (as per appendix enclosed) : YES/NO
9. Time required for mobilization of site organization and start of work : YES/NO
10. Whether list of tools and Plants available with the contractor and proposed to be deployed for this work enclosed : YES/NO
11. Whether all the Pages are read understood and signed. : YES/NO
12. Deviations, if any Pointed out :
13. Whether PF exemption No. is allotted by RPFC of your area if so, indicate number : YES/NO

SIGNATURE OF THE TENDERER

NALCO ANGUL CPP EXPANSION -UNIT 10 (1 x 120 MW)

ELECTRICAL (HT & LT) PACKAGE

BILL OF MATERIALS WITH RELEVANT CLAUSE REFERENCE

Bill of Materials (BOM) contains detailed specification of various Equipments and items supplied by various BHEL Unit-wise. Scope of work specific for each item is indicated in the last column of BOM. In addition to these clauses, other common clauses like painting, calibration, Civil Work etc. (under 6.3.0) related to the work also to be referred.

SL. NO.	DESCRIPTION	Qty Unit 10	Clause Ref No:
A.1	BHEL-JHANSI SCOPE		
A.1.0	GENERATOR TRANSFORMER		
A.1.1	150 MVA GENERATOR TRANSFORMER Description 150 MVA, 10.5kV/235 kV, Three phase, OFAF cooled, YNd1, Generator Transformer complete loose accessories like 2 Nos. of Radiator banks, on load tap changers, HV/LV/HVN bushings, bushing CTs, Turrets, conservators, cooler control cabinet, marshalling box, pipings, common KIOSK etc. Loose items like raise/lower P.Bs, tap changer indicators, facia windows, W.T.I. repeaters, buzzers, signal lamps, etc.shall be mounted and wired in control panel.	1 set*	6.3.1

SL. NO.	DESCRIPTION	Qty Unit 10	Clause Ref No:												
A.1	BHEL-JHANSI SCOPE														
	<p>Complete erection and integration of all accessories and components, grounding, brazing of joints, painting of supports, , connection to earth grid etc., shall also be part of transformer erection.</p> <p>Approximate Dimensions and weight of transformer</p> <p>Max. dimension 15,000 x 10,500 x 7000 mm Shipping. dimension 7170 x 3450 x 3450 mm</p> <table data-bbox="331 797 840 1089"> <thead> <tr> <th>Approximate weights</th> <th>in kg</th> </tr> </thead> <tbody> <tr> <td>Tank & fittings</td> <td>43,000</td> </tr> <tr> <td>Total wt of transformer</td> <td>1,83,000</td> </tr> <tr> <td>Untanking Weight</td> <td>10,000</td> </tr> <tr> <td>Shipping weight (gas filled)</td> <td>1,20,000</td> </tr> <tr> <td>Total oil (49,440 lts)</td> <td>44,000</td> </tr> </tbody> </table> <p>Ref: OGA of Trf drg. 04590050036; Rev:00.</p> <p>* Lump sum rate shall be quoted including final painting</p>	Approximate weights	in kg	Tank & fittings	43,000	Total wt of transformer	1,83,000	Untanking Weight	10,000	Shipping weight (gas filled)	1,20,000	Total oil (49,440 lts)	44,000		
Approximate weights	in kg														
Tank & fittings	43,000														
Total wt of transformer	1,83,000														
Untanking Weight	10,000														
Shipping weight (gas filled)	1,20,000														
Total oil (49,440 lts)	44,000														

SL. NO.	DESCRIPTION	Qty Unit 10	Clause Ref No:												
A.1	BHEL-JHANSI SCOPE														
A.1.2	<p>UNIT AUXILIARY TRANSFORMER</p> <p>16 MVA, 10.5/6.9 kV, ONAN Unit Auxiliary Transformer complete with radiators, conservators, control panels, marshalling box etc.including NGR.</p> <p>Loose items like raise/lower P.Bs, tap changer indicators, facia windows, W.T.I. repeaters, buzzers, signal lamps, etc.shall be mounted and wired in control panel</p> <p>Approximate Dimensions and weight of transformer</p> <p>Overall dimension: 7700 x 6800 x 5000 mm Shipping. dimension 4400 x 2900 x 3250 mm</p> <table border="0"> <tr> <td><i>Approximate weights</i></td> <td><i>in kg</i></td> </tr> <tr> <td>Tank & fittings</td> <td>14800</td> </tr> <tr> <td>Total wt of transformer</td> <td>46,600</td> </tr> <tr> <td>Untanking Weight</td> <td>17800</td> </tr> <tr> <td>Shipping weight (gas filled)</td> <td>25,000</td> </tr> <tr> <td>Total oil (15700 lts)</td> <td>14,000</td> </tr> </table> <p>Ref: OGA of Trf drg. 04590050036; Rev:00.</p>	<i>Approximate weights</i>	<i>in kg</i>	Tank & fittings	14800	Total wt of transformer	46,600	Untanking Weight	17800	Shipping weight (gas filled)	25,000	Total oil (15700 lts)	14,000	1 set*	6.3.1
<i>Approximate weights</i>	<i>in kg</i>														
Tank & fittings	14800														
Total wt of transformer	46,600														
Untanking Weight	17800														
Shipping weight (gas filled)	25,000														
Total oil (15700 lts)	14,000														

SL. NO.	DESCRIPTION	Qty Unit 10	Clause Ref No:
A.1	BHEL-JHANSI SCOPE		
	<p>NGR for UAT</p> <p>6.9 kV, 9.95 ohm, 400 A for 30 sec Neutral Grounding Resistor with connected accessories</p> <p>Approximate dimension: 1200 x 1200</p> <p>Approximate weight: 600 kg</p>		
A.2.0	HT BUSDUCT		
A.2.1	<p>10.5 KV IP Busduct along with support structures, LAVT Cubicle, NG Cubicle and other loose supplied items such as Seal off Bushings, CTs, Hot air blowing equipment, flexible hoses from HAB System unit to Bus Duct, Control cabinet for HAB, Conduiting and wiring for space heaters, illumination, etc. CT/PT wiring & conduiting ,erection works includes making welded joints and flexible joint connection and fixing of rubber bellows & shunts etc comprising of the following</p> <p>a) Main Busduct: 10000 A IP Bus Duct from 120 MW Generator to 150 MVA Three phase generator transformers, with 10000 A main run bus duct</p> <p>Size: 6.35 TK x 1000 O/D Aluminium Alloy enclosure and 450 O/D x 15 TK. Round Aluminium Alloy conductor.</p> <p>Approximate length of all phases: 110 Meters per set</p>	1 set*	6.3.2

SL. NO.	DESCRIPTION	Qty Unit 10	Clause Ref No:
A.1	BHEL-JHANSI SCOPE		
	<p>b) Tap off Busduct: 1000A- to 1 x 16 MVA Unit Auxiliary transformers, LAVT Cubicle, NG Cubicle etc.</p> <p>Size: 4.78 TK.x 780 O/D Aluminium Alloy enclosure and 152.4 Box conductor 8.1 TK</p> <p>Approximate length of all phases: 16 Meters per set</p> <p>Other Details of Busduct:</p> <p>a) App Weight of Bus duct- : 200kg/ Mtr (approx.)</p> <p>b) Hot Air Blower : Size 1500 x 1200 x 1500 mm. Capacity: 6000 cubicmeter / hour ,</p> <p>c) 1 No: NG Cubicle: Size 2000 x 1250 x 1690 mm; Weight: 1400 kg approx.</p> <p>d) 3 Nos: LAVT Cubicle: size 900 x 2250 x 2400 mm Weight : 1000 kg per cubicle.</p> <p>e) Weight of Support Structure: 3.5 MT (approx.)</p> <p>Reference:</p> <p>a) Layout of IPB Drg No. 0 541 00 51 434, rev 01</p> <p>b) Hot Air Blower Ref Drg 35410051380, rev 00.</p> <p>c) NG Cubicle Ref Drg 3 542 10 51 198, rev 00</p> <p>d) LAVT Cubicle Ref Drg :2 542 20 51 129, rev 00</p> <p><i>* Lump sum rate shall be quoted including final painting.</i></p>		

SL NO.	DESCRIPTION	Qty Unit 10	Clause Ref No:
B.1	BHEL-PEM SCOPE		
B.1.0	LT MCC's		
B.1.1	415 V TURBINE MCC [10KA] 13 panels of total dimension 10460 x 900/600 x 2,430 mm in suitable shipping sections. Total Weight: 5400 kg (Approximate)	1 No	6.3.3
B.1.2	415 V TURBINE VALVE MCC [10KB] 18 panels of total dimension 14460 x 600 x 2,430 mm in suitable shipping sections. Total Weight: 6300 kg(Approximate)	1 No	6.3.3
B.1.3	415 V MISCELLANEOUS MCC [9SB] 13 panels of total dimension 10460 x 900/600 x 2,430 mm in suitable shipping sections. Total Weight: 6500 kg(Approximate)	1 No	6.3.3

SL. NO.	DESCRIPTION	Qty Unit 10	Clause Ref No:
B.1	BHEL-PEM SCOPE		
B.1.4	415 V WELDING PDB [PDB-10] 6 panels of total dimension: 4860 x 600 x 2430 mm; Weight : 2100 kg.	1 No	6.3.3
B.1.5	VENTILATION MCC [10TA] 15 panels of total dimension 12060 x 900/600 x 2430 mm in suitable shipping sections. Total Weight: 5700 kg(Approximate)	1 No	6.3.3
B.1.6	AC MCC [10TB] 10 panels of total dimension 8060 x 600 x 2430 mm in suitable shipping sections. Total Weight: 3900 kg(Approximate)	1 No	6.3.3
B.1.7	ESP, AC & VENTILATION MCC [10TC] 12 panels of total dimension 9660 x 600 x 2430 mm in suitable shipping sections. Total Weight: 3900 kg(Approximate)	1 No	6.3.3

SL. NO.	DESCRIPTION	Qty Unit 10	Clause Ref No:
B.1	BHEL-PEM SCOPE		
B.2.0	BATTERY & BATTERY CHARGERS:		
B.2.1	<p>220 V DC Battery & Battery Charger consisting of the following:</p> <p>a) Battery banks:</p> <p>1500 AH, 220V, VRLA Type, 108 Cells housed in single row single tier racks, along with inter cell connectors, inter row connector, inter bank connectors, rack insulators etc.</p> <p>Size of each battery bank: 9776 x 2836 x 935 mm</p> <p>b) Battery Charger:</p> <p>Each charger of Rating- 300A, consists float & boost charger panels, dispatched in suitable shipping sections.</p> <p>Size of Float Charger (FC) : 2200 x 1675 x 1100 mm</p> <p>Size of Float cum Boost Charger (FCB) : 2200 x 1675 x 1100 mm</p> <p>Approximate Weight of charger: 2000 kg / Charger</p> <p>* Lump sum rate shall be quoted</p>	2 Sets*	6.3.5

SL. NO.	DESCRIPTION	Qty Unit 10	Clause Ref No:
B.1	BHEL-PEM SCOPE		
B.3.0	LOCAL PUSH BUTTON STATIONS		
B.3.1	Type – A - For Unidirectional drives	62 Nos.	6.3.12
B.3.2	Type – B - For Bi directional drives	75 Nos.	6.3.12
B.3.3	Type – C - With Ammeters	9 Nos.	6.3.12
B.4.0	6.6 KV UNEARTHED XLPE CABLE TERMINATIONS KITS		
B.4.1	1 C x 500 sq. mm	38 Nos.	6.3.10
B.4.2	3 C x 185 sq. mm	26 Nos.	6.3.10

SL. NO.	DESCRIPTION	Qty Unit 10	Clause Ref No:
B.1	BHEL-PEM SCOPE		
B.5.0	CABLE TRAYS AND ACCESSORIES along with bends, reducers, tees, cross etc.		
B.5.1	600 mm wide, Ladder Type Tray	10800 Mtrs	6.3.11
B.5.2	450 mm wide, Ladder Type Tray	2200 Mtrs	6.3.11
B.5.3	300 mm wide, Ladder Type Tray	2450 Mtrs	6.3.11
B.5.4	150 mm wide, Ladder Type Tray	1200 Mtrs	6.3.11
B.5.5	600 mm wide, Perforated Type Tray	2200 Mtrs	6.3.11
B.5.6	450 mm wide, Perforated Type Tray	800 Mtrs	6.3.11
B.5.7	300 mm wide, Perforated Type Tray	800 Mtrs	6.3.11
B.5.8	150 mm wide, Perforated Type Tray	8500 Mtrs	6.3.11

SL. NO.	DESCRIPTION	Qty Unit 10	Clause Ref No:
B.1	BHEL-PEM SCOPE		
B.6.0	STRUCTURAL STEEL FOR SUPPORT		
B.6.1	Structural Steel for fabrication of supports (ISA - 60X60X6, ISMC – 100, ISMC - 160 etc.)	112 MT	6.3.13
B.7.0	ABOVE GROUND EARTHING		
B.7.1	65 x 8 mm GS Flat	60 Mtrs	6.3.14
B.7.2	50 x 6 mm GS Flat	3400 Mtrs	6.3.14
B.7.3	25 x 6 mm GS Flat	3000 Mtrs	6.3.14
B.7.4	25 x 3 mm GS Flat	300 Mtrs	6.3.14
B.7.5	6 sq. mm wire	1200 Mtrs	6.3.14
B.7.6	Treated Earth Pit	64 Sets*	6.3.14
B.8.0	LIGHTNING PROTECTION		
B.8.1	Vertical Air Termination of size 20 mm dia, 1000 mm long Galvanised Steel Rod with conical end	38 Nos.	6.3.14
B.8.2	Test Links for lightning protection	38 Nos.	6.3.14
B.8.3	25 x 6 mm GI Flat Strips for lightning protection	2625 Mtrs	6.3.14

SL. NO.	DESCRIPTION	Qty Unit 10	Clause Ref No:
C. 1	BHEL-RANIPET SCOPE		
C.1.0	ESP		
C.1.1	ESP LT MAIN SWITCH BOARD Dimension: 11600 x 1700 x 2400 mm Weight: 8000kg (approx).	1 No.	6.3.3
C.1.2	AUXILIARY CONTROL PANEL Dimension : 10800 x 1000 x 2400 mm Weight : 6000 kg (approx)	02 Nos.	6.3.3
C.1.3	STARTER BOX FOR DC AIR HEATER MOTOR Dimension: 750 x 375 x 1000 mm Weight : 200 kg each (approx.)	02 Nos.	6.3.3
C.1.4	ELECTRONIC CONTROLLER with only one loose supplied BAPCON Controller Dimension : 700 x 660 x 2000 mm Weight : 400 kg	14 Sets*	6.3.3

SL. NO.	DESCRIPTION	Qty Unit 10	Clause Ref No:
C. 1	BHEL-RANIPET SCOPE		
C.1.5	RAPPER CONTROL PANEL , with 2 Nos of LOOSE SUPPLIED RAPCON Controller . Size : 1000 x 660 x 2000 mm Approximate Weight : 400 kg	1 Set*	6.3.3
C.1.6	IOS-PC, DC logger PC & Printer	1 set*	6.3.3
C.1.7	Ash Level Indicator	28 Sets*	6.3.7
C.2.0	TESTING of HEATING ELEMENTS & THERMOSTAT		
C.2.1	HEATING ELEMENTS FOR HOPPER	446 Nos.	6.3.8
C.2.2	HEATING ELEMENTS FOR SHAFT INSULATOR	14 Nos.	6.3.8
C.2.3	HEATING ELEMENTS FOR SUPPORT INSULATORS	66 Nos.	6.3.8
C.2.4	THERMOSTAT FOR SUPPORT INSULATORS	2 Nos.	6.3.8
C.2.5	THERMOSTAT FOR HOPPER HEATER	14 Nos	6.3.8
C.3.0	LOCAL START STOP PUSH BUTTON STATION	40 Nos.	6.3.12

SL. NO.	DESCRIPTION	Qty Unit 10	Clause Ref No:
C. 1	BHEL-RANIPET SCOPE		
C.4.0	JUNCTION BOXES (POWER AND CONTROL) Approximate weight: 12 kg each	40 Nos.	6.3.12
C.5.0	CABLES FRLS, PVC, Al conductor cable		
C.5.1	4 C x 1.5 sq. mm FRLS Cu, Screened Armoured Cable	3000 Mtrs	6.3.10
C.6.0	CABLE TRAYS		
C.6.1	450 mm, Ladder type Tray	676 Mtrs	6.3.11
C.7.0	EARTHING MATERIALS		
C.7.1	50 x 6 mm GI Flat	550 Mtrs	6.3.14
C.7.2	30 x 5 mm GI Flat	350 Mtrs	6.3.14
C.7.3	Dia 3.15 mm GI Wire	2400 Mtrs	6.3.14

SL. NO.	DESCRIPTION	Qty Unit 10	Clause Ref No:
C. 1	BHEL-RANIPET SCOPE		
C.8.0	SUPPORT MATERIALS		
C.8.1	Structural steel for fabrication of supports (Angles, Channels etc.)	6 Tonnes	6.3.13
C.9.0	COMMISSIONING		
C.9.1	HIGH VOLTAGE TR. RECTIFIER The scope of work includes oil filtration, sample testing for dielectric strength, PPM etc., calibration of WTI, temperature gauges, Bucholz relay etc. Approximate Oil Weight: 760 kg/ trf	14 Nos.	6.3.18
C.9.2	L.T. GEARED MOTOR (Rapping motors)	40 Nos.	6.3.18
D.1	BHEL-PIPING CENTRE SCOPE		
D.1.0	COMMISSIONING		
D.1.1	BIIDIRECTIONAL MOTORS (L.T.)	5 Nos.	6.3.18

SL. NO.	DESCRIPTION	Qty Unit 10	Clause Ref No:
E.1	BHEL-TRICHY SCOPE		
E.1.1	DC SCANNER AIR FAN MOTOR STARTER BOX Dimension: 900 x 1120 x 476 mm Approximate weight: 200 kg	1 No.	6.3.3
E.1.2	FURNACE TEMPERATURE PROBE STARTER BOX Dimension: 900 x 1120 x 476 mm Weight: 260 kg	1 No.	6.3.3
E.2.0	LT POWER CABLES		
E.2.1	3C x 2.5 sqmm, Cu, Armoured, PVC insulated	21000 Mtrs	6.3.10
E.3.0	CONTROL CABLES		
E.3.1	4C x 2.5 sqmm, Cu, Armoured, PVC insulated	1500 Mtrs	6.3.10

SL. NO.	DESCRIPTION	Qty Unit 10	Clause Ref No:
E. 1	BHEL-TRICHY SCOPE		
E.4.0	CABLE TRAYS		
E.4.1	Perforated Type, 100mm wide	2375 Mtrs	6.3.11
E.4.2	Perforated Type, 150mm wide	1000 Mtrs	6.3.11
E.4.3	Perforated Type, 50mm wide	500 Mtrs	6.3.11
E.5.0	JUNCTION BOXES	150 Nos	6.3.12
E.6.0	COMMISSIONING		
E.6.1	Hoist	1 No	6.3.18
E.6.2	UNIDIRECTIONAL MOTORS (L.T.) (Includes Soot Blower Motors also)	109 Nos.	6.3.18
E.6.3	BIDIRECTIONAL DRIVES (L.T.) (Includes Soot Blower Motors also)	108 Nos.	6.3.18
E.6.4	6.6kV , HT Motors (PA FAN-2 Nos , FD FAN-2 Nos, CEP-2 Nos, MILL MOTOR-6 Nos, BFP-2 Nos & ID FAN-2 Nos; per Unit)	16 Nos	6.3.18

SL. NO.	DESCRIPTION	Qty Unit 10	Clause Ref No:
F.1	BHEL-EDN SCOPE		
F.1.1	<p>AVR</p> <p>Digital AVR comprising of Regulation Cubicle, Thyristor Cubicle, Field Suppression Cubicle along with loose supplied items.</p> <p>Overall dimension : 4060 x 760 x 2296 mm</p> <p>Total Weight : 1000 kg</p>	1 set*	6.3.4
F.1.2	<p>UNIT ELECTRICAL CONTROL PANEL (UECP)</p> <p>Approx Overall dimensions: 1500 x 800 x 2415 mm</p> <p>Approx weight: 800kg.</p>	1 No	6.3.4
F.1.3	<p>TRANSDUCER & AVT PANEL (AVT)</p> <p>Approx Overall dimensions: 1000 x 800 x 2415 mm</p> <p>Approx weight: 700kg.</p>	1 No	6.3.4
F.1.4	<p>GENERATOR RELAY PANEL (GRP)</p> <p>Approx Overall dimensions: 4000 x 800 x 2415 mm</p> <p>Approx weight: 2000kg.</p>	1 No	6.3.4

G.1	BHEL-BHOPAL SCOPE		
G.1.1	GENERATOR, GT & UAT PROTECTION PANELS 4 Nos. panels having each Panel Dimension : 2600 x 1200 x 1200 mm dispatched in 4 shipping sections. Approximate weight: 600 kg	1 set*	6.3.4
H.1	BHEL-HYDERABAD SCOPE		
H.1.0	COMMISSIONING		
H.1.1	UNIDIRECTIONAL MOTORS (L.T.)	11 Nos.	6.3.18
H.1.2	BIDIRECTIONAL DRIVES (L.T.)	18 Nos.	6.3.18
H.1.3	Commissioning of GENERATOR The scope of work includes measuring IR Value, HV Test for Generator Bushing, improving IR value, measuring winding resistance etc.	1 No.	6.3.18

SL. NO.	DESCRIPTION	Qty Unit 10	Clause Ref No:
I.1	CUSTOMER SCOPE OF SUPPLY		
I.1.0	HT CABLES		
	<i>6.6 KV, Armoured FRLS Cable, Al Conductor</i>		
I.1.1	1 C x 500 sq. mm (Al)	900 Mtrs.	6.3.10
I.1.2	3 C x 185 sq. mm (Al)	1900 Mtrs	6.3.10
I.2.0	LT POWER CABLES, FRLS, PVC, Armoured		
I.2.1	4 C x 16 sq. mm , Al	5000 Mtrs	6.3.10
I.2.2	4 C x 10 sq. mm, Al	1500 Mtrs	6.3.10
I.2.3	4 C x 6 sq. mm , Al	2500 Mtrs	6.3.10
I.2.4	3.5 C x 240 sq. mm , Al	2000 Mtrs	6.3.10
I.2.5	3.5 C x 120 sq. mm , Al	2500 Mtrs	6.3.10
I.2.6	3.5 C x 95 sq. mm , Al	825 Mtrs	6.3.10
I.2.7	3.5 C x 70 sq. mm , Al	1875 Mtrs	6.3.10
I.2.8	3.5 C x 50 sq. mm , Al	8500 Mtrs	6.3.10
I.2.9	3.5 C x 25 sq. mm , Al	4500 Mtrs	6.3.10
I.2.10	3 C x 70 sq. mm , Al	2385 Mtrs	6.3.10

BOM/20

SL. NO.	DESCRIPTION	Qty Unit 10	Clause Ref No:
I.1	CUSTOMER SCOPE OF SUPPLY		
I.2.11	3 C x 50 sq. mm , Al	1750 Mtrs	6.3.10
I.2.12	3 C x 35 sq. mm , Al	235 Mtrs	6.3.10
I.2.13	3 C x 25 sq. mm , Al	750 Mtrs	6.3.10
I.2.14	3 C x 16 sq. mm, Al	2750 Mtrs	6.3.10
I.2.15	3 C x 10 sq. mm , Al	3675 Mtrs	6.3.10
I.2.16	3 C x 6 sq. mm , Al	6575 Mtrs	6.3.10
I.2.17	2 C x 240 sq. mm , Al	250 Mtrs	6.3.10
I.2.18	2 C x 120 sq. mm , Al	3000 Mtrs	6.3.10
I.2.19	2 C x 50 sq. mm , Al	2250 Mtrs	6.3.10
I.2.20	2 C x 25 sq. mm , Al	2250 Mtrs	6.3.10
I.2.21	2 C x 16 sq. mm , Al	1710 Mtrs	6.3.10
I.2.22	2 C x 6 sq. mm , Al	4010 Mtrs	6.3.10
I.2.23	2 C x 35 sq. mm , Al	660 Mtrs	6.3.10
I.2.24	3 C x 150 sq. mm , Al	550 Mtrs	6.3.10
I.2.25	2 C x 70 sq. mm , Al	135 Mtrs	6.3.10
I.2.26	3.5 C x 4 sq. mm , Al	2000 Mtrs	6.3.10
I.2.27	1 C x 10 sq. mm , Cu	750 Mtrs	6.3.10

BOM/21

SL. NO.	DESCRIPTION	Qty Unit 10	Clause Ref No:
I.1	CUSTOMER SCOPE OF SUPPLY		
I.2.28	1 C x 16 sq. mm , Cu	750 Mtrs	6.3.10
I.3.0	LT CONTROL CABLES, Armoured		
I.3.1	19 C x 2.5 sq. mm, Cu	1500 Mtrs	6.3.10
I.3.2	14 C x 2.5 sq. mm, Cu	3250 Mtrs	6.3.10
I.3.3	10 C x 2.5 sq. mm , Cu	37725 Mtrs	6.3.10
I.3.4	7 C x 2.5 sq. mm, Cu	5550 Mtrs	6.3.10
I.3.5	5 C x 2.5 sq. mm, Cu	56000Mtrs	6.3.10
I.3.6	4 C x 2.5 sq. mm , Cu	750 Mtrs	6.3.10
I.3.7	3 C x 2.5 sq. mm , Cu	29775Mtrs	6.3.10
I.3.8	10 C x 1.5 sq. mm , Cu	6600 Mtrs	6.3.10
I.3.9	4 C x 1.5 sq. mm , Cu	3250 Mtrs	6.3.10
I.3.10	7 C x 1.5 sq. mm , Cu	2500 Mtrs	6.3.10
I.3.11	2C x 1.5 sq. mm , Cu	375 Mtrs	6.3.10
I.3.12	24C x 2.5 sq. mm , Cu	500 Mtrs	6.3.10
I.3.13	2 C x 2.5 sq. mm, Cu	67350 Mtrs	6.3.10
I.3.14	3 C x 1.5 sq. mm, Cu	100 Mtrs	6.3.10

SL. NO.	DESCRIPTION	Qty Unit 10	Clause Ref No:
I.1	CUSTOMER SCOPE OF SUPPLY		
I.4.0	LT POWER CABLE TERMINATIONS		
I.4.1	3.5 C x 240 sq. mm , Al	26 Nos.	6.3.10
I.4.2	3.5 C x 120 sq. mm , Al	34 Nos	6.3.10
I.4.3	3.5 C x 95 sq. mm , Al	12 Nos	6.3.10
I.4.4	3.5 C x 70 sq. mm , Al	26 Nos	6.3.10
I.4.5	3.5 C x 50 sq. mm , Al	114 Nos	6.3.10
I.4.6	3.5 C x 25 sq. mm , Al	60 Nos	6.3.10
I.4.7	3 C x 70 sq. mm , Al	32 Nos	6.3.10
I.4.8	3 C x 50 sq. mm , Al	24 Nos	6.3.10
I.4.9	3 C x 35 sq. mm , Al	4 Nos	6.3.10
I.4.10	3 C x 25 sq. mm , Al	10 Nos	6.3.10
I.4.11	3 C x 16 sq. mm, Al	36 Nos	6.3.10
I.4.12	3 C x 10 sq. mm , Al	50 Nos	6.3.10
I.4.13	3 C x 6 sq. mm , Al	88 Nos	6.3.10
I.4.14	4 C x 16 sq. mm , Al	66 Nos	6.3.10
I.4.15	4 C x 10 sq. mm, Al	20 Nos	6.3.10
I.4.16	4 C x 6 sq. mm , Al	33 Nos	6.3.10

SL. NO.	DESCRIPTION	Qty Unit 10	Clause Ref No:
I.1	CUSTOMER SCOPE OF SUPPLY		
I.4.17	2 C x 240 sq. mm , Al	4 Nos	6.3.10
I.4.18	2 C x 120 sq. mm , Al	40 Nos	6.3.10
I.4.19	2 C x 50 sq. mm , Al	30 Nos	6.3.10
I.4.20	2 C x 25 sq. mm , Al	30 Nos	6.3.10
I.4.21	2 C x 16 sq. mm , Al	24 Nos	6.3.10
I.4.22	2 C x 6 sq. mm , Al	54 Nos	6.3.10
I.4.23	2 C x 35 sq. mm , Al	8 Nos	6.3.10
I.4.24	3 C x 150 sq. mm , Al	8 Nos	6.3.10
I.4.25	2 C x 70 sq. mm , Al	2 Nos	6.3.10
I.4.26	3.5 C x 4 sq. mm , Al	26 Nos	6.3.10
I.4.27	1 C x 10 sq. mm , Cu	10 Nos	6.3.10
I.4.28	1 C x 16 sq. mm , Cu	10 Nos	6.3.10