



BHARAT HEAVY ELECTRICALS LIMITED
TRANSMISSION BUSINESS ENGINEERING MANAGEMENT
NEW DELHI

COPYRIGHT & CONFIDENTIAL
 THE INFORMATION CONTAINED IN THIS DOCUMENT IS THE PROPERTY OF BHARAT HEAVY ELECTRICALS LIMITED
 THIS MUST NOT BE USED DIRECTLY OR INDIRECTLY IN ANY MANNER DETRIMENTAL TO THE INTEREST OF THE COMPANY

DOCUMENT No.	TB-366-316-021	Rev	00		Prepared	Checked	Approved
CUSTOMER Doc. No.		NAME			VK	MVK	MK
TYPE OF DOC.	TECHNICAL SPECIFICATION	SIGN			<i>[Signature]</i>	<i>[Signature]</i>	<i>[Signature]</i>
TITLE 33/0.433 kV, 630 kVA LT Transformers				DATE	21/4/14	21/4/14	21/4/14
				GROUP	TBEM		
				W.O. No			
CUSTOMER	POWER GRID CORPORATION OF INDIA LIMITED						
PROJECT	Substation Package for Extension of I) 400kV Durgapur S/s, II) 400 kV Maithon S/s, III) 400 kV Biharshariff S/s & IV) 220/132V Purnea S/s						

<u>List of Contents</u>	<u>No. of Pages</u>
Cover Sheet	01
Section 1 Scope & Quantities	04
Section 2 Customer Specification (Specific Technical Requirements)	12
Section 3 Project Details and General Specification	23
Section 4 Guaranteed Technical Particulars	04
<u>Enclosures:</u>	
Annexure – A (NO DEVIATION Certificate)	01

00					First Issue	
Rev.	Date	Altered	Checked	Approved	REVISION DETAILS	
Distribution				CUSTOMER	TBMM	O/C
				-	4	1

SECTION - 1

1.1 SCOPE

This technical specification covers the requirements of design, manufacture, testing at works, packing and dispatch of outdoor type oil filled 33/0.433 kV, 630 kVA transformers complete with accessories to site.

This section covers the scope and quantities of outdoor type oil filled 33/0.433 kV, 630 kVA transformers. The Specific Technical Requirements for the above item as specified by the customer (PGCIL) are given in Section-2. The offered equipment shall also comply with the General Technical Requirements for the project as detailed under section-3 of this specification.

In case of any discrepancies between the requirements mentioned under Section-1/Section-2 and those specified in the Section-3, the specifications given under Section-1/Section-2 shall prevail and shall be treated as binding requirements.

The equipment is required for the following project:

Name of the Customer : POWER GRID CORPORATION OF INDIA LIMITED (PGCIL)
Name of the Project : Extension of I) 400kV Durgapur S/s, II) 400 kV Maithon S/s,
III) 400 kV Biharshariff S/s & IV) 220/132V Purnea S/s

The scope of supplies shall be as per commercial terms and conditions enclosed separately with the enquiry.

1.2 SPECIFIC TECHNICAL REQUIREMENTS

Equipments and system shall be designed to meet the following major technical parameters as brought out hereunder.

Sl. No.	Description	Parameters
1.	Type	Two winding
2.	Service	Outdoor
3.	Number of phases	Three
4.	Frequency	50 Hz
5.	Type of Cooling	ONAN
6.	Rating and Ratio	630kVA, 33/0.433 kV
7.	Impedance at 75 ⁰ C	0.05 %
	Tolerance on Impedance	+ 10%
8.	Duty	Continuous
9.	Overload	As per IS:6600
10.	Maximum Temp. rise over an ambient of 50 ⁰ C	
i)	Oil (Temp. rise measurement by thermometer)	50 ⁰ C
ii)	Winding (Temp. rise measurement	55 ⁰ C

	by resistance method)		
11.	Windings	33 kV 630 kVA	0.433 kV
i)	System apparent short circuit level (kA)	-----As per IS:2026 (Part-I) -----	
ii)	Winding Connection	Delta	Star
iii)	Vector Group	----Dyn 1----	
iv)	Insulation	----Uniform----	
v)	Insulation level (kV)	HV	LV
a)	Power frequency test level (kVrms)	95	2
b)	Basic Impulse level (kVpeak)	250	--
vi)	Highest voltage (kV) for each winding	52	
vii)	Method of earthing	----Solidly earthed----	
12.	Tap Changer		
i)	Tap range	----- +5% /-10% in steps of 2.5% on HV side-----	
ii)	Tap control	Off-circuit tap change switch	
13.	HV Bushings		
i)	Rated Voltage, kV	52	
ii)	Rated Current, A	100	
iii)	Basic Impulse level, kV	250	
iv)	Wet and dry power frequency withstand voltage (kVrms)	95	
v)	Minimum total Creepage distance (mm)	1300	
vi)	Mounting	Tank / Transformer body	
14.	LV and Neutral Bushing		
i)	Rated Voltage (kV)	1.1	
ii)	Rated Current, A	1000	
iii)	Wet & Dry Power frequency Withstand Voltage (kVrms)	2	
iv)	Mounting	Tank / Transformer body	
15.	Terminal details		
i)	High Voltage	Suitable for 33kV cable or O/H Conductor	
ii)	Low Voltage phase and Neutral	Cable Box	
16.	Minimum Clearance in Air (mm)	HV	LV
i)	Phase to Phase	530	25
ii)	Phase to Earth	480	25
17	Guaranteed Losses at rated output	33/0.433 kV 630 kVA	
i)	Copper Losses (kW)	7.2	
ii)	Iron Losses (kW)	1.1	

GUARANTEED LOSSES: The above indicated losses are maximum losses with no positive tolerance. The equipment under no circumstances shall be accepted, if the measured losses are

more than guaranteed losses.

1.3 BILL OF QUANTITIES

The following items are required for Purnea S/s:

S. No.	Details	Unit	Qty
1.	630 kVA, 33/0.433 kV, ONAN, Dyn1, 3-phase Transformer as per specification complete with accessories (Destination: Purnea)	No	1

1. Ten (10) percent extra oil shall also be supplied for topping up, in non-returnable containers suitable for outdoor storage.
2. Supply of lugs for proper termination of 2-1Cx630 sqmm XLPE cables (per phase) and 1-1Cx630 sqmm XLPE cables (for neutral) on LV side of LT Transformer is deemed to be included in bidder's scope.
3. Size of cable box on LV side shall be adequate enough for proper termination of XLPE cables.

In addition, the Bidder shall also recommend optional spare parts and maintenance equipment necessary for three (3) years of successful operation of the equipment. The prices of these shall be indicated in separate schedules and these shall not be considered for the purpose of evaluation.

1.4 QUALIFYING REQUIREMENT

The manufacturer, whose transformers are offered should have designed, manufactured, type tested including short circuit test as per IEC/IS or equivalent standards and supplied transformers of at least 33 kV class of 800 KVA or higher. The transformer should have been in successful operation for at least 2 years as on the date of bid opening i.e. 23.11.12.


1.5 TYPE TESTING

Bidder shall submit valid type test reports (as per relevant IEC/IS Standard) for approval. The type test reports submitted shall be of tests conducted within last 10 years prior to the date of bid opening i.e. 23.11.12. The bidder should have conducted type test on identical or similar equipment/ components to those offered. In case type test reports are found to be technically unacceptable to BHEL/PGCIL, the type test shall be conducted without cost and delivery implication to BHEL.

1.6 QUALITY PLAN

Bidder to follow valid PGCIL approved Quality Plan as per PGCIL procedure. In case the bidder don't have PGCIL approved QP, it will be the bidder's responsibility to get its QP approved directly from the ultimate customer.

1.7 PROJECT TITLE BLOCK

CUSTOMER	POWERGRID CORPORATION OF INDIA LIMITED		
PROJECT	Substation Package for Extension of I) 400kV Durgapur S/s, II) 400 kV Maithon S/s, III) 400 kV Biharshariff S/s & IV) 220/132V Purnea S/s		
CONTRACT NO	CC-CS/153-ER1/SS-1945/3/G8/R/NOA-1/4737, dtd. 08.08.13		
BHEL P.O. No.	PROJ. DOC. No.	REV. No.	
CONTRACTOR	BHARAT HEAVY ELECTRICALS LIMITED		
<i>VENDOR'S STANDARD TITLE BLOCK</i>			

-- X X --

SECTION – 2

As per enclosed Powergrid Technical Specification: LT Transformer (Ref:
C/ENGG/SPEC/LT-TRF, Rev. No. 4, (11 Pages))

MODEL TECHNICAL SPECIFICATION

SECTION: LT TRANSFORMER

SECTION: LT TRANSFORMER

Table of contents

Clause No.	Description	Page No.
1.0	INTENT	3
2.0	SCOPE OF WORK	3
3.0	GENERAL INFORMATION	3
4.0	TECHNICAL REQUIREMENT	4
5.0	INSPECTION AND TESTING	5
6.0	INSPECTION	5
7.0	FACTORY TEST	6
8.0	FITTINGS	8
9.0	SPARE PARTS	8
10.0	TECHNICAL PARAMETERS	9

SECTION: LT TRANSFORMER

1.0 INTENT

This specification is intended to cover outdoor type oil filled 33/0.433KV, 800 & 630 kVA & 11/0.433kV, 630 & 250 kVA transformers .

2.0 Scope of Work

2.1 Scope of Supply

- Transformers as listed above, with insulating oil, all materials and accessories, and complete in all respects.
- Gland plates, power cable, lugs, anchor bolts and hardwares.
- Mandatory & optional spares and special maintenance equipments if any.

2.2 Scope of Service

The scope includes but is not limited to the following items of work to be performed for all equipment and materials furnished under this section:

- a) Design, manufacturing, shop testing, packing & despatch
- b) Transportation inclusive of insurance and delivery, FOR site basis
- c) Unloading, handling, storing, transportation at site up to foundations, oil filling and treatment, erection, testing and commissioning
- d) Civil Works
- e) Supply of external cables and termination as required.
- f) Fire protection system.

3.0 General Information

- 3.1 All temperature indicators, Buchholz relays and other auxiliary devices shall be suitable for 220 V DC Control supply. All alarm and trip Contacts shall also be suitable for connection in 220V DC Circuits.

3.2 Bidders may specifically note that transformers offered shall conform to dynamic short circuit test and dielectric test as per IS-2026. Test report for the same shall be submitted during detail engineering for approval of POWERGRID.

4.0 **TECHNICAL REQUIREMENTS**

4.1 **Core**

The core shall be constructed from high grade, non-aging, cold rolled grain-oriented silicon steel laminations. The maximum flux density in any part of the cores and yoke at normal voltage and frequency shall be such that the flux density at any tap position with 10% voltage variation from the voltage corresponding to the tap shall not exceed 1.9 Wb/sq-m.

4.2 **Windings**

The conductor shall be of electrolytic copper, free from scales and burrs.

4.3 **Insulating Oil**

The oil supplied with transformer shall be unused and have the parameters for unused new oil conforming to IS:335 while tested at oil Contractor's premises, No inhibitors shall be used in oil. Ten percent extra oil shall be supplied for topping up after commissioning in nonreturnable containers suitable for outdoor storage.

4.4 **Terminal Arrangement**

- a) Bushing terminals shall be provided with suitable terminal connectors of approved type and size for cable/overhead conductors termination of HV side and cable termination on LV side.
- b) The neutral terminals of 433V winding shall be brought out on a bushing along with the 433 volt phase terminals to form a 4 wire system for the 415 volt. Additional neutral bushing shall also be provided for earthing.

4.5 **Off Circuit Tap Changing Equipment**

The tap change switch shall be three phase, hand operated for simultaneous switching of similar taps on the three phases by operating an external hand wheel.

4.6 **Marshalling Box**

A metal enclosed, weather, vermin & dust proof marshalling box shall be provided with each transformer to accommodate temperature indicators, terminal blocks etc. It shall have a degree of protection of IP 55 as per IS: 13947Part-1.

4.7 **Cable boxes**

Whenever cable connections are required, suitable cable boxes shall be provided and shall be air insulated. They shall be of sufficient size to accommodate Purchaser's cables and shall have suitable removable side/top cover to facilitate cable termination and inspection. Cable boxes shall be dust & vermin proof.

5.0 **Inspection and Testing**

- a) The Contractor shall draw up and carry out a comprehensive inspection and testing program during manufacture and commissioning of the transformer. The programme shall be duly approved by the Purchaser.
- b) The Contractor shall carry out all routine tests on all the transformers as per relevant standards. Type test report shall be submitted for approval of POWERGRID during detail engineering.

6.0 **Inspection**

6.1 **Tank and Accessories**

- a) Physical and dimensional check of transformer tank and accessories.
- b) Crack detection of major strength weld seams by dye penetration test.

6.2 **Core**

- a) Physical inspection and check of quality of varnish, if used.
- b) Sample testing of core material for checking specific loss, bend properties, magnetisation, characteristics and thickness.
- c) Check on completed core for measurement of iron loss and check for any hot spot by exciting the core so as to induce the designed value of flux density in the core.
- d) HV Test

6.3 **Insulating Material**

- a) Sample checks for physical properties of the material
- b) Check for dielectric strength
- c) Check for the reaction of hot oil on insulating material

6.4 **Winding**

- a) Sample check on winding conductor for mechanical properties and electrical conductivity and on installation covering.
- b) Sample check on insulation paper for pH value, Bursting strength, Electric strength.

6.5 **Assembled Transformer**

- a) Check complete transformer against approved outline drawing provision for all fittings, finish etc.
- b) Jacking test on all the assembled transformers.

6.6 **Oil**

All standard tests in accordance with relevant Standards shall be carried out on oil samples taken from the transformer before and after testing of the transformer.

The contractor shall also prepare a comprehensive inspection and testing programme for all bought out sub-contracted items and shall submit the same to the Purchaser for approval. Such programme shall include the following components:

- a) Buchholz Relay
- b) Winding temperature Indicator
- c) Bushings
- d) Marshaling Box
- e) Tap changer switch
- f) Oil temperature indicator

7.0 **Factory Test**

7.1 All standard routine tests in accordance with latest issue of IS : 2026 shall be carried out on each transformer.

7.2 The transformer shall conform to all the type tests in accordance with latest issues of IS : 2026. The manufacturer shall submit type tests & additional test reports as listed above as already carried out on transformers of identical design for owner's acceptance . In such a case validity of type test reports shall be in line with clause 9.2 of Sec-GTR of technical specifications. Following parameters in general shall be ensured for establishment of identical design as per IEC 60076, Part-V.

- a) Same Voltage ratio, KVA rating, vector group & impedance.
- b) Same conceptual design of core and winding.
- c) Same arrangement and geometrical sequence of the main windings.
- d) Same type of winding conductors.

- e) Same type of main windings.
 - f) Absorbed power at short circuit (ie rated power/per unit short circuit impedance) between 30% and 130% of that relating to the reference transformer.
 - g) Axial forces and winding stresses occurring at short circuit not exceeding 120% of those relating to the reference transformer.
 - h) Same manufacturing process.
 - i) Same Clamping and winding support arrangement..
- 7.3 In addition to all type and routine tests, transformer shall also conform to following additional type tests as per IS : 2026.
- a) Measurement of zero sequence impedance
 - b) Short circuit test
 - c) Measurement of acoustic noise level. This shall conform to NEMA standard publication TR-1.
 - d) Measurement of capacitance and tan delta of transformer winding.
 - e) Test on oil samples as per IS 335-1993
- 7.4 All auxiliary equipment shall be tested as per the relevant IS Test Certificates shall be submitted for bought out items.
- 7.5 High voltage withstand test shall be performed on auxiliary equipment and wiring after complete assembly.
- 7.6 Tank Tests:
- a) Routine Tests: As per CBIP Manual on Transformers including
 - i) Vacuum Tests: As per CBIP Manual on Transformers
 - ii) Pressure Test: As per CBIP Manual on Transformers
- 7.7 In addition to the above, the following checks should be carried out at manufacturer's works before despatch for all transformers:
- a) Check for interchangeability of components of similar transformers and for mounting dimensions.
 - b) Check for proper packing and preservation of accessories like radiators, bushings explosion vent, dehydrating breather, Buchholz relay, conservator etc.
 - c) Check for proper provision of bracings to arrest the movements of core and winding assembly inside the tank.

- d) Test for gas tightness and derivation of leakage rate. To ensure adequate reserve gas capacity during transit and storage.

7.8 The Contractor shall submit a detailed inspection and testing programme for field activities, covering areas right from the receipt of material stage upto commissioning stage as per IS : 1886 - Code of practice for installation and maintenance of transformers. The indicative checks and tests are given below.

- a) Physical checks on each transformer on receipt at site for any damage or short supply.
- b) Tests on oil samples
- c) Oil leakage test
- d) Physical checks for colour of silica in breather
- e) Check for oil level in breather housing, conservator tank, etc.
- f) Check for correct operation of all protections and alarms.
- g) Insulation Resistance Measurement for Main Winding, control wiring etc.
- h) Continuously observe the transformer operation at no load for 24 hours.

8.0 **Fittings**

The following fittings shall be provided with each transformer covered under this specification.

- i) Conservator with drain plug and oil filling hole with blanking plate
- ii) Plain oil Gauge
- iii) Silica gel Breather
- iv) Pressure Relief vent
- v) Pocket on tank cover for Thermometer
- vi) Valves
- vii) Earthing Terminals
- viii) Rating & Terminal Marking Plates
- ix) Lifting Lugs
- x) Rollers
- xi) Air Release Plug

The fittings listed above are only indicative and any other fittings which generally are required for satisfactory operation of transformer are deemed to be included.

9.0 **Spare Parts**

9.1 The list of spares for outdoor type transformers covered under this section shall be as specified in Section-Project

9.2 In addition, the Bidder shall also recommend optional spare parts and maintenance equipment necessary for three(3) years of successful operation of the equipment. The prices of these shall be indicated in respective schedules and these shall not be considered for the purpose of evaluation.

10.0 Technical Specification

S No	Description	Unit	Parameters			
1	Rated Capacity	kVA	250	630	630	800
2	Rated Voltage					
a)	HV	kV	11	11	33	33
b)	LV	kV	0.433	0.433	0.433	0.433
3	Type of Winding		Two Winding			
4	Service		Outdoor			
5	No of Phases	No.	Three			
6	Frequency	Hz	50			
7	Type of Cooling		ONAN	ONAN	ONAN	ONAN
8	Impedance at 75 Deg C	%	0.05	0.05	0.05	0.05
9	Tolerance on Impedance	%	±10	±10	±10	±10
10	Duty		Continuous	Continuous	Continuous	Continuous
11	Overload		IS 6600	IS 6600	IS 6600	IS 6600
12	Max. Temp. Rise over an ambient of 50 Deg C					
a)	Oil (Temperature rise measurement by thermometer)	°C	50			
b)	Winding Temperature rise measurement by resistance method)	°C	55			
13	Windings					
a)	System Apparent Short circuit level (kA)		As per IS 2026-Part 1			
b)	Winding Connection					
(i)	HV		Delta	Delta	Delta	Delta
(ii)	LV		Star	Star	Star	Star
14	Vector Group		Dyn1			
15	Insulation		Uniform			
16	Insulation Level	kVrms				

S No	Description	Unit	Parameters			
a)	Power Frequency Test Level					
(i)	HV	kVrms	28	28	95	95
(ii)	LV	kVrms	2			
17	Basic Impulse Level					
(i)	HV	kVp	75	75	250	250
(ii)	LV	kVp	-	-	-	-
18	Highest voltage (kV) for each winding	kV	12	12	52	52
19	Method of earthing		Solidly earthed			
20	Tap changer					
a)	(i) Tap Change		+5% to -10% in step of 2.5% on HV side			
b)	(ii) Tap control		Off Circuit Tap Change Switch			
21	HV Bushing					
a)	Rated Voltage	kV	12	12	52	52
b)	Rated current	A	100	100	100	100
c)	Basic Impulse Level (kVp)	kVp	75	75	250	250
d)	Wet & Dry Power frequency Withstand Voltage	kVrms	28	28	95	95
e)	Min. Total Creepage Distance	mm	300	300	1300	1300
f)	Mounting		Tank / Transformer Body			
22	LV & Neutral Bushing					
a)	Rated Voltage	kV	1.1	1.1	1.1	1.1
b)	Rated current	A	1000	1000	1000	2000
c)	Basic Impulse Level (kVp)	kVp	-	-	-	-
d)	Wet & Dry Power frequency Withstand Voltage	kVrms	2	2	2	2
e)	Mounting		Tank / Transformer Body			
23	Terminal Details					
a)	HV		Suitable for 11kV Cable or Over Head Conductor		Suitable for 33kV Cable or Over Head Conductor	
b)	LV & Neutral		Cable Box			

S No	Description	Unit	Parameters			
24	Min. Clearance in Air	mm				
a)	Ph-Ph (HV/LV)	mm	280/25	280/25	530/25	530/25
b)	Ph-Earth (HV/LV)	mm	140/25	140/25	480/25	480/25

SECTION-3**PROJECT DETAILS & GENERAL SPECIFICATION****SITE INFORMATION**

	Particular	Details
a)	Customer	Power Grid Corporation of India Limited
b)	Project Title	Extension of I) 400kV Durgapur S/s, II) 400 kV Maithon S/s, III) 400 kV Biharshariff S/s & IV) 220/132V Purnea S/s
c)	Location	Durgapur/ Maithon (West Bengal) Biharshariff/Purnea (Bihar)
d)	Transport Facilities	Nearest Rail Head Durgapur (Durgapur), Maithon (Maithon), Biharshariff (Biharshariff) & Purnea (Katihar)
SITE CONDITIONS		
a)	Altitude above sea level	Less than 1000m
b)	Ambient air temp. (Max)	50°C
c)	Average Humidity	Max. 100%
d)	Special corrosion conditions	No
e)	Solar Radiation	1.2 kW/sq mtr
f)	Atmospheric UV radiation	High
g)	Seismic Acceleration	0.3g horizontal
h)	Pollution Severity	High Pollution level (25mm/kV)
WIND DATA		
a)	Wind velocity	As per IS
b)	Average No. of thunderstorm days per annum	As per IS

1.0 GENERAL

This Chapter covers Technical Requirements and requirements of auxiliary items.

- a) Equipment furnished shall be complete in every respect with all mountings, fittings, fixtures and standard accessories normally provided with such equipment and/or needed for erection, completion and safe

operation of the equipment as required by applicable codes unless included in the list of exclusions.

- b) Material and components not specifically stated in this specification but which are necessary for satisfactory operation of the equipment and accessories specified in this specification shall be deemed to be included unless specifically excluded and shall be supplied at no extra cost.
- c) Whenever a material or article is specified or described by the name of a particular brand, manufacturer or vendor, the specific name mentioned shall be understood as establishing type, function and quality and not as limiting competition.
- d) In case any Deviation Schedule, Bid Proposal Sheet, Schedule of Data Requirements (DRS), test reports or any other document/information are not furnished along-with the bid, the bid is liable to be rejected. Unless brought out clearly, the Bid will be deemed to conform to the specification scrupulously. All deviations from the specification shall be clearly brought out in the respective deviation schedule.
- e) Auxiliary supplies as described below would be available at site.

Normal Voltage	Variation in Voltage	Frequency in HZ	Phase/Wire	Neutral connection
415V	$\pm 10\%$	$50 \pm 5\%$	3/4 Wire	Solidly Earthed.
240V	$\pm 10\%$	$50 \pm 5\%$	1/2 Wire	Solidly Earthed.
220V	190V to 240V	DC	-	Isolated 2 wire System
110V	95V to 120V	DC	-	Isolated 2 wire System
48V	-	DC	-	2 wire system (+) earthed

NOTE: Combined variation of frequency and voltage shall be limited to $\pm 10\%$.

- f) The Bidder shall clearly indicate in the bid, the specific standards in accordance with which the works will be carried out.
- g) The equipment must be new, of highest grade, the best quality of their kind, to best engineering practice and latest state of art, and in accordance with purpose for which they are intended and ensure satisfactory performance throughout the service life.

- h) All similar parts of the equipment shall be made to gauge and shall be interchangeable with and shall be made of same materials and workmanship as the corresponding parts of the equipment. Where feasible, common components, units shall be employed in different pieces of equipment in order to optimize the spare part stock-up and utilization.
- i) The requirement regarding external RIV as specified for equipment shall include the terminal fittings and the equipment shall have been tested preferably with fittings, if any.
- j) All drawings, schedules, annexures appended to this specification shall form part of the specification.

2.0 SERVICES TO BE PERFORMED BY THE EQUIPMENT BEING FURNISHED

- a) The equipment furnished under this specification shall perform all its functions and operate satisfactorily without showing undue strain, restrike etc.
- b) The equipment shall be able to withstand forces due to wind load, short circuit, system over voltages, fluctuations, frequency variations etc., all forces considered together.

3.0 SUPPORT STRUCTURES

- a) The support structures should be hot dip galvanised with minimum 610 gram/m² net of zinc.
- b) The design calculations taking into account the environmental conditions of the substations shall be furnished for sizing of the structures.

4.0 STANDARDS

- a) The equipment to be furnished under this specification shall conform to latest issue with all amendments of standard specified under respective Chapters of this Specification. The Bidder shall note that standards mentioned in the specification are not mutually exclusive or complete in themselves, but intended to compliment each other. The Contractor shall also note that list of standards presented in this specification is not complete. Whenever necessary the list of standards shall be considered in conjunction with specific IS/IEC. When the specific requirements stipulated in the specifications exceed or differ than those required by the applicable standards, the stipulation of the specification shall take precedence.

- b) Other internationally accepted standards which ensure equivalent or better performance than that specified in the standards referred shall also be accepted.
- c) In case governing standards for the equipment is different from IS or IEC, the salient points of difference shall be clearly brought out in additional information schedule alongwith English language version of standard or relevant extract of the same. The equipment conforming to standards other than IS/IEC shall be subject to Employer's approval.

5.0 ENGINEERING DATA AND OTHER REQUIREMENTS

- 5.1 The furnishing of engineering data by the Contractor shall be in accordance with the Schedule for each set of equipment as specified in this Technical Specification and the data furnished under the Schedule of Data Requirements (DRS). The review of these data by the Employer will cover only general conformance of the data to the specifications and documents, interfaces with the equipment provided under the specifications, external connections and of the dimensions which might affect overall layout. This review by the Employer may not indicate a thorough review of all dimensions, quantities and details of the equipment, materials, any devices or items indicated or the accuracy of the information submitted. This review and/or approval by the Employer shall not be considered by the Contractor, as limiting any of his responsibilities and liabilities for mistakes and deviations from the requirements, specified under these specifications and documents.
- 5.2 All engineering data submitted by the Contractor after final process including review and approval by the Employer shall form part of the Contract Document and the entire works performed under these specifications shall be performed in strict conformity, unless otherwise explicitly requested by the Employer in Writing.
- 5.3 The equipment offered shall also comply to the following:-
 - a) To facilitate erection of equipment, all items to be assembled at site shall be "match marked".
 - b) The reports for all type tests and additional type tests as per technical specification shall be furnished by the Contractor alongwith equipment / material drawings. The type tests conducted earlier should have either been conducted in accredited laboratory (accredited based on ISO / IEC Guide 25 / 17025 or EN 45001 by the national accreditation body of the country where laboratory is located) or witnessed by the representative(s) of POWERGRID or Utility. The test reports submitted shall be of the tests conducted within last 5 (five) years prior to the date of bid opening. In case the test reports are of the test

conducted earlier than 5 (five) years prior to the date of bid opening, the contractor shall repeat these test(s) at no extra cost to the purchaser.

In the event of any discrepancy in the test reports i.e. any test report not acceptable due to any design / manufacturing changes (including substitution of components) or due to non-compliance with the requirement stipulated in the Technical Specification or any/all additional type tests not carried out, same shall be carried out without any additional cost implication to the Purchaser.

- c) The Purchaser intends to repeat the type tests and additional type tests on Capacitors for which test charges shall be payable as per provision of contract. The price of conducting type tests and additional type tests shall be included in Bid price and break up of these shall be given in the relevant schedule of Bid Proposal Sheets. These Type test charges would be considered in bid evaluation. In case Bidder does not indicate charges for any of the type tests or does not mention the name of any test in the price schedules, it will be presumed that the particular test has been offered free of charge. Further, in case any Bidder indicates that he shall not carry out a particular test, his offer shall be considered incomplete and shall be liable to be rejected.
- d) Four (4) copies of all test reports shall be submitted for approval before shipment of equipment. The reports shall indicate clearly the standard values specified for each test, to facilitate checking of the test reports. Six (6) bound copies of test reports shall be submitted after approval of test results.
- e) Six (6) copies of documentation of test certificate/ test result alongwith the relevant drawing (wherever applicable) from the raw material stage to final stage as per approved Quality Plan (QP) will be furnished by supplier for each and every equipment immediately after shipment of equipment.
- f) 1 RTF and 8 copies of all drawings for each substation plus 6 copies and one RTF of each drawing for corporate office shall be furnished after approval of drgs. 6 copies of instruction/operation manuals for each substation and corporate centre shall also be furnished after approval of manuals.
- g) The following program shall be followed for approval of drawings/manuals :
 - i. Initial comments/approval by Employer within 4 (four) weeks of receipt of drawings.
 - ii. Resubmission of drawings/manuals within 4 (four) weeks of comments (including both ways postal time).

- iii. Approval of drawings/manuals within 3 weeks of receipt of resubmission. Within 21 days of approval, stipulated number of copies and reproducibles in case of drgs shall be furnished by Contractor.

NOTE : The contractor may please note that all resubmissions must incorporate all comments given in the prior submission by the Employer failing which the submission of documents is likely to be returned.

- h) Six (6) No. of copies of drawings, Schedule of Data Requirements (DRS) and other documents shall be sent for approval. First submission shall be made within 4 weeks of LOA.
- i) All exposed ferrous parts shall be hot dip galvanised as per IS : 2633 & IS : 4579.
- j) All current making and breaking contact surfaces shall preferably be silver plated.
- k) The equipment name plate/ wiring diagram plate should preferably be of stainless steel. In case of aluminium it should be atleast 2 mm thick. The inscription on the name plate/wiring diagram plate shall be engraved and no punching shall be accepted except for equipment Sr. No. and year of manufacture.
- l) Each drawing submitted by the Contractor shall be clearly marked with the name of the Employer, the unit designation, the specifications title, the specification number and the name of the Project. If standard catalogue pages are submitted, the applicable items shall be indicated therein. All titles, notings, markings and writings on the drawing shall be in English. All the dimensions should be in metric units.
- m) Further work by the Contractor shall be in strict accordance with these drawings and no deviation shall be permitted without the written approval of the Employer, if so required.
- n) All manufacturing and fabrication work in connection with the equipment prior to the approval of the drawings shall be at the Contractor's risk. The Contractor may make any changes in the design which are necessary to make the equipment conform to the provisions and intent of the Contract and such changes will again be subject to approval by the Employer. Approval of Contractor's drawing of work by the engineering shall not relieve the contractor of any of his responsibilities and liabilities under the Contract.

6.0 DESIGN IMPROVEMENTS

- 6.1 The Employer or the Contractor may propose changes in the specification of the equipment or quality thereof and if the parties agree upon any such changes, the specification shall be modified accordingly.
- 6.2 The Bidder should however note that changes proposed by him will have to be supported with applicable type test reports.
- 6.3 If any such agreed change is such that it affects the price and schedule of completion, the parties shall agree in writing as to the extent of any change in the price and/or schedule of completion before the Contractor proceeds with the change. Following such agreement, the provision thereof, shall be deemed to have been amended accordingly.

7.0 QUALITY ASSURANCE PROGRAMME

- 7.1 To ensure that the equipment and services under the scope of this Contract whether manufactured or performed within the Contractor's Works or at his Sub-contractor's premises or at the Employer's site or at any other place of Work are in accordance with the specifications, the Contractor shall adopt suitable quality assurance programme to control such activities at all points necessary. Such programme shall be outlined by the Contractor and shall be finally accepted by the Employer after discussions before the award of Contract. A quality assurance programme of the contractor shall generally cover the following :
- a) His organisation structure for the management and implementation of the proposed quality assurance programme.
 - b) System for Document and Data Control.
 - c) Qualification and Experience data of Bidder's key personnel.
 - d) The procedure for purchases of materials, parts components and selection of sub-contractor's services including vendor analysis, source inspection, incoming raw material inspection, verification of material purchases etc.
 - e) System for shop manufacturing and site erection controls including process controls and fabrication and assembly control.
 - f) System for Control of non-conforming products including Deviation Dispositioning, if any and system for corrective and preventive actions based on the feed back received from the Customers and also internally documented system for Customer complaints.
 - g) Inspection and test procedure both for manufacture and field activities.

- h) System for Control of calibration of testing and measuring equipment and the indication of calibration status on the instruments.
- i) System for indication and appraisal of inspection status.
- j) System of Internal Quality Audits and Management review and initiation of corrective and Preventive actions based on the above.
- k) System for authorising release of manufactured product to the Employer.
- l) System for maintenance of records.
- m) System for handling storage and delivery.
- n) A quality plan detailing out the specific quality control measures and procedure adopted for controlling the quality characteristics relevant to each item of equipment furnished and /or service rendered.
- o) System for various field activities i.e. unloading, receipt at site, proper storage, erection, testing and commissioning of various equipment and maintenance of records". In this regard, the Employer has already prepared Standard Field Quality Plan for Switchyard Civil Works Document Code No. CC/QA&I/SFQP/SS/03/970905/Rev.1 which is required to be followed for associated civil works. Field Quality Plan pertaining to receipt, storage, erection, testing and commissioning shall be mutually discussed and agreed upon before placement of order.

The Employer or his duly authorised representative reserves the right to carry out quality audit and quality surveillance of the system and procedure of the Contractor/his vendor's quality management and control activities.

7.2 Quality Assurance Documents

The Contractor shall be required to submit the following Quality Assurance Documents.

- i) All Non-Destructive Examination procedures, stress relief and weld repair procedure actually used during fabrication, and reports including radiography interpretation reports.
- ii) Welder and welding operator qualification certificates.
- iii) Welder's identification list, listing welder's and welding operator's qualification procedure and welding identification symbols.

- iv) Raw Material test reports on components as specified by the specification and/or agreed to in the quality plan.
- v) The manufacturing Quality Plan indicating Customer Inspection Points (CIPs) at various stages of manufacturing as mutually agreed upon, and methods used to verify that the inspection and testing points in the quality plan were performed satisfactorily.
- vi) Stress relief time temperature charts.
- vii) Factory test results for testing required as per applicable codes/mutually agreed quality plan/standard referred in the specifications.
- viii) Stress relief time temperature charts/oil impregnation time temperature charts.

8.0 INSPECTION, TESTING & INSPECTION CERTIFICATE

- 8.1 The Employer, his duly authorised representative and/or outside inspection agency acting on behalf of the Employer shall have at all reasonable times access to the Contractor's premises or Works and shall have the power at all reasonable times to inspect and examine the materials and workmanship of the Works during its manufacture or erection and if part of the Works is being manufactured or assembled at other premises or works, the Contractor shall obtain for the Employer and for his duly authorised representative permission to inspect as if the works were manufactured or assembled on the Contractor's own premises or works. The equipment if found unsatisfactory as to workmanship or material is liable to be rejected.
- 8.2 The Employer reserves the right to witness any or all type, acceptance and routine tests specified for which at least 30 days notice in advance shall be given by the Contractor. Contractor shall ensure before giving notice for type test that all drawings and quality plans have been got approved. The equipment shall be dispatched to site only after approval of Routine and Acceptance test results and Issuance of Dispatch Clearance in writing by the Employer.
- 8.3 The Contractor shall give the Employer/Inspector Twenty one (21) days written notice of any material being ready for testing for each stage of testing as identified in the approved quality plan as customer inspection point. Such tests shall be to the Contractor's account except for the expenses of the Inspector. The Employer/inspector, unless witnessing of the tests is waived, will attend such tests within Twenty one (21) days of the date of which the equipment is notified as being ready for test/inspection, failing which the Contractor may proceed with the test which shall be deemed to

have been made in the Inspector's presence and he shall forthwith forward to the Inspector six copies of tests, duly certified.

- 8.4 The Employer or Inspector shall, within Twenty (21) days from the date of inspection as defined herein give notice in writing to the Contractor, of any objection to any drawings and all or any equipment and workmanship which in his opinion is not in accordance with the Contract. The Contractor shall give due consideration to such objections and shall either make the modifications that may be necessary to meet the said objections or shall confirm in writing to the Employer/Inspector giving reasons therein, that no modifications are necessary to comply with the Contract.
- 8.5 When the factory tests have been completed at the Contractor's or Sub-Contractor's works, the Employer/Inspector shall issue a certificate to this effect within fifteen (15) days after completion of tests but if the tests are not witnessed by the Employer/Inspector, the certificate shall be issued within fifteen (15) days of receipt of the Contractor's Test certificate by the Employer/Inspector. Failure of the Employer/Inspector to issue such a certificate shall not prevent the Contractor from proceeding with the Works. The completion of these tests or the issue of the certificate shall not bind the Employer to accept the equipment should, it, on further tests after erection, be found not to comply with the Contract.
- 8.6 In all cases where the Contract provides for tests whether at the premises or works of the Contractor or of any Sub- Contractor, the Contractor except where otherwise specified shall provide free of charge such items as labour, materials, electricity, fuel, water, stores, apparatus and instruments as may be reasonably demanded by the Employer/Inspector or his authorised representative to carry out effectively such tests of the equipment in accordance with the Contract and shall give facilities to the Employer/Inspector or to his authorised representative to accomplish testing.
- 8.7 The inspection and acceptance by Employer and issue of Inspection Certificate thereon shall in no way limit the liabilities and responsibilities of the Contractor in respect of the agreed quality assurance programme forming a part of the Contract, or if such equipment is found to be defective at a later stage.
- 8.8 Material Inspection clearance certificate (MICC) shall be issued by the Employer after inspection of the equipment. Employer may waive off the presence of Employer's inspecting engineer. In that case test will be carried out as per approved QP and test certificate will be furnished by the supplier for approval. MICC will be issued only after review and approval of the test reports.
- 8.9 The Employer will have the right of having at his own expenses any other test(s) of reasonable nature carried out at Contractor's premises or at site or

in any other place in addition of aforesaid type and routine tests, to satisfy that the material comply with the specification.

8.10 The Employer reserves the right for getting any field tests conducted on the completely assembled equipment at site.

9.0 ENGINEER'S SUPERVISION

- a) To eliminate delays and avoid disputes and litigation it is agreed between the parties to the Contract that all matters and questions shall be referred to the Engineer and without prejudice to the provision of Section GCC, the contractor shall proceed to comply with the Engineer's decision.
- b) The work shall be performed under the direction and supervision of the Engineer. The scope of the duties of the Engineer, pursuant to the contract, will include but not be limited to the following :
 - i) Interpretation of all the terms and conditions of these documents and specifications ;
 - ii) Review and interpretation of all the Contractor's drawings, engineering data etc. ;
 - iii) Witness or authorise his representative to witness tests and trial either at the manufacturer's works or at site, or at any place where work is performed under the Contract ;
 - iv) Inspect, accept or reject any equipment, material and work under the Contract ;
 - v) Issue certificate of acceptance and/or progressive payment and final payment certificates ;
 - vi) Review and suggest modifications and improvements in completion schedules from time to time ; and
 - vii) Supervise the quality Assurance programme implementation at all stages of the Works.

10.0 TESTS

10.1 Charging

- a) On completion of erection of the equipment and before charging, each item of the equipment shall be thoroughly cleaned and then inspected jointly by the Engineer and the Contractor for correctness and completeness of installation and acceptability for charging,

leading to initial pre-commissioning tests at Site. The list of pre-commissioning tests to be performed are given in Chapt-TST and shall be included in the Contractor's quality assurance programme.

The pre-commissioning checks for various Switchyard Equipment shall be in line with the Pre-Commissioning checklist, Document code no. OS/T&C/BAY/95 (Rev. 0). Further, as regards to pre-commissioning checks for Series Capacitors and the overall system including Series Capacitor and other equipment, protection etc., shall be mutually discussed and agreed upon.

- b) The Contractor's commissioning engineers, specially identified as far as possible, shall be responsible for carrying out all the pre-commissioning tests. On completion of inspection and checking and after the pre-commissioning tests are satisfactorily over, the complete equipment shall be placed on Initial Operation during which period the complete equipment shall be operated integral with sub-systems and supporting equipment as a complete substation.

10.2 Commissioning Tests

- a) The available instrumentation and control equipment will be used during such tests and the Engineer will calibrate, all such measuring equipment and devices as far as practicable. However, unmeasurable parameters shall be taken into account in a reasonable manner by the Engineer, for the requirement of these tests.
- b) Any special equipment, tools and tackles required for the successful completion of the Commissioning Tests shall be provided by the Contractor, free of cost.
- c) The specific tests to be conducted on equipment have been brought out in the Chapter-TST.

10.3 Test Codes

The provisions outlines in the IS & IEC codes or other international and Indian approved equivalents shall generally be used as a guide for all the above test procedures unless otherwise specified in the Technical Specifications.

11.0 HANDLING, STORING AND INSTALLATION

- a) In accordance with the specific installation instructions as shown on manufacturer's drawings or as directed by the Employer or his representative, the Contractor shall unload, store, erect, install, wire, test and place into commercial use all the electrical equipment included in the contract. Equipment shall be installed in a neat,

workmanlike manner so that it is level, plumb, square and properly aligned and oriented. Commercial use of switchyard equipment means completion of all site tests specified and energisation at rated voltage.

- b) Contractor may engage manufacturer's Engineers to supervise the unloading, transportation to site, storing, testing and commissioning of the various equipment being procured by them separately. Contractor shall unload, transport, store, erect, test and commission the equipment as per instructions of the manufacturer's supervisory Engineer(s) and shall extend full cooperation to them.
- c) In case of any doubt/misunderstanding as to the correct interpretation of manufacturer's drawings or instructions, necessary clarifications shall be obtained from the Employer. Contractor shall be held responsible for any damage to the equipment consequent to not following manufacturer's drawings/instructions correctly.
- d) Where assemblies are supplied in more than one section, Contractor shall make all necessary mechanical and electrical connections between sections including the connection between buses. Contractor shall also do necessary adjustments/alignments necessary for proper operation of circuit breakers, isolators and their operating mechanisms. All components shall be protected against damage during unloading, transportation, storage, installation, testing and commissioning. Any equipment damaged due to negligence or carelessness or otherwise shall be replaced by the Contractor at his own expense.
- e) The Contractor shall be fully responsible for the equipment/material until the same is handed over to the Employer in an operating condition after commissioning. Contractor shall be responsible for the maintenance of the equipment/material while in storage as well as after erection until taken over by Employer, as well as protection of the same against theft, element of nature, corrosion, damages etc.
- f) Where material/equipment is unloaded by Employer before the Contractor arrives at site or even when he is at site, Employer by right can hand over the same to Contractor and there upon it will be the responsibility of Contractor to store the material in an orderly and proper manner.
- g) Contractor shall be responsible for the proper storage and maintenance of all materials/equipment entrusted to him. He shall take all required steps to carry out frequent inspection of material/equipment stored as well as erected until the same is taken over by the Employer.

- h) The words 'erection' and 'installation' used in the specification are synonymous.
- i) Exposed live parts shall be placed high enough above ground to meet the requirements of electrical and other statutory safety codes.
- j) Clearances and spacings shall be provided as per relevant IS.

Bidder shall confirm in their technical offer that all clearances and spacing as stated above will invariably be provided. Even though phase to earth clearance under normal conditions will be as above at certain points where there can be bird faults (i.e. a bird sitting on the earthed metal part coming in contact with the HT terminal) adequate clearance as required shall be provided between the HT terminal and nearest grounded metal part.

12.0 TAKING OVER

Upon successful completion of all the tests to be performed at Site on equipment furnished and erected by the Contractor, the Engineer shall issue to the contractor a taking over certificate as a proof of the final acceptance of the equipment. such certificate shall not unreasonably be withheld nor will the Engineer delay the issuance thereof on account of minor omissions or defects which do not affect the commercial operation and/or cause any serious risk to the equipment. Such certificate shall not relieve the Contractor of any of his obligations which otherwise survive, by the terms and conditions of the Contract after issuance of such certificate.

13.0 PROTECTION

All coated surfaces shall be protected against abrasion, impact, discoloration and any other damages. All exposed threaded portions shall be suitably protected with protecting device. All ends of equipment connections shall be properly sealed with suitable devices to protect them from damage. The parts which are likely to get rusted, due to exposure to weather should also be properly treated and protected in a suitable manner.

14.0 PRESERVATIVE SHOP COATING

- 14.1 All exposed metallic surfaces subject to corrosion shall be protected by shop application of suitable coatings. All surfaces which will not be easily accessible after the shop assembly, shall beforehand be treated and protected for the life of the equipment. All surfaces shall be thoroughly cleaned of all mill scale, oxide and other coatings and prepared in the shop. The surfaces that are to be finish painted after installation or require corrosion protection until installation, shall be shop painted with at least two coats of primer. Transformers and other electrical equipment, if included shall be shop finished with one or more coats of primer and two coats of

high grade resistance enamel. The finished colours shall be selected and specified by the Employer at a later date.

14.2 Shop primer for all steel surfaces which will be exposed to operating temperature below 95 deg.C. shall be selected by the Contractor, after obtaining specific approval of the Employer regarding the quality of primer proposed to be applied. Special high temperature primer shall be used on surfaces exposed to temperatures higher than 95 deg.C. and such primers shall also be subject to the approval of the Employer.

14.3 All other steel surfaces which are not to be painted shall be coated with suitable dust preventive compound subject to the approval of the Employer.

15.0 PROTECTIVE GUARDS

Suitable guards shall be provided for protection of personnel on all exposed rotating and/or moving machine parts. All such guards with necessary spares and accessories shall be designed for easy installation and removal for maintenance purpose.

16.0 DESIGN CO-ORDINATION

The Contractor shall be responsible for the selection and design of appropriate equipment to provide the best coordinated performance of the entire system. The basic design requirements are detailed out in this Technical Specification. The design of various components, sub-assemblies and assemblies shall be so done so that it facilitates easy field assembly and maintenance. All the rotating components shall be so selected that the natural frequency of the complete unit is not critical at or close to the operating range of the unit.

17.0 DESIGN CO-ORDINATION MEETING

The Contractor will be called upon to attend design co-ordination meetings with the Employer, other Contractor's and the Consultants of the Employer during the period of Contract. The Contractor shall attend such meetings at his own cost at New Delhi or at mutually agreed venue as and when required and fully cooperate with such persons and agencies involved during those discussions.

18.0 BUS POST INSULATORS

The post insulators shall conform in general to latest IS:2544, IEC-168 and IEC-815.

CONSTRUCTIONAL FEATURES

18.1 Post type insulators shall consist of a porcelain part permanently secured in a

metal base to be mounted on the supporting structures. They shall be capable of being mounted upright. They shall be designed to withstand any shocks to which they may be subjected to by the operation of the associated equipment. Only solid core insulators will be acceptable.

- 18.2 Porcelain used shall be homogeneous, free from lamination, cavities and other flaws or imperfections that might affect the mechanical or dielectric quality and shall be thoroughly vitrified, tough and impervious to moisture.
- 18.3 Glazing of the porcelain shall be of uniform brown in colour, free from blisters, burrs and other similar defects.
- 18.4 The insulator shall have alternate long and short sheds with aerodynamic profile. The shed profile shall also meet the requirements of IEC-815 for the specified pollution level.
- 18.5 When operating at normal rated voltage there shall be no electric discharge between conductor and insulators which would cause corrosion or injury to conductors or insulators by the formation of substance produced by chemical action.
- 18.6 The design of the insulators shall be such that stresses due to expansion and contraction in any part of the insulator shall not lead to deterioration.
- 18.7 All ferrous parts shall be hot dip galvanised in accordance with the latest edition of IS:2633 and IS :4579. The zinc used for galvanising shall be grade Zn 99.95 as per IS:209. The zinc coating shall be uniform, adherent, smooth, reasonably bright, continuous and free from imperfections such as flux, ash, rust stains, bulky white deposits and blisters. The metal parts shall not produce any noise generating corona under the operating conditions.
- 18.8 If corona extinction voltage is to be achieved with the help of corona ring or any other similar device, the same shall be deemed to be included in the scope of the Contractor.

18.9 Tests

The post insulators shall be subject to type, acceptance, sample and routine tests as per IS:2544 and IEC-168.

18.10 TECHNICAL REQUIREMENTS FOR BUS POST INSULATORS

- | | | | |
|----|--|---|------------|
| a) | Type | : | Solid Core |
| b) | Voltage class (kV) | : | 420 |
| c) | Dry & wet one minute power frequency withstand voltage | : | 680 |

	(kV rms)	
d)	Dry lightning impulse withstand voltage (kVp)	: ± 1425
e)	Wet switching surge withstand voltage (kVp)	: ± 1050
f)	Max. radio interference voltage (in microvolts) at voltage of 305 KVrms between phase to ground	: 1000
g)	Corona extinction voltage (kV rms)	320 (Min.)
h)	Total minimum cantilever strength (kg)	800
i)	Minimum torsional moment	As per IEC-273
j)	Total height of insulator (mm)	3650
k)	Pollution level as per IEC-815	Heavy (III)
l)	Minimum total creepage distance for heavy pollution (mm)	10500

19.0 REQUIREMENT OF AUXILIARY ITEMS

19.1 BUSHINGS, HOLLOW COLUMN INSULATORS, SUPPORT INSULATORS

- a) Bushings shall be manufactured and tested in accordance with IS : 2099 & IEC : 137 while hollow column insulators shall be manufactured and tested in accordance with IEC:233/IS: 5621/IEC:61264, as applicable. The support insulators shall be manufactured and tested as per IS:2544/IEC:168 and IS:2099/IEC:273. The insulators shall also conform to IEC:815 as applicable.
- b) Support insulators, bushings and hollow column insulators shall be manufactured from high quality porcelain. Porcelain used shall be homogeneous, free from laminations, cavities and other flaws or imperfections that might affect the mechanical or dielectric quality and shall be thoroughly vitrified tough and impervious to moisture.
- c) Glazing of the porcelain shall be uniform brown in colour, free from blisters, burrs and similar other defects.

- d) Support insulators/bushings/hollow column insulators shall be designed to have ample insulation, mechanical strength and rigidity for the conditions under which they will be used.
- e) When operating at normal rated voltage there shall be no electric discharge between the conductors and bushing which would cause corrosion or injury to conductors, insulators or supports by the formation of substances produced by chemical action. No radio interference shall be caused by the insulators/bushings when operating at the normal rated voltage.
- f) Bushing porcelain shall be robust and capable of withstanding the internal pressures likely to occur in service. The design and location of clamps and the shape and the strength of the porcelain flange securing the bushing to the tank shall be such that there is no risk of fracture. All portions of the assembled porcelain enclosures and supports other than gaskets, which may in any way be exposed to the atmosphere shall be composed of completely non hygroscopic material such as metal or glazed porcelain.
- g) All iron parts shall be hot dip galvanised and all joints shall be air tight. Surface of joints shall be trued up porcelain parts by grinding and metal parts by machining. Insulator/bushing design shall be such as to ensure a uniform compressive pressure on the joints.

h) **TESTS :**

In accordance with the requirements stipulated, bushings, hollow column insulators and support insulators shall conform to type tests and shall be subjected to routine tests in accordance with IS : 2099 & IS : 2544.

i) Parameters of bushings/Hollow column insulators/support insulators :

- | | | | |
|----|--|---|-------------------|
| a) | Rated Voltage | : | 420 kV* |
| b) | Impulse withstand voltage (Dry & Wet) | : | ± 1425 kVp* |
| c) | Switching surge withstand voltage(Dry & Wet) | : | ± 1050 kVp* |
| d) | Power frequency with-stand voltage | : | 630 kVrms* |
| e) | Total creepage distance | : | 25mm/kV* |
| f) | Pollution level | : | Class-III : Heavy |

(as per IEC-71)

- g) Insulator shall also meet requirement of IEC - 815, as applicable, having alternate long & short sheds.

NOTE : * The equipment rating is only indicative. Appropriate rating equipment may be supplied if so required in view of the series capacitor requirement.

19.2 CONTROL PANELS, RELAY PANELS, CABINETS, JUNCTION BOXES, TERMINAL BOXES, MARSHALING BOXES AND MARSHALING KIOSKS:

- a) All types of boxes, cabinet/panels shall generally conform to IS : 5039, IS : 8623, IEC : 439, as applicable and the clauses given below :
- b) Control cabinet/panels, junction boxes, Marshaling box & terminal boxes shall be sheet steel/Al. enclosed and shall be dust, water and vermin proof. Sheet steel used shall be at least 2.0 mm thick cold rolled/2.5 mm hot rolled. The box shall be properly braced to prevent wobbling. There shall be sufficient reinforcement to provide level surfaces, resistance to vibrations and rigidity during transportation and installation. In case of Al. enclosed box the thickness of Al. shall be such that it provides adequate rigidity and long life as comparable with sheet steel of specified thickness.
- c) The enclosures of all outdoor type control cabinets/panel, junction boxes, terminal box & marshaling boxes shall provide a degree of protection of not less than IP 55 as per IS : 13947 and the same for indoor type enclosures shall be IP 31 as per IS : 13947 and one control cabinet/panel, junction box, terminal box & marshaling box of each type shall be tested for the same, if the type test reports submitted are not to the satisfaction of the owner.
- d) Control cabinet/panels, junction boxes, marshaling box & terminal box shall be provided with padlocking arrangements.
- e) All doors, removable covers and plates shall be gasketed all around with neoprene gaskets. The neoprene gasket shall be tested in the presence of Employer's representative.
- f) All sheet steel work shall be degreased, pickled, phosphated and then applied with two coats of zinc chromate primer and two coats of finishing synthetic enamel paint. The colour of finishing paint shall be light admiralty grey in accordance with shade No. 697 of IS : 5 outside and inside shall be glossy white.

- g) All terminal boxes, control cabinet/panels, junction boxes & marshaling boxes shall be designed for the entry of cable from bottom by means of weather proof and dust-proof connections. Boxes and cabinet/panels shall be so designed with generous clearances to avoid interference between the wiring entering from below and any terminal blocks or accessories mounted within the box or cabinet/panel. Suitable cable gland plate on the base of the box shall be provided for this purpose. Necessary number of cable glands of suitable sizes shall be supplied and fitted on this gland plate. This removable gasketed gland plate shall have provision for spare glands to be used in future. The glands shall project at least 25 mm above the gland plate to prevent the entry of moisture in the cable crutch. The roof of the outdoor cabinet/panels/boxes shall preferably be of sloping design to prevent stagnation of water.
- h) Suitable heaters shall be provided in the cabinet/panel, junction boxes & marshaling boxes to prevent condensation. Heaters shall maintain cubicle temperature approximately 10°C above the outside air temperature. The heaters shall be suitable for 240 V AC supply voltage. On-off switch and fuse for this shall be provided.
- i) **Terminal Block :**

All internal wiring to be connected to the external equipment shall terminate on terminal blocks, preferably vertically mounted on the side of cabinet/panel, junction box, terminal box and marshaling box.

The terminal blocks shall be made of moulded, non-inflammable thermosetting plastic. The material of terminal block moulding shall not deteriorate because of varied conditions of heat, cold, humidity, dryness, etc. that would be anticipated at the location where the equipment is proposed to be installed.

The terminal shall be such that maximum contact area is achieved when a cable is terminated. The terminal shall have a locking characteristic to prevent cable from escaping from the terminal clamp unless it is done intentionally. The terminal blocks shall be non-disconnecting stud type equivalent to Elmex type CAT - M4/CST.

The terminal blocks shall be of extensible design.

The terminal blocks shall have locking arrangement to prevent its escape from the mounting rails.

The terminal blocks shall be of **650 V** grade and shall be rated to carry continuously the maximum current that is expected to be carried by the terminals.

The terminal blocks used for CT circuits shall be fully enclosed with removable covers of transparent, non-deteriorating type plastic

material. Insulating barriers shall be provided between the terminal blocks. These barriers shall not hinder the operator from carrying out the wiring without removing the barriers.

The terminals shall be provided with the marking tags for wiring identification.

All boxes shall be provided with 20 % spare terminals unless otherwise specified.

- j) There shall be a minimum clearance of 250 mm between the first row of terminal block and the cable gland plate or side of the box. Also the clearance between two rows of terminal blocks or side of the box shall be a minimum of 150 mm.
- k) The arrangements shall be in such a manner so that it is possible to safely connect or disconnect terminals on live circuits and replace fuse links when the cabinet/panel is live. Cabinet/panel wiring should be suitable for 60°C as the space heaters will keep the temperature 10°C higher than the ambient.

l) **Wiring :**

All wiring shall be carried out with **650 V** grade, stranded copper wires. The minimum size of the stranded conductor used for internal wiring shall be as follows :

i) All circuits except CT circuits – 1.5/ 0.75.00.4 sq.mm (depending on the device current rating)

ii) CT circuits- 4sq mm; minimum no. of strands shall be 3 per conductor.

iii) Wrapping wires shall be used for electronic rack connection.

All internal wiring shall be securely supported, neatly arranged readily accessible and connected to equipment terminals and terminal blocks.

Wire terminations shall be made with solderless crimping type of tinned copper lugs which firmly grip the conductor and insulation. Insulated sleeves shall be provided at all the wire terminations. Engraved core identification plastic ferrules marked to correspond with the wiring diagram shall be fitted at both ends of each wire. Ferrules shall fit tightly on the wires and shall not fall off when the wire is disconnected from terminal blocks.

All wires directly connected to trip circuit breaker shall be distinguished by the addition of a red coloured unlettered ferrule. Number 6 & 9 shall not be included for ferrule purposes.

All terminals including spare terminals of auxiliary equipment shall be

wired upto terminal blocks. Each equipment shall have its own central control cabinet in which all contacts including spare contacts from all poles shall be wired out.

A 240V, single phase, 50 Hz, 15 amp AC plug and socket shall be provided in the cabinet/panel with ON-OFF switch for connection of hand lamps. Plug and socket shall be of industrial grade.

For illumination of Control cabinet/panel a 20 Watts Fluorescent Tube/Incandescent Lamp shall be provided.

All control switches shall be of rotary switch type or push button type and toggle/piano switches shall not be accepted.

In accordance with the requirements stipulated under this Chapter control cabinet/panels, junction boxes, terminal boxes & marshaling boxes shall conform to type tests and shall be subjected to routine tests in accordance with IS : 5039. In addition to the type tests, verification of the degree of protection as per IS : 13947, shall be conducted, if the type test reports submitted by the Contractor are not to the satisfaction of the owner. After protection degree tests on control cabinet/panel, power frequency voltage of 2.0 kV rms for 1 minute shall be applied for checking insulation resistance and functional test shall also be conducted.

m) **Earthing :**

Positive earthing of the cabinet/panel shall be ensured by providing two separate earthing pads. The earth wire shall be terminated on to the earthing pad and secured by the use of star or self etching washers. Earthing of hinged door shall be done by using a separate earth wire.

19.3 MOTORS :

Motors shall be "Squirrel Cage" three phase induction motors of sufficient size capable of satisfactory operation for the application and duty as required for the driven equipment and shall conform to type tests and shall be subjected to routine tests as per applicable standards. The motors shall be of approved make.

19.4 TERMINAL CONNECTORS AND CLAMP CONNECTORS :

The Terminal Connectors of all types shall meet the following requirements:

a) Terminal connectors shall be manufactured and tested as per IS: 5561.

- b) All castings shall be free from blow holes, surface blisters, cracks and cavities. All sharp edges and corners shall be blurred and rounded off.
- c) No part of a clamp shall be less than 10 mm thick.
- d) All ferrous parts shall be hot dip galvanised conforming to IS: 2633.
- e) For bimetallic connectors, copper alloy liner of minimum thickness of 2 mm shall be provided.
- f) Flexible connectors shall be made from tinned copper/aluminium sheets or cables.
- g) All current carrying parts shall be designed and manufactured to have minimum contact resistance.
- h) Connectors shall be designed to be corona free in accordance with the requirements stipulated in IS: 5561.
- i) All test/checks on terminal connectors shall be as per IS: 5561.

19.5 AUXILIARY SWITCH :

The type test reports or the following tests on auxiliary switch shall be furnished :

- a) Electrical endurance test - A minimum of 2000 operations for 2A DC with a time constant greater than or equal to 20 milliseconds with a subsequent examination of mV drop/visual defects/temperature rise test.
- b) Mechanical endurance test - A minimum of 1,00,000 operations with a subsequent checking of contact pressure test/visual examination.
- c) Heat run test on contacts.
- d) IR/HV test etc.

SECTION -IV
GUARANTEED AND TECHNICAL PARTICULARS FOR AUXILIARY TRANSFORMER

S. No.	Parameter	
1	Manufacture's Name & Address	
2	Service	
3	Rated Voltage (i) HV Winding (kV) (ii) LV Winding (kV)	
4	Rated frequency (Hz)	
5	Number of phases	
6	Connections (i)HV Winding (ii)LV Winding	
7	Connections symbol	
8	Type of cooling	
9	Rating available at different cooling (if any) in %	
10	Tap changing equipment (i) Manufacture (ii) Type (iii) No. Of steps	
11	Guaranteed positive sequence impedance at 75 °C with 100 % rating at (i) Principal tap (ii) Maximum tap (iii) Minimum tap	
12	Temperature rise over an ambient of 50 °C (i) Top oil (if applicable °C) (ii) Windings (by resistance measurement method) °C	
13	Guaranteed losses at rated voltage on principal tap and at rated frequency (i) No load loss or iron losses (KW) (ii) Copper loss at full load at 75 °C (KW)	
14	Cooler Data (i) Type of Cooler (ii) Number of Coolers and % of transformer cooling equipment	
15	Withstand time for three phase short circuit at terminals (second)	
16	No load current at rated voltage and rated frequency (A)	
17	Insulation level (a) Separate source power frequency	

	<p>voltage withstand</p> <p>(i) HV Winding (kV rms)</p> <p>(ii) LV Winding (kV rms)</p> <p>(b) Induced over voltage withstanding</p> <p>(i) HV Winding (kV rms)</p> <p>(ii) LV Winding (kV rms)</p> <p>(c) Full wave lighting impulse withstanding</p> <p>(i) HV Winding (kVp)</p> <p>(ii) LV Winding (kVp)</p> <p>(d) Switching impulse withstand voltage</p> <p>(i) HV Winding (kV)</p> <p>(ii) LV Winding (kV)</p>	
18	<p>Regulation at full load at 75 °C</p> <p>(i) At unity power factor (%)</p> <p>(ii) At 0.8 power factor (%)</p>	
19	<p>Terminal arrangement</p> <p>(i) High voltage</p> <p>(ii) Low voltage</p> <p>(iii) LV Neutral</p>	
20	<p>Over excitation withstand time (second)</p> <p>(i) 120 %</p> <p>(ii) 150 %</p>	
21	<p>Bushing</p> <p>(a) High voltage</p> <p>(i) Manufacturer</p> <p>(ii) Type</p> <p>(iii) Minimum Creepage distance (mm)</p> <p>(b) Low voltage</p> <p>(i) Manufacturer</p> <p>(ii) Type</p> <p>(iii) Minimum Creepage distance (mm)</p> <p>(c) LV Neutral</p> <p>(i) Manufacturer</p> <p>(ii) Type</p> <p>(iii) Minimum Creepage distance (mm)</p>	
22	<p>Proposed method of transformer shipment</p>	
23	<p>Total quantity of oil (liters) required for first filling (wherever applicable)</p>	
24	<p>Is vacuum filling required? If so state absolute pressure</p>	
25	<p>Efficiency at 75 °C at Unit power factor</p> <p>(a) At full load (%)</p> <p>(b) At ¾ load (%)</p> <p>(c) At ½ load (%)</p>	
26	<p>Approximate dimensions</p>	

	(a) Tank enclosure LxBxH (mm) (b) Overall LXBXH (mm)	
27	Untaking height (m)	
28	Approximate weight (i) Core and winding (kg) (ii) Tank fittings (kg) (iii) Oil (if applicable) (kg) (iv) Total weight (kg)	
29	Dispatch details (i) Approximate mass of heaviest package (kg) (ii) Approximate dimensions of largest package- (a) Length (mm) (b) Breath (mm) (c) Height (mm)	
30	Reference Standards	
31	Type of Construction (Core Shell)	
32	Thermal time constant (Hours)	
33	Magnetising in rush current (A)	
34	No load current at rated frequency and at (i)90 %voltage (A) (ii) 100 %voltage (A) (iii)110% voltage(A)	
35	Power factor of no load current	
36	Zero sequence impedance at principal tap	
37	Capacitance between winding and to earth(micro farad)	
38	Percentage reactance at rated current and frequency and at (i)Principal tap (ii)Maximum tap (iii)Minimum tap	
39	Off/ON load tap changer details (a) Ratings (i)Rated voltage (ii)Rated current (iii)Step voltage (iv)Number of steps	
40	Radiator (i) Overall dimensions LxBxH (mm) (II) Total weight with oil (kg) (iii) Total weight without oil (kg) (iv) Type of mounting (v) Thickness of Radiator tube	
41	Weight of Transformer (i)Core (kg) (ii)Windings (a) HV (kg)	

	(b) LV (kg) (iii)Insulation(kg) (iv)Tank/enclosure and fittings (kg) (v) Oil) (kg) (vi)Total weight (kg)	
42	Dimensions (i)Tank/enclosure LxBxH (mm) (ii)Overall LxBxH (mm)	
43	Shipping details (i)Weight of heaviest package (kg) (ii)Total shipping weight (kg) (iii)No. of packages (iv) Dimension of largest package LxBxH (mm)	

ANNEXURE - A
SCHEDULE OF TECHNICAL DEVIATIONS

Bidder shall list below all technical deviation clause wise w.r.t. tender specifications:

<u>S.No.</u>	<u>Page No.</u>	<u>Clause No.</u>	<u>Deviation</u>	<u>Reason / Justification</u>
--------------	-----------------	-------------------	------------------	-------------------------------

Any deviation not specifically brought out in this section shall not be admissible for any commercial implication at later stage. Except to the technical deviations listed in this schedule, bidder's offer shall be considered in full compliance to the tender specifications irrespective of any such deviation indicated / taken elsewhere in the submitted offer.

Date:

Tenderer's Stamp & Signature